

Model 750

Code No. 3200-53

STOP

©THE HICKOK ELECTRICAL INSTRUMENT COMPANY, CLEVELAND, OHIO, 1963

PRINTED IN U. S. A.

- Note 1:** A # in the Bias column indicates Bias should be set at 100 and proper button pressed while Bias Dial is rotated until tube strikes.
- Note 2:** For voltage regulator tubes a star ★ in the Notations column identifies the approximate starting voltage and the figure in the Mut. Cond. column represents the nominal operating voltage.
- Note 3:** Set PLATE VOLTS Switch on NORMAL position for all tests that DO NOT have Plate Volts=Low notation.

VOLTAGE REGULATOR TUBES

0A2	OFF	AP-0502-0	---	-----	---	H 150V	★155V REGULATION=2 VOLTS FROM 5 TO 30 MA
0A3/VR75	OFF	AP-0502-0	---	-----	---	H 75V	★100 V REGULATION=5 VOLTS FROM 5 TO 40 MA
0B2	OFF	AP-0502-0	---	-----	---	H 108V	★115 V REGULATION=2 VOLTS FROM 5 TO 30 MA
0B3/VR90	OFF	AP-0502-0	---	-----	---	H 90V	★105 V REGULATION=5 VOLTS FROM 5 TO 30 MA
0C2	OFF	AP-0502-0	---	-----	---	H 75V	★105 V REGULATION=3 VOLTS. FROM 5 TO 30MA.
0C3/VR105	OFF	AP-0502-0	---	-----	---	H 105V	★115 V REGULATION=2 VOLTS FROM 5 TO 40 MA
0D3/VR150	OFF	AP-0502-0	---	-----	---	H 150V	★160 V REGULATION=4 VOLTS FROM 5 TO 40 MA
0E3/85A1	OFF	AP-0208-0	---	-----	---	H 85V	★120V REGULATION=3 VOLTS FROM 1 TO 8 MA
0E3/85A2	OFF	AP-0108-0	---	-----	---	H 85V	★125 V REGULATION=3 VOLTS

0D3/VR150	OFF	AP-0502-0	---	---	---	H 150V	★180 V REGULATION=4 VOLTS FROM 5 TO 40 MA
0E3/85A1	OFF	AP-0208-0	---	---	---	H 85V	★120 V REGULATION=3 VOLTS FROM 1 TO 8 MA
0G3/85A2	OFF	AP-0102-0	---	---	---	H 85V	★125 V REGULATION=3 VOLTS FROM 1 TO 10 MA
90C1	OFF	AP-0507-0	---	---	---	H 90V	★110 V REGULATION=14 VOLTS FROM 1 TO 40 MA.
150B2	OFF	AP-0102-0	---	---	---	H 150V	★160 V REGULATION=5 VOLTS. FROM 5 TO 15 MA.
874	OFF	AP-0301-0	---	---	---	H 90V	★115 V REGULATION=7 VOLTS FROM 10 TO 50 MA
5644	OFF	AP-0102-0	---	---	---	H 95V	★120 V REGULATION=5 VOLTS FROM 5 TO 25 MA
5651	OFF	AP-0107-0	---	---	---	H 87V	★167 V REGULATION=3 VOLTS FROM 1.5 TO 3.5 MA
5783	OFF	AP-0305-0	---	---	---	H 87V	★115 V REGULATION=3 VOLTS FROM 1.5 TO 3.5 MA
5787	OFF	AP-0305-0	---	---	---	H 100V	★130 V REGULATION=8 VOLTS FROM 5 TO 30 MA
6073	OFF	AP-0502-0	---	---	---	H 150V	★155 V REGULATION=2 VOLTS FROM 5 TO 30 MA
6074	OFF	AP-0502-0	---	---	---	H 108V	★115 V REGULATION=1 VOLT FROM 5 TO 30 MA
6213	OFF	AP-0305-0	---	---	---	H 130V	★170 V REGULATION=1 VOLT FROM 1 TO 2.5 MA.
6308	OFF	AP-0301-0	---	---	---	H 87V	★115 V REGULATION=3 VOLTS FROM 1.5 TO 2.5 MA
6332	OFF	AP-0102-0	---	---	---	H 63V	★80 V REGULATION=5 VOLTS FROM 0.2 TO 1.5 MA.
6354	OFF	AP-0102-0	---	---	---	H 150V	★160 V REGULATION=5 VOLTS. FROM 5 TO 15 MA.
6542	OFF	AP-0301-0	---	---	---	H 150V	★185 V REGULATION=6 VOLTS FROM 5 TO 25 MA.
6626	OFF	AP-0502-0	---	---	---	H 150V	★155 V REGULATION=2 VOLTS FROM 5 TO 30 MA
6627	OFF	AP-0502-0	---	---	---	H 108V	★115 V REGULATION=1.5 VOLTS FROM 5 TO 30 MA
0A4	OFF	AP-0572-0	100	B 91	P5	-----	[SHORT ON 2-3 FOR TESTERS HAVING SERIAL NUMBER PREFIX: 149- SHORT ON 1-5 SHORT ON 1-2-5 FOR TESTERS HAVING SERIAL NUMBER PREFIX: 148- PLATE NO. 1. HOLD BUTTON DOWN FOR 5 SECONDS Set Cath. Act. Switch on NORMAL position
0Y4	BLST	HY-3501-0	0	B 45	P2	-----	PLATE NO. 2. HOLD BUTTON DOWN FOR 5 SECONDS Set Cath. Act. Switch on NORMAL position
0Z4	OFF	AP-0508-0	0	B 65	P2	-----	Diode
0Z4	OFF	AP-0308-0	0	B 65	P2	-----	HOLD DOWN P1 AND PRESS P4 PENT. SECT. CAP=G. HOLD DOWN P1 AND PRESS P4 Osc. Sect.
1A3	1.4	HR-0203-0	0	A 0	P1	-----	
1A5	1.4	HS-5340-0	18	B 35	---	C 800	
1A7	1.4	HS-5340-0	0	B 42	---	C 900	
1A7	1.4	HS-5643-0	24	A 15	P4	G 400	
1AC5	1.1	EV-2780-0	20	A 54	P4	G 750	
1AD4	1.1	DV-4120-0	14	B 56	P4	D 1400	Plate Volts=Low
1AD5	1.1	EV-2780-0	0	A 48	P4	G 700	
1AE4	1.1	BX-6230-0	14	B 62	P4	D 1550	
1AF4	1.4	BX-6230-0	17	B 39	P4	D 950	
1AF5	1.4	BX-6540-0	9	A 32	P4	G 600	
1AF5	1.4	BX-0300-0	0	A 0	P1	-----	Pent. Sect. DIODE SECT. OK ABOVE 250 ON 1500 SCALE
1AG4	1.1	DV-4120-0	25	A 65	P4	G 1000	
1AG5	1.1	EW-5120-0	23	A 10	P4	G 375	
1AG5	1.1	EW-0300-0	0	A 0	P1	-----	Pent. Sect. DIODE SECT. OK ABOVE 150 ON 1500 SCALE
1AH4	1.1	ET-4120-0	12	A 51	P4	C 750	

1AF4	1.4	BX-6230-0	17	B	39	P4	D	950	
1AF5	1.4	BX-6540-0	9	A	32	P4	G	600	Pent. Sect.
1AF5	1.4	BX-0300-0	0	A	0	P1	-----	-----	DIODE SECT. OK ABOVE 250 ON 1500 SCALE
1AG4	1.1	DV-4120-0	25	A	65	P4	G	1000	
1AG5	1.1	EW-5120-0	23	A	10	P4	G	375	Pent. Sect.
1AG5	1.1	EW-0300-0	0	A	0	P1	-----	-----	DIODE SECT. OK ABOVE 150 ON 1500 SCALE
1AH4	1.1	FT-4120-0	12	A	51	P4	G	750	
1AJ5	1.1	EW-5120-3	22	A	10	P4	G	425	Pent. Sect.
1AJ5	1.1	EW-0300-0	0	A	40	P1	-----	-----	Diode Sect.
1AK4	1.1	FT-4120-0	12	A	28	P4	G	600	
1AK5	1.1	EW-5120-3	22	A	0	P4	G	280	Pent. Sect.
1AK5	1.1	EW-0300-0	0	A	20	P1	-----	-----	Diode Sect.
1AU2	1.1	EV-0900-0	0	A	81	P5	-----	-----	
1AU3	1.1	HS-0000-0	0	A	53	P5	-----	-----	Cap=P
1AX2	1.4	BS-0000-0	0	A	57	P5	-----	-----	Cap=P
1B3	1.1	HS-0000-0	0	A	80	P5	-----	-----	Cap=P
1B4	2.0	ER-0230-0	15	A	48	P4	G	650	Cap=G
1C3	1.4	BX-4200-0	19	A	55	P4	G	760	
1C5	1.4	HS-5340-0	18	B	66	---	C	1550	
1D5	2.0	HS-0340-0	18	B	31	---	C	750	
1DN5	1.4	BX-6230-0	14	A	43	P4	G	630	Pent. Sect.
1DN5	1.4	HR-0400-0	0	A	0	P1	-----	-----	DIODE SECT. OK ABOVE 500 ON 1500 SCALE
1E3	1.1	EV-1800-0	20	B	83	P4	D	3500	
1G3	1.1	HS-0000-0	0	A	80	P5	-----	-----	Cap=P
1H2	1.4	BS-0000-0	0	A	78	P5	-----	-----	Cap=P
1H5	1.4	HS-0300-0	0	A	0	P4	G	275	TRIODE SECT. CAP=G
1H5	1.4	HS-0500-0	0	A	0	P1	-----	-----	Diode Sect.
1H6	2.0	HS-6300-0	10	A	38	P4	G	575	Triode Sect.
1H6	2.0	HS-6500-0	10	A	40	P1	-----	-----	Diode No. 1
1H6	2.0	HS-6400-0	10	A	40	P1	-----	-----	Diode No. 2
1J3	1.1	HS-0000-0	0	A	53	P5	-----	-----	Cap=P
1K3	1.1	HS-0000-0	0	A	53	P5	-----	-----	Cap=P
1L4	1.4	HR-6230-0	19	B	49	P4	C	1025	
1L6	1.4	BX-6253-4	0	A	56	P4	G	1000	Pent. Sect.
1L6	1.4	BX-4352-6	0	A	18	P4	G	400	Osc. Sect.
1LA4	1.4	JR-6230-0	18	B	35	---	C	800	
1LA6	1.4	JR-6253-4	8	A	58	P4	G	1000	Pent. Sect.
1LA6	1.4	JR-4352-6	0	A	0	P4	G	350	Osc. Sect.
1LB4	1.4	JR-6230-0	18	B	44	---	C	925	
1LC5	1.4	JR-6234-0	13	A	52	P4	G	750	HOLD DOWN P1 AND PRESS P4
1LC6	1.4	JR-6253-4	8	A	58	P4	G	1000	Pent. Sect.
1LC6	1.4	JR-4352-6	19	A	0	P4	G	350	Osc. Sect.
1LD5	1.4	JR-6230-0	14	A	35	P4	G	575	Pent. Sect.
1LD5	1.4	JR-0400-0	0	A	0	P1	-----	-----	Diode Sect.
1LE3	1.4	JR-6200-0	25	B	56	P4	C	1200	
1LF3	1.4	JR-6200-0	25	B	56	P4	C	1200	
1LG5	1.4	JR-6234-0	15	B	50	P4	C	1050	
1LH4	1.4	JR-6200-0	0	A	0	P4	G	275	Triode Sect.
1LH4	1.4	JR-6400-0	0	A	0	P1	-----	-----	Diode Sect.
1LN5	1.4	JR-6234-0	11	B	31	P4	C	750	
1N2	1.1	HS-0000-0	0	A	80	P5	-----	-----	Cap=P
1N5	1.4	HS-0340-0	11	B	31	P4	C	750	Cap=G
1Q5	1.4	HS-5340-0	0	B	73	---	C	2000	HOLD DOWN P1 AND PRESS P4
1Q6	1.1	EV-2780-0	14	A	0	P4	G	400	Pent. Sect.
1Q6	1.1	EV-0600-0	0	A	0	P1	-----	-----	Diode Sect.
1R5	1.4	BX-4306-2	10	B	62	P4	C	1400	Plate Volts=Low
1S2A	1.4	ES-0000-0	0	A	84	P5	-----	-----	Cap=P
1S4	1.4	BX-3240-0	23	B	65	P4	C	1500	Plate Volts=Low
1S5	1.4	BX-6540-0	13	A	40	P4	G	625	Pent. Sect.
1S5	1.4	BX-0340-0	0	A	15	P1	-----	-----	Diode Sect.

1S4	1.4 BX-3240-0	23	B 65	P4	C 1500	Cap=P	Plate Volts=Low
1S5	1.4 BX-6540-0	13	A 40	P4	G 625		Pent. Sect.
1S5	1.4 BX-0340-0	0	A 15	P1	-----		Diode Sect.
1S6	1.1 EV-3180-0	14	A 0	P4	G 400		Pent. Sect.
1S6	1.1 EV-0600-0	0	A 0	P1	-----		Diode Sect.
1T4	1.4 BX-6230-0	0	B 31	P4	C 750		Plate Volts=Low
1T6	1.1 EV-3186-0	14	A 0	P4	G 400		Pent. Sect.
1T6	1.1 EV-0600-0	0	A 0	P1	-----		Diode Sect.
1U4	1.4 BX-6230-0	14	B 42	P4	C 900		
1U5	1.4 BX-6230-0	13	A 40	P4	G 625		Pent. Sect.
1U5	1.4 BX-6430-0	13	A 15	P1	-----		Diode Sect.
1U6	1.4 BX-6253-4	10	A 56	P4	G 1000		Ampl. Sect.
1U6	1.4 BX-4356-2	0	A 0	P4	G 350		Osc. Sect.
1V	6.3 ER-0203-0	0	B 40	P3	-----		
1V2	0.6 EV-0900-0	0	B 65	P5	-----		
1V5	1.1 EV-2780-0	20	A 54	P4	G 750		
1V6	1.1 EX-3120-5	12	A 28	P4	G 500		Pent. Sect.
1V6	1.1 EX-5600-3	27	A 0	P4	G 300		Triode Sect.
1W4	1.4 BX-6230-0	16	A 62	P4	G 925		
1W5	1.1 EV-2780-0	0	A 45	P4	G 735		
1X2	1.1 BS-0000-0	0	A 80	P5	-----	Cap=P	
1Z2	1.4 BS-0000-0	0	A 80	P5	-----	Cap=P	
2A3	2.5 ER-3200-0	74	B 81	P4	D 3000		
2AF4	2.5 ET-2105-0	16	B 88	P4	E 6600		Plate Volts=Low
2B3	1.4 HS-0000-0	0	A 80	P5	-----	Cap=P	
2B7	2.5 HR-0236-0	22	B 48	P4	C 1000		PENT SECT. CAP=B
2B7	2.5 HR-0536-0	22	A 32	P1	-----		Diode No. 1
2B7	2.5 HR-0436-0	22	A 32	P1	-----		Diode No. 2
2B23	6.3 HS-0308-0	0	B 87	P5	-----		
2BN4	2.0 ET-2501-0	16	B 89	P4	E 6800		
2BN4A	2.0 ET-2501-0	16	B 89	P4	E 8000		
2C21	6.3 HR-4506-0	35	B 62	P4	C 1375		Triode No. 1
2C21	6.3 HR-0302-0	35	B 62	P4	C 1375		TRIODE NO. 2
2C39	6.3 HS-6503-0	24	B 87	P4	F20000		CAP=B USE HICKOK ADAPTER CODE NO. 1950 50
2C45	7.5 ER-3200-0	37	B 73	P4	C 2000		
2C50	12.6 HY-1203-0	41	B 70	P4	C 1800		Triode No. 1
2C50	12.6 HY-4506-0	41	B 70	P4	C 1800		Triode No. 2
2C51	6.3 KR-7608-2	16	B 88	P4	E 5000		Triode No. 1
2C51	6.3 KR-3402-8	16	B 88	P4	E 5000		Triode No. 2
2C52	12.6 HY-4506-2	15	B 48	P4	C 1000		Triode No. 1
2C52	12.6 HY-1203-5	15	B 48	P4	C 1000		Triode No. 2
2C53	6.3 HS-5008-0	0	A 0	P4	G 300		Cap=P
2CW4	2.0 DR-4208-0	9	B 87	P4	E 9000		PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO. 1050-127
2CY5	2.5 ET-1562-0	12	B 84	---	D 4000		HOLD DOWN P1 AND PRESS P4
2D21	6.3 ET-1602-5	#	B 95	P5	-----		Strikes at about 26
2DS4	2.0 DR-4208-0	9	B 85	P4	E 7500		PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO. 1050-127
2DZ4	2.5 ET-6105-0	11	B 87	P4	E 7250		Plate Volts=Low
2E22	6.3 FR-3024-0	40	B 75	P4	C 2200		Cap=P
2E24	6.3 HS-5030-0	29	B 81	P4	D 3200		Cap=P
2E25	6.3 HS-5040-8	0	B 79	P4	D 2800		Cap=P
2E26	6.3 HS-5031-8	37	B 84	P4	D 3500		Cap=P
2E30	6.3 ET-1560-2	14	B 81	P4	D 3000		
2E31	1.1 DV-4120-0	18	A 29	P4	G 500		
2E32	1.1 DV-4120-0	18	A 29	P4	G 500		
2E35	1.1 DV-4120-0	20	A 28	P4	G 500		
2E36	1.1 DV-4120-0	20	A 28	P4	G 500		
2E41	1.1 EW-5120-0	23	A 10	P4	G 375		Pent. Sect.
2E41	1.1 EW-0300-0	0	A 0	P1	-----		DIODE SECT. OK ABOVE 150 ON 1500 SCALE
2E42	1.1 EW-5120-0	23	A 10	P4	G 375		Pent. Sect.

2E41	1.1	EW-3120-0	0	A 0	P1	G 375	Pent. Sect.
2E41	1.1	EW-0300-0	0	A 0	P1	-----	DIODE SECT. OK ABOVE 150 ON 1500 SCALE
2E42	1.1	EW-5120-0	23	A 10	P4	G 375	Pent. Sect.
2E42	1.1	EW-0300-0	0	A 0	P1	-----	DIODE SECT. OK ABOVE 150 ON 1500 SCALE
2EA5	2.5	ET-1562-0	12	B 84	P4	E 6000	-----
2EN5	2.0	ET-0705-6	0	A 78	P1	-----	Diode No. 1
2EN5	2.0	ET-0205-6	0	A 78	P1	-----	Diode No. 2
2ER5	2.0	ET-2567-0	11	B 88	P4	E10500	-----
2ES5	2.5	ET-2501-0	10	B 86	P4	E 8650	-----
2EV5	2.5	ET-1562-0	10	B 88	P4	E 8800	-----
2FH5	2.5	ET-2507-0	12	B 88	P4	E 8750	-----
2FO5	2.5	ET-2507-0	13	B 89	P4	E10500	-----
2FQ5A	2.5	ET-2507-0	13	B 90	P4	E12000	-----
2FS5	2.5	ET-1567-0	10	B 84	P4	E 6500	-----
2G21	1.1	EX-3265-1	27	-----	P4	G 250	HEPT. SECT. OK ABOVE 150
2G21	1.1	EX-3100-0	25	A 13	P4	G 400	Triode Sect.
2G22	1.1	EX-3265-1	27	-----	P4	G 250	HEPT. SECT. OK ABOVE 150
2G22	1.1	EX-3100-0	25	A 13	P4	G 400	Triode Sect.
2GK5	2.5	ET-2507-6	13	B 90	P4	F15000	-----
2GU5	2.5	ET-1562-0	10	B 89	P4	E11500	-----
2GW5	2.5	ET-2105-0	19	B 89	P4	D 4600	-----
2HK5	2.5	ET-1502-0	13	B 90	P4	E 4800	-----
2T4	2.5	ET-2105-0	16	B 88	P4	E 6500	Plate Volts=Low
2V2	2.5	HS-0005-0	0	B 68	P5	-----	CAP=P SHORT ON 1
2X2A	2.5	ER-0000-0	0	B 88	P5	-----	Cap=P
3A2	3.0	BS-0000-0	0	B 85	P5	-----	Cap=P
3A3	3.0	HS-0000-0	0	B 75	P5	-----	Cap=P
3A4	2.5	BX-4230-0	11	B 71	----	C 1900	HOLD DOWN P1 AND PRESS P4
3A5	3.0	BX-5600-0	35	B 73	P4	C 2000	Triode No. 1
3A5	3.0	HR-3200-0	35	B 73	P4	C 2000	Triode No. 2
3AF4A	3.0	ET-2105-0	16	B 88	P4	E 6600	Plate Volts=Low
3AL5	3.0	ET-0701-6	0	A 78	P1	-----	Diode No. 1
3AL5	3.0	ET-0205-6	0	A 78	P1	-----	Diode No. 2
3AU6	3.0	ET-1567-2	10	B 78	P4	D 3000	-----
3AV6	3.0	ET-1702-5	14	B 48	P4	D 1250	Triode Sect.
3AV6	3.0	ET-1602-5	14	A 30	P1	-----	Diode No. 1
3AV6	3.0	ET-1502-7	14	A 30	P1	-----	Diode No. 2
3AW3	3.0	HS-0000-0	0	B 75	P5	-----	Cap=P
3B2	3.0	HS-0000-0	0	B 68	P5	-----	Cap=P
3B4	2.5	EV-3710-0	50	B 69	P4	C 1700	-----
3B24	3.0	ER-0000-0	0	B 90	P5	-----	CAP=P. 1ST HALF OF FIL
3B24	3.0	CR-0000-0	0	B 90	P5	-----	CAP=P. 2nd HALF OF FIL
3B26	3.0	HS-0000-0	0	B 92	P5	-----	Cap=P
3B28	3.0	ER-0000-0	0	B 41	P2	-----	Cap=P
3B29	4.3	ER-0000-0	0	B 94	P5	-----	Cap=P
3BA6	3.0	ET-1567-2	0	B 79	P4	D 3200	-----
3BC5	3.0	ET-1562-0	11	B 85	P4	D 4300	-----
3BE6	3.0	ET-7562-1	0	B 35	----	C 800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
3BE6	3.0	ET-1602-7	20	B 88	P4	E 6500	Osc. Sect.
3BN4	3.0	ET-2501-0	16	B 89	P4	E 6800	-----
3BN4A	3.0	ET-2501-0	16	B 89	P4	E 8000	-----
3BN6	3.0	ET-2751-6	0	A 30	P4	G 800	Limiter Grid
3BN6	3.0	ET-6751-2	0	A 40	P4	G 825	Quadrature Grid
3BU8	3.0	EV-7821-9	0	B 15	----	C 600	PENTODE NO. 1 HOLD DOWN P1 AND PRESS P4
3BU8	3.0	EV-7321-6	0	B 15	----	C 600	PENTODE NO. 2 HOLD DOWN P1 AND PRESS P4
3BY6	3.0	ET-1562-7	12	B 56	P4	C 1200	Grid No. 1
3BY6	3.0	ET-7562-1	16	B 0	----	C 500	GRID NO. 3. HOLD DOWN P1 AND PRESS P4
3BZ6	3.0	ET-1562-7	10	B 86	P4	D 4500	-----
3C2	3.0	HS-0000-0	0	A 88	P5	-----	Cap=P
3CA	2.5	BX-6220-0	22	B 61	P4	C 1250	Plate Volts=Low

3BY6	3.0	ET-7562-1	16	B	50	C	500	GRID NO. 3 HOLD DOWN P1 AND PRESS P4
3BZ6	3.0	ET-1562-7	10	B	86	P4	D	4500	
3C2	3.0	HS-0000-0	0	A	88	P5		Cap=P
3C4	2.5	BX-6230-0	23	B	61	P4	C	1350	Plate Volts=Low
3C24	6.3	ER-0000-0	11	B	48	P4	C	1000	G= SIDE PIN P= TOP PIN
3CB6	3.0	ET-1562-7	10	B	86	P4	D	4500	
3CE5	3.0	ET-1562-0	10	B	86	P4	D	4500	
3CF6	3.0	ET-1562-7	10	B	86	P4	D	4500	
3CS6	3.0	ET-1562-7	16	A	22	P4	G	500	Grid No. 1
3CS6	3.0	ET-7562-1	0	A	60	P4	G	1250	Grid No. 3
3CY5	3.0	ET-1562-0	12	B	84	D	4000	HOLD DOWN P1 AND PRESS P4
3D6	2.5	JR-6230-0	16	B	76	D	2400	HOLD DOWN P1 AND PRESS P4
3D21A	12.6	HS-6048-0	32	B	89	P4	D	5200	Cap=P
3DG4	3.0	DR-0700-0	0	A	80	P3		Plate No. 1
3DG4	3.0	DR-0500-0	0	A	80	P3		Plate No. 2
3DK6	3.0	ET-1562-7	10	B	87	P4	E	6500	
3DT6	3.0	ET-1562-7	12	A	20	P4	G	600	Grid No. 1
3DT6	3.0	ET-7562-1	8	A	50	P4	G	500	Grid No. 3
3DZ4	3.0	ET-6105-0	11	B	87	P4	E	7250	Plate Volts=Low
3E5	2.5	BX-6235-0	27	A	70	P4	G	1200	Short on 1
3E6	3.0	JR-6234-0	22	B	62	P4	D	1700	
3EA5	3.0	ET-1562-0	12	B	84	P4	E	6000	
3EH7	3.0	EV-2781-9	16	B	82	P4	D	4350	
3EJ7	3.0	EV-2781-9	10	B	85	P4	E	7750	
3ER5	3.0	ET-2567-0	11	B	88	P4	E	10500	
3EV5	3.0	ET-1562-0	10	B	88	P4	E	8800	
3FH5	3.0	ET-2507-0	12	B	88	P4	E	8750	
3FO5	3.0	ET-2507-0	13	B	89	P4	E	10500	
3FQ5A	3.0	ET-2507-0	13	B	90	P4	E	12000	
3FS5	3.0	ET-1567-0	10	B	84	P4	E	6500	
3GK5	3.0	ET-2507-6	13	B	90	P4	F	15000	
3GS8	3.0	EV-7821-9	0	A	20	G	500	PENT. NO. 1. HOLD DOWN P1 AND PRESS P4
3GS8	3.0	EV-7321-6	0	A	20	G	500	PENT. NO. 2. HOLD DOWN P1 AND PRESS P4
3GU5	3.0	ET-1562-0	10	B	89	P4	E	11500	
3GW5	3.0	ET-2105-0	19	B	89	P4	D	4600	
3HK5	3.0	ET-1502-0	13	B	90	P4	E	4800	
3HM6	3.0	EV-2781-9	11	B	86	P4	E	10000	
3HT6	3.0	EV-2781-9	10	B	86	P4	E	8000	
3JC6	3.0	EV-2781-9	11	B	88	P4	E	11000	
3JD6	3.0	EV-2783-9	10	B	84	E	8500	HOLD DOWN P1 AND PRESS P4
3KF8	3.0	EV-7821-9	10	B	25	P4	C	700	Pent. No. 1
3KF8	3.0	EV-7321-6	10	B	25	P4	C	700	Pent. No. 2
3LE4	2.5	JR-6230-0	55	B	53	P4	C	1100	
3LF4	2.5	JR-6230-0	0	B	73	C	2000	HOLD DOWN P1 AND PRESS P4
3Q4	3.0	HR-3240-0	0	B	70	D	2000	HOLD DOWN P1 AND PRESS P4
3Q5	2.5	HS-5340-0	0	B	73	C	2000	HOLD DOWN P1 AND PRESS P4
3S4	2.5	HR-3240-0	23	B	65	P4	C	1500	Plate Volts=Low
3V4	3.0	HR-6230-0	0	B	70	D	2000	HOLD DOWN P1 AND PRESS P4
4A6	3.0	HS-5600-0	27	B	48	P4	C	1000	Triode No. 1
4A6	3.0	CX-4300-0	27	B	48	P4	C	1000	Triode No. 2
4AU6	4.3	ET-1567-2	10	B	78	P4	D	3000	
4AV6	4.3	ET-1702-5	14	B	48	P4	D	1250	Triode Sect.
4AV6	4.3	ET-0602-0	14	A	30	P1		Diode No. 1
4AV6	4.3	ET-0502-0	14	A	30	P1		Diode No. 2
4BA6	4.3	ET-1567-2	0	B	79	P4	D	3200	
4BC5	4.3	ET-1562-0	11	B	85	P4	D	4300	
4BC8	4.3	EV-7608-9	18	B	88	P4	E	6200	Triode No. 1
4BC8	4.3	EV-2103-9	18	B	88	P4	E	6200	Triode No. 2
4BE6	4.3	EV-7562-1	0	B	25	C	800	AMPL. SECT.

4BE6	4.3	ET-7562-1	0	B 35	P4	C 800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
4BE6	4.3	ET-1602-7	20	B 88	P4	E 6500	Osc. Sect.
4BN6	4.3	ET-2751-6	0	A 30	P4	G 800	Limiter Grid
4BN6	4.3	ET-6751-2	0	A 40	P4	G 825	Quadrature Grid
4BQ7A	4.3	EV-7608-9	15	B 88	P4	E 6400	Triode No. 1
4BQ7A	4.3	EV-2103-9	15	B 88	P4	E 6400	Triode No. 2
4BS8	4.3	EV-7608-9	16	B 89	P4	E 7200	Triode No. 1
4BS8	4.3	EV-2103-9	16	B 89	P4	E 7200	Triode No. 2
4BU8	4.3	EV-7821-9	0	B 15	----	C 600	PENTODE NO. 1 HOLD DOWN P1 AND PRESS P4
4BU8	4.3	EV-7321-6	0	B 15	----	C 600	PENTODE NO. 2 HOLD DOWN P1 AND PRESS P4
4BX8	4.3	EV-7608-9	11	B 85	P4	E 5000	TRIODE NO. 1. PLATE VOLTS=LOW
4BX8	4.3	EV-2103-9	11	B 85	P4	E 5000	TRIODE NO. 2. PLATE VOLTS=LOW
4BZ6	4.3	ET-1562-7	10	B 86	P4	D 4500	
4BZ7	4.3	EV-7608-9	17	B 89	P4	E 6800	Triode No. 1
4BZ7	4.3	EV-2103-9	17	B 89	P4	E 6800	Triode No. 2
4BZ8	4.3	EV-7608-9	14	B 88	P4	E 7000	Triode No. 1
4BZ8	4.3	EV-2103-9	14	B 88	P4	E 7000	Triode No. 2
4CB6	4.3	ET-1562-7	10	B 86	P4	D 4500	
4CE5	4.3	ET-1562-0	10	B 86	P4	D 4500	
4CS6	4.3	ET-1562-7	16	A 22	P4	G 500	Grid No. 1
4CS6	4.3	ET-7562-1	0	A 60	P4	G 1250	Grid No. 3
4CY5	4.3	ET-1562-0	12	B 84	----	D 4000	HOLD DOWN P1 AND PRESS P4
4DE6	4.3	ET-1562-7	10	B 86	P4	D 4500	
4DK6	4.3	ET-1562-7	10	B 87	P4	E 6500	
4DT6	4.3	ET-1562-7	12	A 20	P4	G 600	Grid No. 1
4DT6	4.3	ET-7562-1	8	A 50	P4	G 500	Grid No. 3
4EH7	4.3	EV-2781-9	16	B 82	P4	D 4350	
4EJ7	4.3	EV-2781-9	10	B 85	P4	E 7750	
4ES8	4.3	EV-7608-0	22	B 90	P4	E 7500	Triode No. 1
4ES8	4.3	EV-2103-0	22	B 90	P4	E 7500	Triode No. 2
4EW6	4.3	ET-1562-7	11	B 82	P4	D 5000	
4GK5	4.3	ET-2507-6	13	B 90	P4	F15000	
4GM6	4.3	ET-1562-7	10	B 86	P4	E 9000	
4GS8	4.3	EV-7821-9	0	A 20	----	G 500	PENT. NO. 1. HOLD DOWN P1 AND PRESS P4
4GS8	4.3	EV-7321-6	0	A 20	----	G 500	PENT. NO. 2. HOLD DOWN P1 AND PRESS P4
4GW5	4.3	ET-2105-0	19	B 89	P4	D 4600	
4GZ5	4.3	ET-2761-0	18	B 85	P4	D 5000	
4HK5	4.3	ET-1502-0	14	B 91	P4	E13000	
4HM6	4.3	EV-2781-9	11	B 86	P4	E10000	
4HS8	4.3	EV-7821-9	10	B 21	P4	C 650	Pent. No. 1
4HS8	4.3	EV-7321-6	10	B 21	P4	C 650	Pent. No. 2
4HT6	4.3	EV-2781-9	10	B 86	P4	E 8000	
4JC6	4.3	EV-2781-9	11	B 88	P4	E11000	
4JD6	4.3	EV-2783-9	10	B 84	----	E 8500	HOLD DOWN P1 AND PRESS P4
4KF8	4.3	EV-7821-9	10	B 25	P4	C 700	Pent. No. 1
4KF8	4.3	EV-7321-6	10	B 25	P4	C 700	Pent. No. 2
5A6	5.0	EV-7160-3	25	B 84	P4	D 3600	
5AM8	5.0	EV-2631-9	10	B 82	P4	D 3500	Pent. Sect.
5AM8	5.0	EV-0807-0	0	A 78	P1	-----	Diode Sect.
5AN8	5.0	EV-8679-1	10	B 86	P4	D 4500	Pent. Sect.
5AN8	5.0	EV-2173-6	24	B 83	P4	D 3300	Triode Sect.
5AQ5	5.0	ET-1562-0	18	B 84	P4	D 3700	
5AR4	5.0	JS-0600-0	0	B 68	P3	-----	Plate No. 1
5AR4	5.0	JS-0400-0	0	B 68	P3	-----	Plate No. 2
5AS4	5.0	JS-0600-0	0	B 35	P3	-----	Plate No. 1
5AS4	5.0	JS-0400-0	0	B 30	P3	-----	Plate No. 2
5AS8	5.0	EV-2913-7	10	B 86	P4	D 4500	Pent. Sect.
5AS8	5.0	EV-0608-7	0	A 78	P1	-----	Diode Sect.
5AT8	5.0	EV-9673-8	10	B 86	P4	D 4600	Pent. Sect.
5AT8	5.0	EV-1293-8	15	B 88	P4	E 5800	Triode Sect.

5AS4	5.0	JS-0400-0	0	B	30	P3	-----	Plate No. 2
5AS8	5.0	EV-2913-7	10	B	86	P4	D 4500	Pent. Sect.
5AS8	5.0	EV-0608-7	0	A	78	P1	-----	Diode Sect.
5AT8	5.0	EV-9673-8	10	B	86	P4	D 4600	Pent. Sect.
5AT8	5.0	EV-1203-8	15	B	89	P4	E 5800	Triode Sect.
5AU4	7.5	JS-0600-0	0	B	51	P3	-----	Plate No. 1
5AU4	7.5	JS-0400-0	0	B	45	P3	-----	Plate No. 2
5AV8	5.0	EV-6987-0	10	B	86	P4	D 4500	Pent. Sect.
5AV8	5.0	EV-2301-0	24	B	83	P4	D 3300	Triode Sect.
5AW4	6.3	JS-0600-4	0	B	36	P3	-----	Plate No. 1
5AW4	6.3	JS-0400-6	0	B	31	P3	-----	Plate No. 2
5AZ4	5.0	JS-0600-4	0	A	36	P3	-----	Plate No. 1
5AZ4	5.0	JS-0400-6	0	A	27	P3	-----	Plate No. 2
5B8	5.0	EV-6987-1	15	B	86	P4	D 4500	Pent. Sect.
5B8	5.0	EV-2301-9	24	B	83	P4	D 3300	Triode Sect.
5BC3	5.0	BT-0900-0	0	B	35	P3	-----	PLATE NO. 1, USE HICKOK ADAPTER CODE NO 133-144.
5BC3	5.0	BT-0500-0	0	B	30	P3	-----	Plate No. 2
5BE8	5.0	EV-9678-3	12	B	78	P4	D 3000	Pent. Sect.
5BE8	5.0	EV-1203-0	10	B	89	P4	E 8500	Triode Sect.
5BK7A	5.0	EV-7608-9	10	B	89	P4	E 8500	Triode No. 1
5BK7A	5.0	EV-2103-9	10	B	89	P4	E 8500	Triode No. 2
5BQ7A	5.0	EV-7608-9	15	B	88	P4	E 6400	Triode No. 1
5BQ7A	5.0	EV-2103-9	15	B	88	P4	E 6400	Triode No. 2
5BR8	5.0	EV-9678-0	12	B	78	P4	D 3000	Pent. Sect.
5BR8	5.0	EV-1203-0	10	B	89	P4	E 8500	Triode Sect.
5BS8	5.0	EV-7608-9	16	B	89	P4	E 7200	Triode No. 1
5BS8	5.0	EV-2103-9	16	B	89	P4	E 7200	Triode No. 2
5BT8	5.0	EV-8679-0	10	B	86	P4	D 4500	Pentode Sect.
5BT8	5.0	EV-0103-0	0	A	68	P1	-----	Diode No. 1
5BT8	5.0	EV-0203-0	0	A	68	P1	-----	Diode No. 2
5BW8	5.0	EV-6987-0	12	B	78	P4	D 3000	Pent. Sect.
5BW8	5.0	EV-0302-0	0	A	78	P1	-----	Diode No. 1
5BW8	5.0	EV-0102-0	0	A	78	P1	-----	Diode No. 2
5BZ7	5.0	EV-7608-9	17	B	89	P4	E 6800	Triode No. 1
5BZ7	5.0	EV-2103-9	17	B	89	P4	E 6800	Triode No. 2
5CG8	5.0	EV-9678-0	10	B	86	P4	D 4600	Pent. Sect.
5CG8	5.0	EV-1203-0	15	B	89	P4	E 5800	Triode Sect.
5CL8	5.0	EV-9678-0	10	B	83	P4	D 3500	Tetrode Sect.
5CL8	5.0	EV-1203-0	12	B	89	P4	E 7000	Triode Sect.
5CM6	5.0	EV-3917-0	18	B	84	P4	D 3700	
5CM8	5.0	EV-2673-0	10	B	86	P4	D 4500	Pent. Sect.
5CM8	5.0	EV-9108-0	12	B	65	P4	C 1500	Triode Sect.
5CQ8	5.0	EV-2637-0	10	B	83	P4	D 3400	Tetrode Sect.
5CQ8	5.0	EV-9108-0	11	B	89	P4	E 7000	Triode Sect.
5CR8	5.0	EV-2673-8	10	B	82	P4	D 4150	Pent. Sect.
5CR8	5.0	EV-9108-0	19	B	84	P4	D 4000	Triode Sect.
5CU4	5.0	JS-0601-0	0	B	50	P3	-----	Plate No. 1
5CU4	5.0	JS-0401-0	0	B	50	P3	-----	Plate No. 2
5CZ5	5.0	EV-3917-0	10	B	87	P4	D 4500	
5DH8	5.0	EV-9678-0	10	B	88	P4	D 5000	Pent. Sect.
5DH8	5.0	EV-1203-0	14	B	84	P4	D 3600	Triode Sect.
5DJ4	5.0	JS-0600-0	0	B	35	P3	-----	Plate No. 1
5DJ4	5.0	JS-0400-0	0	B	30	P3	-----	Plate No. 2
5EA8	5.0	EV-2637-0	9	B	79	P4	D 3600	Pent. Sect.
5EA8	5.0	EV-9108-0	10	B	89	P4	E 8500	Triode Sect.
5EH8	5.0	EV-7986-0	7	B	81	P4	D 4400	Pent. Sect.
5EH8	5.0	EV-2301-0	15	B	87	P4	E 7500	Triode Sect.
5ES8	5.0	EV-7608-0	22	B	90	P4	E 7500	Triode No. 1
5ES8	5.0	EV-2103-0	22	B	90	P4	E 7500	Triode No. 2
5EU8	5.0	EV-7198-0	9	B	79	P4	D 3600	Pent. Sect.

5EH8	5.0	EV-2301-0	15	B 87	P4	E 7500	Triode Sect.
5ES8	5.0	EV-7608-0	22	B 90	P4	E 7500	Triode No. 1
5ES8	5.0	EV-2103-0	22	B 90	P4	E 7500	Triode No. 2
5EU8	5.0	EV-7198-0	9	B 79	P4	D 3600	Pent. Sect.
5EU8	5.0	EV-2306-0	10	B 89	P4	E 8500	Triode Sect.
5EW6	5.0	ET-1562-7	11	B 82	P4	D 5000	
5FG7	5.0	EV-9678-0	10	B 82	P4	D 3700	Pent. Sect.
5FG7	5.0	EV-1203-0	14	B 89	P4	E 7500	Triode Sect.
5FV8	5.0	EV-9678-0	10	B 79	P4	D 3500	Pent. Sect.
5FV8	5.0	EV-1203-0	15	B 89	P4	E 7250	Triode Sect.
5GH8	5.0	EV-2637-0	11	B 81	P4	D 4000	Pent. Sect.
5GH8	5.0	EV-9108-0	13	B 88	P4	E 8500	Triode Sect.
5GM6	5.0	ET-1562-7	10	B 86	P4	E 9000	
5GX6	5.0	ET-1562-7	13	B 65	P4	C 1800	
5HG8	5.0	EV-2893-0	10	B 85	P4	E 5000	Pent. Sect.
5HG8	5.0	EV-6703-0	33	B 85	P4	D 2900	Triode Sect.
5J6	5.0	ET-5207-0	17	B 88	P4	E 5300	Triode No. 1
5J6	5.0	ET-6107-0	17	B 88	P4	E 5300	Triode No. 2
5KE8	5.0	EV-2637-0	10	B 85	P4	7800	Pent. Sect.
5KE8	5.0	EV-9108-0	16	B 88	P4	7300	Triode Sect.
5R4	5.0	JS-0600-0	0	B 20	P3	Plate No. 1
5R4	5.0	JS-0400-0	0	B 15	P3	Plate No. 2
5T4	5.0	JS-0600-0	0	B 43	P3	Plate No. 1
5T4	5.0	JS-0400-0	0	B 34	P3	Plate No. 2
5T8	5.0	EV-8907-6	15	B 48	P4	D 1200	Triode Sect.
5T8	5.0	EV-0607-1	0	A 78	P1	Diode No. 1
5T8	5.0	EV-0203-7	0	A 78	P1	Diode No. 2
5T8	5.0	EV-0107-8	0	A 78	P1	Diode No. 3
5U4	5.0	JS-0600-0	0	B 35	P3	Plate No. 1
5U4	5.0	JS-0400-0	0	B 30	P3	Plate No. 2
5U8	5.0	EV-2637-0	12	B 78	P4	D 3000	Pent. Sect.
5U8	5.0	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
5V3	6.3	JS-0600-4	0	B 45	P3	Plate No. 1
5V3	6.3	JS-0400-6	0	B 38	P3	Plate No. 2
5V4	5.0	JS-0600-0	0	B 60	P3	Plate No. 1
5V4	5.0	JS-0400-0	0	B 60	P3	Plate No. 2
5V6	5.0	HS-5348-0	18	B 84	P4	D 3700	
5W4	5.0	JS-0600-0	0	A 38	P3	Plate No. 1
5W4	5.0	JS-0400-0	0	A 32	P3	Plate No. 2
5X4	5.0	HY-0500-0	0	B 35	P3	Plate No. 1
5X4	5.0	HY-0300-0	0	B 30	P3	Plate No. 2
5X8	5.0	EV-7986-1	10	B 86	P4	D 4600	Pent. Sect.
5X8	5.0	EV-2306-1	15	B 89	P4	E 5800	Triode Sect.
5Y3	5.0	JS-0600-0	0	A 36	P3	Plate No. 1
5Y3	5.0	JS-0400-0	0	A 27	P3	Plate No. 2
5Y4	5.0	HY-0500-0	0	A 36	P3	Plate No. 1
5Y4	5.0	HY-0300-0	0	A 27	P3	Plate No. 2
5Z3	5.0	ER-0300-0	0	B 35	P3	Plate No. 1
5Z3	5.0	ER-0200-0	0	B 30	P3	Plate No. 2
5Z4	5.0	JS-0600-0	0	B 57	P3	Plate No. 1
5Z4	5.0	JS-0400-0	0	B 57	P3	Plate No. 2
6A3	6.3	ER-3200-0	74	B 81	P4	D 3000	
6A5	6.3	HS-5300-0	55	B 84	P4	D 3600	
6A6	6.3	HR-5604-0	17	B 65	P4	C 1500	Triode No. 1
6A6	6.3	HR-3204-0	17	B 65	P4	C 1500	Triode No. 2
6A7	6.3	HR-0236-5	0	B 48	P4	C 1000	Pent. Sect. CAP=0
6A7	6.3	HR-5436-2	22	A 0	P4	G 350	PLATE VOLTS-LOW Osc. Sect.
6A8	6.3	HS-0348-5	0	B 48	P4	C 1000	Pent. Sect. CAP=0
6A8	6.3	HS-5648-3	22	A 0	P4	G 350	PLATE VOLTS-LOW Osc. Sect.
6AR4	6.3	ET-6107-0	14	B 85	P4	D 4000	

6A8	6.3	HS-5648-3	22	A	0	P4	D	350	Osc. Sect.
6AB4	6.3	ET-6107-0	14	B	85	P4	D	4000	
6AB7	6.3	HS-4865-3	0	B	84	P4	D	4000	
6AB8	6.3	EV-9683-7	21	B	82	P4	D	3300	Pent. Sect.
6AB8	6.3	EV-2103-0	25	B	61	P4	C	1350	Triode Sect.
6AC5	6.3	HS-5308-0	0	B	48	P4	C	1000	
6AC7	6.3	HS-4865-3	13	B	86	P4	E	6000	
6AD4	6.3	DW-1805-0	20	B	56	P4	C	1200	
6AD7	6.3	HS-5348-6	15	B	73	P4	C	2000	Pent. Sect.
6AD7	6.3	HS-1608-3	0	B	15	P4	C	600	Triode Sect.
6AF3	6.3	EV-0000-0	0	B	50	-----	-----	-----	CAP=P MAKE SHORTS TEST
6AF3	6.3	EV-0002-0	0	B	50	P3	-----	-----	CAP-P, REVERSE METER MAKE NO SHORTS TEST
6AF4	6.3	ET-2105-0	16	B	88	P4	E	6600	Plate Volts=Low
6AF6	6.3	HS-4358-0	0	B	100	P4	-----	-----	EYE 1 OPEN EYE 2 CLOSED
6AF6	6.3	HS-3458-0	0	B	100	P4	-----	-----	EYE 2 OPEN EYE 1 CLOSED
6AG5	6.3	ET-1562-0	10	B	84	P4	D	4000	
6AG7	6.3	HS-4865-1	12	B	89	P4	E	7500	
6AH4	6.3	HS-1508-0	48	B	87	P4	D	4500	
6AH6	6.3	ET-1567-2	13	B	86	P4	E	6000	
6AH7	6.3	HY-5604-3	25	B	72	P4	C	1900	Triode No. 1
6AH7	6.3	HY-1302-6	25	B	72	P4	C	1900	Triode No. 2
6AJ4	6.3	JX-1502-0	16	B	89	P4	E	10000	
6AJ5	6.3	ET-1562-0	13	B	78	P4	D	2500	Plate Volts=Low
6AK4	6.3	DW-1805-7	26	B	86	P4	D	3800	
6AK5	6.3	ET-1562-0	10	B	83	P4	D	4400	
6AK6	6.3	ET-1567-2	17	B	76	P4	C	2300	
6AL5	6.3	ET-0701-6	0	A	78	P1	-----	-----	Diode No. 1
6AL5	6.3	ET-0205-6	0	A	78	P1	-----	-----	Diode No. 2
6AL7	6.3	HS-6358-0	Vary	B	100	P4	-----	-----	BIAS CONTROLS LEFT PATTERN
6AL7	6.3	HS-5348-0	Vary	B	100	P4	-----	-----	BIAS CONTROLS BOTH PATTERNS
6AL7	6.3	HS-4358-0	Vary	B	100	P4	-----	-----	BIAS CONTROLS RIGHT PATTERN
6AM4	6.3	JX-1502-0	11	B	88	P4	E	9000	
6AM8	6.3	EV-2631-9	10	B	82	P4	D	3500	Pent. Sect.
6AM8	6.3	EV-0807-0	0	A	78	P1	-----	-----	Diode Sect.
6AN4	6.3	ET-2105-0	13	B	88	P4	E	7500	
6AN5	6.3	ET-1567-0	7	B	89	-----	E	7000	HOLD DOWN P1 AND PRESS P4
6AN6	6.3	HR-0506-0	0	A	65	P1	-----	-----	Diode No. 1
6AN6	6.3	HR-0406-0	0	A	65	P1	-----	-----	Diode No. 2
6AN6	6.3	HR-0306-0	0	A	65	P1	-----	-----	Diode No. 3
6AN6	6.3	HR-0206-0	0	A	65	P1	-----	-----	Diode No. 4
6AN8	6.3	EV-8679-1	10	B	86	P4	D	4500	Pent. Sect.
6AN8	6.3	EV-2173-6	24	B	83	P4	D	3300	Triode Sect.
6AQ5	6.3	ET-1562-0	18	B	84	P4	D	3700	
6AQ6	6.3	ET-1702-0	15	B	48	P4	D	1200	Triode Sect.
6AQ6	6.3	ET-0602-0	0	A	30	P1	-----	-----	Diode No. 1
6AQ6	6.3	ET-0502-0	0	A	30	P1	-----	-----	Diode No. 2
6AQ7	6.3	HY-4506-0	13	B	59	P4	D	1600	Triode Sect.
6AQ7	6.3	HY-4102-0	0	A	53	P1	-----	-----	Diode No. 1
6AQ7	6.3	HY-4302-0	0	A	53	P1	-----	-----	Diode No. 2
6AR5	6.3	ET-1562-0	17	B	76	P4	D	2400	
6AR6	6.3	GY-7351-0	17	B	86	P4	E	5400	
6AS5	6.3	ET-2761-0	22	B	89	-----	E	5600	HOLD DOWN P1 AND PRESS P4
6AS6	6.3	ET-1562-7	0	B	70	P4	C	1800	
6AS7	7.5	HY-4506-2	55	B	86	P4	D	4000	TRIODE NO. 1 PLATE VOLTS=LOW
6AS7	7.5	HY-1203-5	55	B	86	P4	D	4000	TRIODE NO. 2 PLATE VOLTS=LOW
6AS8	6.3	EV-2913-7	10	B	86	P4	D	4500	Pent. Sect.
6AS8	6.3	EV-0608-7	0	A	78	P1	-----	-----	Diode Sect.
6AT6	6.3	ET-1702-0	15	B	48	P4	D	1200	Triode Sect.
6AT6	6.3	ET-1602-0	15	A	30	P1	-----	-----	Diode No. 1

6AS6	6.3	ET-1562-7	0	B 70	P4	C 1800	
6AS7	7.5	HY-4506-2	55	B 86	P4	D 4000	TRIODE NO. 1 PLATE VOLTS - LOW
6AS7	7.5	HY-1203-5	55	B 86	P4	D 4000	TRIODE NO. 2 PLATE VOLTS - LOW
6AS8	6.3	EV-2913-7	10	B 86	P4	D 4500	Pent. Sect.
6AS8	6.3	EV-0608-7	0	A 78	P1	-----	Diode Sect.
6AT6	6.3	ET-1702-0	15	B 48	P4	D 1200	Triode Sect.
6AT6	6.3	ET-1602-0	15	A 30	P1	-----	Diode No. 1
6AT6	6.3	ET-1502-0	15	A 30	P1	-----	Diode No. 2
6AT8	6.3	EV-9673-8	10	B 86	P4	D 4600	Pent. Sect.
6AT8	6.3	EV-1203-8	15	B 89	P4	E 5800	Triode Sect.
6AU4	6.3	HY-0503-0	0	B 58	P3	-----	
6AU5	6.3	HS-1583-0	18	B 89	P4	E 5600	Plate Volts=Low
6AU6	6.3	ET-1567-2	10	B 78	P4	D 3000	
6AU7	6.3	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
6AU7	6.3	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
6AU8	6.3	EV-7986-0	10	B 88	P4	E 6000	Pent. Sect.
6AU8	6.3	EV-2301-0	13	B 88	P4	E 4900	Triode Sect.
6AV5	6.3	HS-1583-0	28	B 89	P4	E 5500	Plate Volts=Low
6AV6	6.3	ET-1702-5	14	B 48	P4	D 1250	Triode Sect.
6AV6	6.3	ET-1602-5	14	A 30	P1	-----	Diode No. 1
6AV6	6.3	ET-1502-7	14	A 30	P1	-----	Diode No. 2
6AW8	6.3	EV-7986-3	14	B 89	P4	E 7500	Pent. Sect.
6AW8	6.3	EV-2301-9	13	B 83	P4	E 4000	Triode Sect.
6AX4	6.3	HY-0503-0	0	B 40	P3	-----	
6AX5	6.3	HS-0508-3	0	A 40	P3	-----	Plate No. 1
6AX5	6.3	HS-0308-5	0	A 40	P3	-----	Plate No. 2
6AX7	6.3	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
6AX7	6.3	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
6AX8	6.3	EV-2637-0	10	B 78	P4	D 3000	Pent. Sect.
6AX8	6.3	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
6AY3	6.3	ET-0209-0	0	B 48	P3	-----	USE HICKOK ADAPTER CODE NO. 1059-144
6AZ5	6.3	DW-0807-0	0	A 75	P1	-----	Diode No. 1
6AZ5	6.3	DW-0102-0	0	A 75	P1	-----	Diode No. 2
6AZ6	6.3	DW-0204-8	0	A 78	P1	-----	Diode No. 1
6AZ6	6.3	DW-0705-8	0	A 78	P1	-----	Diode No. 2
6AZ8	6.3	EV-6123-0	10	B 84	P4	D 4000	Pent. Sect.
6AZ8	6.3	EV-9807-0	24	B 83	P4	D 3300	Triode Sect.
6B4	6.3	HS-5300-0	74	B 81	P4	D 3000	
6B7	6.3	HR-0236-0	22	B 48	P4	C 1000	PENT. SECT. CAP = G
6B7	6.3	HR-0536-0	22	A 32	P1	-----	Diode No. 1
6B7	6.3	HR-0436-0	22	A 32	P1	-----	Diode No. 2
6BA3	6.3	EV-0709-0	0	B 51	P3	-----	USE HICKOK ADAPTER CODE NO. 1059-144
6BA5	6.3	DW-1578-0	18	B 73	P4	D 2150	
6BA6	6.3	ET-1567-2	0	B 79	P4	D 3200	
6BA7	6.3	EV-7913-2	0	B 31	---	C 750	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
6BA7	6.3	EV-2103-7	16	B 89	P4	E 8000	Osc. Sect.
6BA8	6.3	EV-7986-0	10	B 88	P4	E 6000	Pent. Sect.
6BA8	6.3	EV-2301-0	29	B 79	P4	D 2700	Triode Sect.
6BC4	6.3	EV-2106-0	14	B 89	P4	F10000	
6BC5	6.3	ET-1562-0	11	B 85	P4	D 4300	
6BC7	6.3	EV-0809-0	0	A 82	P1	-----	Diode No. 1
6BC7	6.3	EV-0607-0	0	A 82	P1	-----	Diode No. 2
6BC7	6.3	EV-0201-0	0	A 82	P1	-----	Diode No. 3
6BC8	6.3	EV-7608-9	18	B 88	P4	E 6200	Triode No. 1
6BC8	6.3	EV-2103-9	18	B 88	P4	E 6200	Triode No. 2
6BD4	6.3	HS-0501-0	0	A 25	P1	-----	Cap = P
6BD5	6.3	HS-1583-0	21	B 87	P4	E 5000	
6BD6	6.3	ET-1567-2	10	B 69	P4	D 2000	
6BE6	6.3	ET-7562-1	0	B 35	---	C 800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4

6BD4	6.3	HS-0501-0	0	A 25	P1	Cap=P
6BD5	6.3	HS-1583-0	21	B 87	P4	E 5000	
6BD6	6.3	ET-1567-2	10	B 69	P4	D 2000	
{6BE6	6.3	ET-7562-1	0	B 35	C 800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
{6BE6	6.3	ET-1602-7	20	B 88	P4	E 6500	Osc. Sect.
6BE7	6.3	EV-7163-9	29	B 48	P4	C 1000	
{6BE8	6.3	EV-9678-3	12	B 78	P4	D 3000	Pent. Sect.
{6BE8	6.3	EV-1203-0	10	B 89	P4	E 8500	Triode Sect.
6BF5	6.3	ET-1562-0	20	B 89	E 7500	HOLD DOWN P1 AND PRESS P4
{6BF6	6.3	ET-1702-0	21	B 72	P4	C 1900	Triode Sect.
{6BF6	6.3	ET-1602-0	21	A 30	P1	Diode No. 1
{6BF6	6.3	ET-1502-0	21	A 30	P1	Diode No. 2

**KEEP YOUR TUBE TESTER UP TO DATE WITH
SAVE 28%—**

{6BF7	6.3	DW-7805-0	14	B 87	P4	E 4800	Triode No. 1
{6BF7	6.3	DW-2104-0	14	B 87	P4	E 4800	Triode No. 2
6BF8	6.3	EV-0906-0	0	A 78	P1	Diode No. 1
6BF8	6.3	EV-0806-0	0	A 78	P1	Diode No. 2
6BF8	6.3	EV-0706-0	0	A 78	P1	Diode No. 3
6BF8	6.3	EV-0306-0	0	A 78	P1	Diode No. 4
6BF8	6.3	EV-0206-0	0	A 78	P1	Diode No. 5
6BF8	6.3	EV-0106-0	0	A 78	P1	Diode No. 6
6BG6	6.3	HS-5083-0	18	B 89	P4	E 6000	Cap=P
{6BG7	6.3	DW-7805-0	14	B 87	P4	E 4800	Triode No. 1
{6BG7	6.3	DW-2104-0	14	B 87	P4	E 4800	Triode No. 2
6BH3	6.3	EV-0209-0	0	B 48	P3	USE HICKOK ADAPTER CODE NO. 1050-144
6BH6	6.3	ET-1562-7	10	B 77	P4	D 2800	
{6BH8	6.3	EV-7986-0	8	B 88	P4	E 6000	Pent. Sect.
{6BH8	6.3	EV-2301-0	26	B 83	P4	D 3300	Triode Sect.
6BJ6	6.3	ET-1562-7	10	B 75	P4	C 2500	
6BJ7	6.3	EV-0809-3	0	A 80	P1	Diode No. 1
6BJ7	6.3	EV-0607-3	0	A 80	P1	Diode No. 2
6BJ7	6.3	EV-0201-3	0	A 80	P1	Diode No. 3
6BJ8	6.3	EV-8709-0	26	B 80	P4	D 2800	Triode Sect.
{6BJ8	6.3	EV-0603-0	0	A 78	P1	Diode No. 1
{6BJ8	6.3	EV-0102-0	0	A 78	P1	Diode No. 2
6BK5	6.3	EV-3186-0	0	B 89	P4	E 7500	
6BK6	6.3	ET-1702-5	14	B 48	P4	D 1250	Triode Sect.
6BK6	6.3	ET-0602-5	0	A 53	P1	Diode No. 1
6BK6	6.3	ET-0502-7	0	A 53	P1	Diode No. 2
6BK7	6.3	EV-7608-9	10	B 89	P4	E 8500	Triode No. 1
6BK7	6.3	EV-2103-9	10	B 89	P4	E 8500	Triode No. 2
6BL4	6.3	HY-0503-0	0	B 62	P3	
{6BL7	6.3	HY-4506-0	23	B 89	P4	E 7000	Triode No. 1
{6BL7	6.3	HY-1203-0	23	B 89	P4	E 7000	Triode No. 2
{6BM8	6.3	EV-3672-0	26	B 84	P4	D 4000	Pent. Sect.
{6BM8	6.3	EV-1908-0	0	B 73	P4	C 2500	Triode Sect.
6BN4	6.3	ET-2501-0	16	B 89	P4	E 6800	
6BN4A	6.3	ET-2501-0	16	B 89	P4	E 8000	
{6BN6	6.3	ET-2751-6	0	A 30	P4	G 800	Limiter Grid
{6BN6	6.3	ET-6751-2	0	A 40	P4	G 825	Quadrature Grid
{6BN8	6.3	EV-8709-0	15	B 78	P4	D 2500	Triode Sect.
{6BN8	6.3	EV-0603-0	0	A 78	P1	Diode No. 1
{6BN8	6.3	EV-0102-0	0	A 78	P1	Diode No. 2
6BQ5	6.3	EV-2793-0	14	B 89	P4	E 7500	
6BQ6	6.3	HS-5048-0	28	B 89	P4	E 5500	CAP=P. PLATE VOLTS=LOW
6BQZA	6.3	EV-7608-9	15	B 88	P4	E 6400	Triode No. 1

6BN8	6.3	EV-0102-0	0	A 78	P1	-----	Diode No. 2
6BQ5	6.3	EV-2793-0	14	B 89	P4	E 7500	CAP=P PLATE VOLTS=LOW
6BQ6	6.3	HS-5048-0	28	B 89	P4	E 5500	Triode No. 1
6BQ7A	6.3	EV-7608-9	15	B 88	P4	E 6400	Triode No. 2
6BQ7A	6.3	EV-2103-9	15	B 88	P4	E 6400	Pent. Sect.
6BR8	6.3	EV-9678-0	12	B 78	P4	D 3000	Triode Sect.
6BR8	6.3	EV-1203-0	10	B 89	P4	E 8500	USE HICKOK ADAPTER CODE NO. 139-144
6BS3	6.3	EV-0209-0	0	A 50	P3	-----	Triode No. 1
6BS8	6.3	EV-7608-9	16	B 89	P4	E 7200	Triode No. 2
6BS8	6.3	EV-2103-9	16	B 89	P4	E 7200	Triode Sect.
6BT6	6.3	ET-1702-0	15	B 48	P4	D 1200	Diode No. 1
6BT6	6.3	ET-1602-0	15	A 53	P1	-----	Diode No. 2
6BT6	6.3	ET-1502-0	15	A 53	P1	-----	Pentode Sect.
6BT8	6.3	EV-8679-0	10	B 86	P4	D 4500	Diode No. 1
6BT8	6.3	EV-0103-0	0	A 68	P1	-----	Diode No. 2
6BT8	6.3	EV-0203-0	0	A 68	P1	-----	Triode Sect.
6BU6	6.3	ET-1702-0	21	B 72	P4	C 1900	Diode No. 1
6BU6	6.3	ET-1602-0	21	A 53	P1	-----	Diode No. 2
6BU6	6.3	ET-1502-0	21	A 53	P1	-----	PENT. NO. 1 HOLD DOWN P1 AND PRESS P4
6BU8	6.3	EV-7821-9	0	B 15	---	C 600	PENT. NO. 2 HOLD DOWN P1 AND PRESS P4
6BU8	6.3	EV-7321-6	0	B 15	---	C 600	Triode Sect.
6BV8	6.3	EV-2301-0	19	B 89	P4	E 5600	Diode No. 1
6BV8	6.3	EV-0907-0	0	A 78	P1	-----	Diode No. 2
6BV8	6.3	EV-0608-0	0	A 78	P1	-----	Plate No. 1
6BW4	6.3	EV-0709-1	0	A 40	P3	-----	Plate No. 2
6BW4	6.3	EV-0109-7	0	A 40	P3	-----	Pent. Sect.
6BW8	6.3	EV-6987-0	12	B 78	P4	D 3000	Diode No. 1
6BW8	6.3	EV-0302-0	0	A 78	P1	-----	Diode No. 2
6BW8	6.3	EV-0102-0	0	A 78	P1	-----	Triode No. 1
6BX6	6.3	EV-2781-9	10	B 87	P4	E 6500	Triode No. 2
6BX7	6.3	HY-4506-2	35	B 89	P4	E 7600	Triode No. 1
6BX7	6.3	HY-1203-5	35	B 89	P4	E 7600	TRIODE NO. 1 PLATE VOLTS=LOW
6BX8	6.3	EV-7608-9	11	B 85	P4	E 5000	TRIODE NO. 2 PLATE VOLTS=LOW
6BX8	6.3	EV-2103-9	11	B 85	P4	E 5000	Plate No. 1
6BY5	6.3	HS-0508-0	0	B 38	P3	-----	Plate No. 2
6BY5	6.3	HS-0401-0	0	B 38	P3	-----	Grid No. 1
6BY6	6.3	ET-1562-7	12	B 56	P4	C 1200	GRID NO. 3. HOLD DOWN P1 AND PRESS P4
6BY6	6.3	ET-7562-1	16	B 0	---	C 500	Pent. Sect.
6BY8	6.3	EV-1789-2	10	B 78	P4	D 3000	Diode Sect.
6BY8	6.3	EV-0603-0	0	A 78	P1	-----	Triode No. 1
6BZ6	6.3	ET-1562-7	10	B 86	P4	D 4500	Triode No. 2
6BZ7	6.3	EV-7608-9	17	B 89	P4	E 6800	Triode No. 1
6BZ7	6.3	EV-2103-9	17	B 89	P4	E 6800	Triode No. 2
6BZ8	6.3	EV-7608-9	14	B 88	P4	E 7000	Triode No. 1
6BZ8	6.3	EV-2103-9	14	B 88	P4	E 7000	Triode No. 2
6C4	6.3	ET-6107-0	25	B 75	P4	C 2200	
6C5	6.3	HS-5308-0	21	B 73	P4	C 2000	
6C6	6.3	GR-0235-4	21	B 57	P4	C 1225	Cap=G
6CA4	6.3	EV-0703-0	0	B 42	P3	-----	Plate No. 1
6CA4	6.3	EV-0103-0	0	B 42	P3	-----	Plate No. 2
6CA5	6.3	DU-2761-0	0	B 88	P4	E 7000	Plate Volts=Low
6CA7	6.3	HS-5348-1	23	B 88	P4	E 6000	
6CB5	7.5	HS-4013-0	40	B 89	P4	E 7000	Cap=P
6CB6	6.3	ET-1562-7	10	B 86	P4	D 4500	
6CD6	6.3	HS-5083-0	29	B 88	P4	E 6000	CAP=P PLATE VOLTS=LOW
6CE5	6.3	ET-1562-0	10	B 86	P4	D 4500	
6CF6	6.3	ET-1562-7	10	B 86	P4	D 4500	
6CG7	6.3	EV-7608-9	23	B 79	P4	D 2600	Triode No. 1
6CG7	6.3	EV-2103-9	23	B 79	P4	D 2600	Triode No. 2
6CG8	6.3	EV-9678-0	10	B 86	P4	D 4600	Pent. Sect.

6CD6	6.3	HS-5083-0	29	B 88	P4	E 6000	CAP=P PLATE VOLTS=LOW
6CE5	6.3	ET-1562-0	10	B 86	P4	D 4500	
6CF6	6.3	ET-1562-7	10	B 86	P4	D 4500	
6CG7	6.3	EV-7608-9	23	B 79	P4	D 2600	Triode No. 1
6CG7	6.3	EV-2103-9	23	B 79	P4	D 2600	Triode No. 2
6CG8	6.3	EV-9678-0	10	B 86	P4	D 4600	Pent. Sect.
6CG8	6.3	EV-1203-0	15	B 89	P4	E 5800	Triode Sect.
6CH7	6.3	EV-7608-0	17	B 89	P4	E 6800	Triode No. 1
6CH7	6.3	EV-2103-0	17	B 89	P4	E 6800	Triode No. 2
6CH8	6.3	EV-7236-0	10	B 86	P4	D 4500	PENTODE SECT DISREGARD NEON FLASH IN SHORT TESTING ON TESTERS HAVING SERIAL NUMBER PREFIX 149.
6CH8	6.3	EV-8901-0	24	B 83	P4	D 3300	Triode Sect.
6CJ6	6.3	EV-2073-1	51	B 87	P4	E 4600	Cap=P
6CK4	6.3	HS-1508-0	46	B 89	P4	D 5500	
6CK6	6.3	EV-2713-6	0	B 89	P4	E 9000	
6CL5	6.3	HS-4013-0	46	B 92	P4	D 4600	Cap=P
6CL6	6.3	EV-2631-7	12	B 89	P4	E 7500	
6CL8	6.3	EV-9678-0	10	B 83	P4	D 3500	Tetrode Sect.
6CL8	6.3	EV-1203-0	12	B 89	P4	E 7000	Triode Sect.
6CM6	6.3	EV-3917-0	18	B 84	P4	D 3700	
6CM7	6.3	EV-7603-0	27	B 73	P4	D 2000	Triode No. 1
6CM7	6.3	EV-8109-0	23	B 88	P4	E 4400	Triode No. 2
6CM8	6.3	EV-2673-0	10	B 86	P4	D 4500	Pent. Sect.
6CM8	6.3	EV-9108-0	12	B 65	P4	C 1500	Triode Sect.
6CN7	6.3	EV-7806-0	15	B 48	P4	D 1200	Triode Sect.
6CN7	6.3	EV-0203-0	0	A 78	P1	-----	Diode No. 1
6CN7	6.3	EV-0103-0	0	A 78	P1	-----	Diode No. 2
6CQ4	6.3	HY-0503-0	0	B 49	P3	-----	
6CQ8	6.3	EV-2637-0	10	B 83	P4	D 3400	Tetrode Sect.
6CQ8	6.3	EV-9108-0	11	B 89	P4	E 7000	Triode Sect.
6CR6	6.3	ET-7561-2	13	B 70	P4	D 1950	Pent. Sect.
6CR6	6.3	ET-0201-0	0	A 30	P1	-----	Diode Sect.
6CR8	6.3	EV-2673-8	10	B 82	P4	D 4150	Pent. Sect.
6CR8	6.3	EV-9108-0	19	B 84	P4	D 4000	Triode Sect.
6CS6	6.3	ET-1562-7	16	A 22	P4	G 500	Grid No. 1
6CS6	6.3	ET-7562-1	0	A 60	P4	G 1250	Grid No. 3
6CS7	6.3	EV-7608-0	22	B 75	P4	D 2200	Triode No. 1
6CS7	6.3	EV-3109-0	26	B 88	P4	E 4500	Triode No. 2
6CU5	6.3	ET-2761-0	22	B 88	-----	E 6000	HOLD DOWN P1 AND PRESS P4
6CU6	6.3	HS-5048-0	28	B 89	P4	E 5500	CAP=P. PLATE VOLTS=LOW
6CU8	6.3	EV-7236-1	10	B 86	P4	D 4500	Pent. Sect.
6CU8	6.3	EV-8901-0	24	B 83	P4	D 3300	Triode Sect.
6CW4	6.3	DR-4208-0	9	B 87	P4	E 9000	PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO. 1150-127
6CW5	6.3	EV-2793-0	16	B 89	P4	E 7500	
6CX8	6.3	EV-7986-0	11	B 89	P4	E 6500	Pent. Sect.
6CX8	6.3	EV-2301-0	13	B 87	P4	D 4400	Triode Sect.
6CY5	6.3	ET-1562-0	12	B 84	-----	D 4000	HOLD DOWN P1 AND PRESS P4
6CY7	6.3	EV-7608-0	13	B 53	P4	D 1300	Triode No. 1
6CY7	6.3	EV-2109-0	60	B 86	P4	D 4000	Triode No. 2
6CZ5	6.3	EV-3917-0	10	B 87	P4	D 4500	
6D4	6.3	ET-1705-0	#	B 96	P5	-----	Strikes at about 67
6D6	6.3	GR-0235-4	17	B 67	P4	C 1600	Cap=G
6DA4	6.3	HY-0503-0	0	B 40	P3	-----	
6DA5	6.3	EV-1902-0	Vary	B 100	P5	-----	Connect a 1 megohm resistor from Plate jack to octal test socket pin No. 7. Vary Bias to vary beam angle.
6DA6	6.3	EV-2783-9	12	B 80	P4	D 3000	
6DA7	6.3	EV-7608-0	23	B 79	P4	D 2600	Triode No. 1
6DA7	6.3	EV-3109-0	55	B 87	P4	E 4700	Triode No. 2

Vary Bias to vary beam angle.

6DA6	6.3	EV-2783-9	12	B 80	P4	D 3000	
6DA7	6.3	EV-7608-0	23	B 79	P4	D 2600	Triode No. 1
6DA7	6.3	EV-3109-0	55	B 87	P4	E 4700	Triode No. 2
6DB5	6.3	EV-3912-0	25	B 90	----	E 6000	HOLD DOWN P1 AND PRESS P4
6DB6	6.3	ET-1562-7	12	B 72	P4	D 2050	Grid No. 1
6DB6	6.3	ET-7562-1	17	B 48	-----	C 1000	GRID NO. 3. HOLD DOWN P1 AND PRESS P4
6DC6	6.3	ET-1562-7	10	B 85	P4	D 4000	
6DE4	6.3	HY-0503-0	0	B 49	P3	-----	
6DE6	6.3	ET-1562-7	10	B 86	P4	D 4500	
6DE7	6.3	EV-7608-0	30	B 73	P4	C 2000	Triode No. 1
6DE7	6.3	EV-2109-0	55	B 88	P4	D 5000	Triode No. 2
6DG6	6.3	HS-5348-0	25	B 89	-----	E 6000	HOLD DOWN P1 AND PRESS P4
6DJ8	6.3	EV-7608-0	20	B 91	P4	E12500	Triode No. 1
6DJ8	6.3	EV-2103-0	20	B 91	P4	E12500	Triode No. 2
6DK6	6.3	ET-1562-7	10	B 87	P4	E 6500	
6DM4	6.3	HY-0503-0	0	B 49	P3	-----	
6DN6	6.3	HS-5083-0	28	B 89	-----	E 9000	CAP=P. HOLD DOWN P1 AND PRESS P4
6DN7	6.3	HY-4506-0	24	B 73	P4	C 2000	Triode No. 1
6DN7	6.3	HY-1203-0	22	B 89	P4	E 7500	Triode No. 2
6DQ4	6.3	JX-0503-0	0	B 43	P3	-----	
6DQ5	6.3	HS-1043-0	60	B 90	P4	D 4000	Cap=P
6DQ6	6.3	HS-5048-0	36	B 87	-----	E 5000	CAP=P. HOLD DOWN P1 AND PRESS P4
6DR4	6.3	ET-6507-0	14	B 48	P4	D 1250	
6DR7	6.3	EV-7608-0	13	B 57	P4	C 1250	Triode No. 1
6DR7	6.3	EV-2109-0	55	B 89	P4	D 5400	Triode No. 2
6DS4	6.3	DR-4208-0	9	B 85	P4	E 7500	PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO. 1050-127
6DS5	6.3	ET-1562-0	14	B 88	P4	E 6000	
6DT4	6.3	HY-0503-0	0	A 68	P3	-----	
6DT5	6.3	EV-3917-0	22	B 88	P4	E 5100	
6DT6	6.3	ET-1562-7	12	A 20	P4	G 600	Grid No. 1
6DT6	6.3	ET-7562-1	8	A 50	P4	G 500	Grid No. 3
6DT8	6.3	EV-7608-9	14	B 85	P4	D 4000	Triode No. 1
6DT8	6.3	EV-2103-9	14	B 85	P4	D 4000	Triode No. 2
6DW4	6.3	EV-0709-0	0	B 54	P3	-----	USE HICKOK ADAPTER CODE NO. 1050-144
6DW5	6.3	EV-3917-0	28	B 89	P4	E 5500	Plate Volts=Low
6DZ4	6.3	ET-6105-0	11	B 87	P4	E 7250	Plate Volts=Low
6DZ8	6.3	EV-3672-0	25	B 87	P4	D 4600	Pent. Sect.
6DZ8	6.3	EV-1908-0	17	B 34	P4	C 850	Triode Sect.
6E5	6.3	GR-5403-0	0	B100	P4	-----	Eye Open
6E5	6.3	GR-5423-0	0	B100	P4	-----	Eye Closed
6EA5	6.3	ET-1562-0	12	B 84	P4	E 6000	
6EA7	6.3	JX-4506-0	10	B 67	P4	C 1800	Triode No. 1
6EA7	6.3	JX-1203-0	53	B 91	P4	E 6500	Triode No. 2
6EA8	6.3	EV-2637-0	9	B 79	P4	D 3600	Pent. Sect.
6EA8	6.3	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
6EB5	6.3	ET-0205-6	0	A 70	P1	-----	Diode No. 1
6EB5	6.3	ET-0701-6	0	A 70	P1	-----	Diode No. 2
6EB8	6.3	EV-7986-0	0	B 88	P4	E10,000	Pent. Sect.
6EB8	6.3	EV-2301-0	10	B 72	P4	C 2000	Triode Sect.
6EH5	6.3	ET-2761-0	13	B 88	P4	E 7200	
6EH7	6.3	EV-2781-9	16	B 82	P4	D 4350	
6EH8	6.3	EV-7986-0	7	B 81	P4	D 4400	Pent. Sect.
6EH8	6.3	EV-2301-0	15	B 87	P4	E 7500	Triode Sect.
6EJ7	6.3	EV-2781-9	10	B 85	P4	E 7750	
6EM5	6.3	EV-3917-0	16	B 88	P4	E 5100	
6EM7	6.3	HY-4506-0	13	B 66	P4	C 1600	Triode No. 1
6EM7	6.3	HY-1203-0	60	B 89	P4	E 6650	Triode No. 2
6EM7	6.3	HY-2783-1	20	B 89	P4	E 4300	Pent. Sect.

6EM7	6.3	HY-4506-0	13	B 66	P4	C 1600	Triode No. 1
6EM7	6.3	HY-1203-0	60	B 89	P4	E 6650	Triode No. 2
6EQ7	6.3	EV-2763-1	20	B 44	P4	C 1300	Pent. Sect.
6EQ7	6.3	EV-0803-0	0	A 30	P1	Diode Sect.
6ER5	6.3	ET-2567-0	11	B 88	P4	E10500	
6ES5	6.3	ET-2501-0	10	B 86	P4	E 8650	
6ES8	6.3	EV-7608-0	22	B 90	P4	E 7500	Triode No. 1
6ES8	6.3	EV-2103-0	22	B 90	P4	E 7500	Triode No. 2
6ET7	6.3	EV-7986-0	11	B 88	P4	E 8000	Pent. Sect.
6ET7	6.3	EV-0301-0	0	A 18	P1	Diode No. 1
6ET7	6.3	EV-0201-0	0	A 18	P1	Diode No. 2
6EU7	6.3	BS-8709-0	14	B 48	P4	D 1250	Triode No. 1
6EU7	6.3	BS-5604-0	14	B 48	P4	D 1250	Triode No. 2
6EU8	6.3	EV-7198-0	9	B 79	P4	D 3600	Pent. Sect.
6EU8	6.3	EV-2306-0	10	B 89	P4	E 8500	Triode Sect.
6EV5	6.3	ET-1562-0	10	B 88	P4	E 8800	
6EV7	6.3	EV-7608-0	10	B 83	P4	E 5800	Triode No. 1
6EV7	6.3	EV-2103-0	10	B 83	P4	E 5800	Triode No. 2
6EW6	6.3	ET-1562-7	11	B 82	P4	D 5000	
6EW7	6.3	EV-7608-0	34	B 69	P4	C 1700	Triode No. 1
6EW7	6.3	EV-2109-0	61	B 91	P4	E 7500	Triode No. 2
6EX6	6.3	HS-5083-0	53	B 90	P4	E 5500	Cap=P

Tubes indicating shorts: Re-test using HS-5013-0

6EY6	6.3	HS-5348-0	29	B 86	P4	D 4400	
6EZ5	6.3	HS-5348-0	47	B 74	P4	C 2000	
6EZ8	6.3	FU-9800-0	25	B 79	P4	D 3200	Triode No. 1
6EZ8	6.3	FU-7600-0	25	B 79	P4	D 3200	Triode No. 2
6EZ8	6.3	FU-2301-0	15	B 79	P4	D 3200	Triode No. 3
6F4	6.3	GR-2307-0	18	B 89	P4	E 6000	Plate Volts=Low
6F5	6.3	HS-0408-1	12	B 57	P4	D 1500	Cap=G
6F6	6.3	HS-5348-1	23	B 70	P4	C 2000	
6F7	6.3	HR-0236-5	18	B 53	P4	C 1100	PENT. SECT. CAP=G
6F7	6.3	HR-5406-3	35	B 0	P4	C 500	Triode Sect.
6F8	6.3	HS-5608-0	23	B 79	P4	D 2600	Triode No. 1
6F8	6.3	HS-0304-0	23	B 79	P4	D 2600	TRIODE NO 2 CAP=G
6FA7	6.3	EV-7986-1	10	B 61	P4	C 1350	Tetrode No. 1
6FA7	6.3	EV-7186-9	10	B 61	P4	C 1350	Tetrode No. 2
6FA7	6.3	EV-9306-1	0	A 30	P1	Diode Sect.
6FD6	6.3	ET-1657-2	18	A 42	P1	
6FD7	6.3	EV-7608-0	12	B 66	P4	C 1600	Triode No. 1
6FD7	6.3	EV-2109-0	59	B 89	P4	E 7500	Triode No. 2
6FE5	6.3	HS-5348-0	30	B 93	P4	E 6300	
6FG5	6.3	ET-1567-0	10	B 80	P4	D 3600	
6FG7	6.3	EV-9678-0	10	B 82	P4	D 3700	Pent. Sect.
6FG7	6.3	EV-1203-0	14	B 89	P4	E 7500	Triode Sect.
6FH5	6.3	ET-2507-0	12	B 88	P4	E 8750	
6FH6	6.3	HS-5048-0	36	B 87	E 5000	CAP=P HOLD DOWN P1 AND PRESS P4
6FH8	6.3	FU-6970-0	28	B 66	P4	D 2500	TETRODE PLATE NO. 1
6FH8	6.3	FU-6870-0	25	B 50	P4	C 1300	TETRODE PLATE NO. 2
6FH8	6.3	FU-6170-0	25	B 50	P4	C 1300	TETRODE PLATE NO. 3
6FH8	6.3	FU-2300-0	32	B 75	P4	E 5400	Triode Sect.
6FM8	6.3	EV-8907-0	15	B 48	P4	D 1200	Triode Sect.
6FM8	6.3	EV-0601-0	0	A 78	P1	Diode No. 1
6FM8	6.3	EV-0203-0	0	A 78	P1	Diode No. 2
6FQ5	6.3	ET-2507-0	13	B 89	P4	E10500	
6FQ5A	6.3	ET-2507-0	13	B 90	P4	E12000	
6FQ7	6.3	EV-7608-0	23	B 79	P4	D 2600	Triode No. 1
6FQ7	6.3	EV-2103-0	23	B 79	P4	D 2600	Triode No. 2
6FR7	6.3	EV-7608-0	13	B 66	P4	C 1600	Triode No. 1
6FR7	6.3	EV-3109-0	60	B 89	P4	E 6650	Triode No. 2

6FQ5A	6.3	ET-2507-0	13	B 90	P4	E12000	
6FO7	6.3	EV-7608-0	23	B 79	P4	D 2600	Triode No. 1
6FO7	6.3	EV-2103-0	23	B 79	P4	D 2600	Triode No. 2
6FR7	6.3	EV-7608-0	13	B 66	P4	C 1600	Triode No. 1
6FR7	6.3	EV-3109-0	60	B 89	P4	E 6650	Triode No. 2
6FS5	6.3	ET-1567-0	10	B 84	P4	E 6500	
6FV6	6.3	ET-1567-2	14	B 84	P4	E 6000	
6FV8	6.3	EV-9678-0	10	B 79	P4	D 3500	Pent. Sect.
6FV8	6.3	EV-1203-0	15	B 89	P4	E 7250	Triode Sect.
6FW5	6.3	HS-1583-0	50	B 88	P4	D 5000	
6FW8	6.3	EV-7608-0	21	B 90	P4	E 8500	Triode No. 1
6FW8	6.3	EV-2103-0	21	B 90	P4	E 8500	Triode No. 2
6FY8	6.3	EV-3672-0	32	B 89	P4	E 4500	Pent. Sect.
6FY8	6.3	EV-1908-0	21	B 65	P4	C 1500	Triode Sect.
6G6	6.3	HS-5348-0	17	B 76	P4	C 2300	
6GC5	6.3	EV-6917-0	25	B 90	P4	E 6000	
6GC6	6.3	HS-5083-0	50	B 89	P4	E 4750	Cap=P
6GD7	6.3	EV-9678-0	10	B 82	P4	E 7500	Pent. Sect.
6GD7	6.3	EV-1203-0	14	B 89	P4	E10000	Triode Sect.
6GE8	6.3	EV-8917-0	14	B 71	P4	D 2300	Pent. Sect.
6GE8	6.3	EV-3602-0	63	B 89	P4	E 6200	Triode Sect.
6GF7	6.3	EV-9801-0	19	B 32	P4	C 400	TRIODE NO. 1 USE HICKOK ADAPTER CODE NO. 1050-144
6GF7	6.3	EV-2603-0	61	B 88	P4	E 400	Triode No. 2
6GH8	6.3	EV-2637-0	11	B 81	P4	D 4000	Pent. Sect.
6GH8	6.3	EV-9108-0	13	B 88	P4	E 8500	Triode Sect.
6GJ5	6.3	EV-6073-0	31	B 89	----	E 7000	(CAP=P. HOLD DOWN P1 AND PRESS P4 USE HICKOK ADAPTER CODE NO. 1050-144
6GJ8	6.3	EV-2637-0	10	B 82	P4	D 4200	
6GJ8	6.3	EV-9108-0	10	B 88	P4	E 8000	
6GK5	6.3	ET-2507-6	13	B 90	P4	F15000	
6GK6	6.3	EV-2781-3	10	B 90	P4	E 9000	
6GL7	6.3	JX-4506-0	21	B 40	P4	C 850	Triode No. 1
6GL7	6.3	JX-1203-0	56	B 90	P4	E 5000	Triode No. 2
6GM5	6.3	EV-6917-0	10	B 89	P4	E 7900	
6GM6	6.3	ET-1562-7	10	B 86	P4	E 9000	
6GN8	6.3	EV-7986-0	14	B 88	P4	E 7700	Pent. Sect.
6GN8	6.3	EV-2301-0	16	B 61	P4	C 1350	Triode Sect.
6GQ7	6.3	EV-0809-0	0	A 77	P1	---	Diode No. 1
6GQ7	6.3	EV-0607-0	0	A 77	P1	---	Diode No. 2
6GQ7	6.3	EV-0201-0	0	A 77	P1	---	Diode No. 3
6GS8	6.3	EV-7821-9	0	A 20	---	G 500	PENT. NO. 1. HOLD DOWN P1 AND PRESS P4
6GS8	6.3	EV-7321-6	0	A 20	----	G 500	PENT. NO. 2. HOLD DOWN P1 AND PRESS P4.
6GT5	6.3	EV-6973-0	31	B 89	----	E 7000	(HOLD DOWN P1 AND PRESS P4 USE HICKOK ADAPTER CODE NO. 1050-144
6GU5	6.3	ET-1562-0	10	B 89	P4	E11500	
6GU7	6.3	EV-7608-0	32	B 76	P4	D 2300	Triode No. 1
6GU7	6.3	EV-2103-0	32	B 76	P4	D 2300	Triode No. 2
6GW5	6.3	ET-2105-0	19	B 89	P4	D 4600	
6GW6	6.3	HS-5048-0	31	B 89	---	E 7000	CAP=P. HOLD DOWN P1 AND PRESS P4
6GX6	6.3	ET-1562-7	13	B 65	P4	C 1800	
6GY6	6.3	ET-1562-7	14	B 61	P4	C 1400	
6GY8	6.3	EV-0607-0	0	A 76	P1	-----	Triode No. 1
6GY8	6.3	FU-3908-0	21	B 55	P4	C 1200	Triode No. 2
6GY8	6.3	FU-1200-0	30	B 55	P4	C 1250	Triode No. 3
6H5	6.3	GR-5403-0	0	B100	P4	-----	Eye Open
6H5	6.3	GR-5423-0	0	B100	P4	-----	Eye Closed
6H6	6.3	HS-0508-0	0	A 73	P1	-----	Diode No. 1
6H6	6.3	HS-0304-0	0	A 73	P1	-----	Diode No. 2
6HB6	6.3	EV-2781-9	10	A 86	P4	F15000	
6HC8	6.3	EV-3672-0	17	B 87	P4	D 4600	Pent. Sect.
6HC8	6.3	EV-3672-0	17	B 87	P4	D 4600	

6H6	6.3	HS-0304-0	0	A 73	P1	-----	Diode No. 1
6HB6	6.3	EV-2781-9	10	A 86	P4	F15000	Diode No. 2
6HC8	6.3	EV-3672-0	17	B 87	P4	D 4600	Pent. Sect.
6HC8	6.3	EV-1908-0	10	B 71	P4	C 2000	Triode Sect.
6HF8	6.3	EV-7986-0	11	B 86	P4	E 7500	Pent. Sect.
6HF8	6.3	EV-2301-0	15	B 76	P4	D 3200	Triode Sect.
6HG8	6.3	EV-2893-0	10	B 85	P4	E 5000	Pent. Sect.
6HG8	6.3	EV-6703-0	33	B 85	P4	D 2900	Triode Sect.
6HJ8	6.3	EV-2631-9	10	B 84	P4	E 6500	Pent. Sect.
6HJ8	6.3	EV-0907-0	0	A 77	P1	-----	Diode Sect.
6HK5	6.3	ET-1502-0	13	B 90	P4	E 4800	
6HL8	6.3	EV-2637-0	10	B 86	P4	E 7300	Pent. Sect.
6HL8	6.3	EV-9108-0	15	B 87	P4	E 6100	Triode Sect.
6HM6	6.3	EV-2781-9	11	B 86	P4	E10000	
6HR6	6.3	ET-1567-2	10	B 85	P4	E 6250	
6HS6	6.3	ET-1567-2	15	B 81	P4	D 4100	
6HS8	6.3	EV-7821-9	10	B 21	P4	C 650	Pent. No. 1
6HS8	6.3	EV-7321-6	10	B 21	P4	C 650	Pent. No. 2
6HT6	6.3	EV-2781-9	10	B 86	P4	E 8000	
6HW8	6.3	EV-6237-9	14	B 74	P4	C 2200	
6HZ6	6.3	ET-1562-7	10	B 63	P4	C 1400	
6HZ8	6.3	EV-7986-0	12	B 89	P4	E 8500	Pent. Sect.
6HZ8	6.3	EV-2301-0	19	B 73	P4	C 2000	Triode Sect.
6J4	6.3	ET-1702-0	15	B 89	P4	F11000	
6J5	6.3	HS-5308-0	23	B 79	P4	D 2600	
6J6	6.3	ET-5207-0	17	B 88	P4	E 5300	Triode No. 1
6J6	6.3	ET-6107-0	17	B 88	P4	E 5300	Triode No. 2
6J7	6.3	HS-0348-5	21	B 57	P4	C 1225	Cap=G
6J8	6.3	HS-5348-6	12	B 48	P4	C 1000	HEPT. SECT. CAP=G
6J8	6.3	HS-5608-4	23	B 66	P4	C 1600	Triode Sect.
6JA8	6.3	EV-7986-0	12	B 87	P4	E 8500	Tetrode Sect.
6JA8	6.3	EV-2301-0	21	B 65	P4	C 1500	Triode Sect.
6JB6	6.3	EV-2013-8	31	B 89	----	E 7000	CAP-P. HOLD DOWN P1 AND PRESS P4. USE HICKOK ADAPTER CODE NO. 1050-144
6JB8	6.3	EV-2637-0	25	B 48	P4	C 1000	Pent. Sect.
6JB8	6.3	EV-9108-0	21	B 74	P4	D 2300	Triode Sect.
6JC6	6.3	EV-2781-9	10	B 85	P4	E10000	
6JC8	6.3	EV-2637-0	10	B 82	P4	D 4000	Pent. Sect.
6JC8	6.3	EV-8901-0	10	B 87	P4	E 8500	Triode Sect.
6JD6	6.3	EV-2781-9	10	B 88	P4	E10000	
6JE6	6.3	EV-2073-8	36	B 90	P4	E 7800	CAP-P. PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO. 1050-144
6JE8	6.3	EV-7986-0	13	B 88	P4	E 8500	Pent. Sect.
6JE8	6.3	EV-2301-0	13	B 80	P4	D 4000	Triode Sect.
6JF8	6.3	HR-5046-0	36	B 83	P4	D 3900	PENT. SECT. CAP-P PLATE VOLTS=LOW
6JF8	6.3	HR-0802-0	0	B 41	P3	-----	Diode Sect.
6JH6	6.3	ET-1562-7	11	B 84	P4	E 6000	
6JH8	6.3	EV-6937-1	22	B 57	P4	C 1200	PLATE NO. 1. DISREGARD NEON FLASH IN SHORT TESTING
6JH8	6.3	EV-6837-1	22	B 57	P4	C 1200	PLATE NO. 2. DISREGARD NEON FLASH IN SHORT TESTING
6JK8	6.3	EV-7608-9	23	B 77	P4	C 2400	Triode No. 1
6JK8	6.3	EV-2103-9	18	B 89	P4	E 5500	Triode No. 2
6JL8	6.3	EV-7986-0	12	B 87	P4	E 8600	Pent. Sect.
6JL8	6.3	EV-2301-0	17	B 82	P4	D 4200	Triode Sect.
6JN8	6.3	EV-9678-0	17	B 90	P4	E 7000	Pent. Sect.
6JN8	6.3	EV-1203-0	17	B 85	P4	E 6000	Triode Sect.
6JT8	6.3	EV-7986-0	15	B 88	P4	F 9000	Pent. Sect.
6JT8	6.3	EV-2301-0	20	B 39	P4	C 850	Triode Sect.
6JU8	6.3	EV-0809-0	0	A 78	P1	-----	Diode No. 1
6JU8	6.3	EV-0708-0	0	A 78	P1	-----	Diode No. 2

6JN8	6.3	EV-1203-0	17	B 85	P4	E 6000	Triode Sect.
6JT8	6.3	EV-7986-0	15	B 88	P4	F 9000	Pent. Sect.
6JT8	6.3	EV-2301-0	20	B 39	P4	C 850	Triode Sect.
6JU8	6.3	EV-0809-0	0	A 78	P1	-----	Diode No. 1
6JU8	6.3	EV-0708-0	0	A 78	P1	-----	Diode No. 2
6JU8	6.3	EV-0203-0	0	A 78	P1	-----	Diode No. 3
6JU8	6.3	EV-0102-0	0	A 78	P1	-----	Diode No. 4
6JV8	6.3	EV-7986-0	12	B 87	P4	E 7000	Pent. Sect.
6JV8	6.3	EV-2301-0	16	B 79	P4	D 2650	Triode Sect.
6K4	6.3	DU-2105-0	29	B 85	P4	D 3450	
6K6	6.3	HS-5348-0	17	B 76	P4	D 2400	
6K7	6.3	HS-0348-5	13	B 63	P4	C 1450	Cap=G
6K8	6.3	HS-5348-6	11	B 48	P4	C 1000	HEX. SECT. CAP=G
6Kg	6.3	HS-5608-4	17	B 81	P4	D 3000	Triode Sect.
6KA8	6.3	EV-6983-7	14	B 71	P4	C 2000	Pent. Sect.
6KA8	6.3	EV-2103-0	19	B 71	P4	C 2000	Triode Sect.
6KD8	6.3	EV-2637-0	5	B 84	P4	D 4200	Pent. Sect.
6KD8	6.3	EV-9108-0	15	B 90	P4	E 8000	Triode Sect.
6KE8	6.3	EV-2637-0	10	B 85	P4	C 7800	Pent. Sect.
6KE8	6.3	EV-9108-0	16	B 88	P4	C 7300	Triode Sect.
6KF8	6.3	EV-7821-9	10	B 25	P4	C 700	Pent. No. 1
6KF8	6.3	EV-7321-6	10	B 25	P4	C 700	Pent. No. 2
6KL8	6.3	EV-2763-1	5	B 70	---	D 2300	PENT SECT. HOLD DOWN P1 AND PRESS P4
6KL8	6.3	EV-0803-0	0	A 33	P1	-----	Diode Sect.
6KM8	6.3	EV-7986-0	5	B 49	---	C 550	TETRODE PLATE 1. HOLD DOWN P1 AND PRESS P4
6KM8	6.3	EV-7286-0	5	B 50	---	C 500	TETRODE PLATE 2. HOLD DOWN P1 AND PRESS P4
6KM8	6.3	EV-7186-0	5	B 50	---	C 500	TETRODE PLATE 3. HOLD DOWN P1 AND PRESS P4
6KM8	6.3	EV-0306-0	0	A 31	P1	-----	Diode Sect.
6KS8	6.3	EV-7986-0	17	B 86	P4	E 6000	Pent. Sect.
6KS8	6.3	EV-2301-0	18	B 75	P4	C 2300	Triode Sect.
6KT8	6.3	EV-7986-0	10	B 83	P4	E 7000	Pent. Sect.
6KT8	6.3	EV-2301-0	20	B 56	P4	C 1500	Triode Sect.
6KV8	6.3	EV-7986-0	14	B 89	P4	F13500	Pent. Sect.
6KV8	6.3	EV-2301-0	15	B 77	P4	D 3100	Triode Sect.
6KZ8	6.3	EV-2673-0	13	B 82	P4	D 4000	Pent. Sect.
6KZ8	6.3	EV-9108-0	17	B 88	P4	E 6500	Triode Sect.
6L4	6.3	GR-2307-0	16	B 89	P4	E 6000	Plate Volts=Low
6L5	6.3	HS-5308-0	24	B 72	P4	C 1900	
6L6	6.3	HS-5348-1	17	B 88	P4	E 5000	
6L7	6.3	HS-0348-5	10	B 48	P4	D 1100	CAP GRID. CAP=G
6L7	6.3	HS-5348-1	14	B 48	P4	D 1100	Pin Grid
6LB8	6.3	EV-7986-0	16	B 87	P4	E 8200	Pent. Sect.
6LB8	6.3	EV-2301-0	16	B 86	P4	E 4500	Triode Sect.
6M3	6.3	JS-0000-0	0	B 65	---	-----	MAKE SHORTS TEST CAP=P
6M3	6.3	JS-0003-0	0	B 65	P3	-----	MAKE NO SHORTS TEST CAP=P. REVERSE METER
6N4	6.3	ET-1502-0	18	B 88	P4	E 6000	
6N7	6.3	HS-5608-3	17	B 65	P4	C 1500	Triode No. 1
6N7	6.3	HS-4308-6	17	B 65	P4	C 1500	Triode No. 2
6N8	6.3	EV-2613-9	8	B 71	---	D 2200	PENT. SECT. HOLD DOWN P1 AND PRESS P4
6N8	6.3	EV-2713-9	8	A 30	P1	-----	Diode No. 1
6N8	6.3	EV-2813-9	8	A 30	P1	-----	Diode No. 2
6P5	6.3	HS-5308-0	32	B 63	P4	C 1450	
6Q4	6.3	EV-1903-0	10	B 89	P4	F12000	
6Q5	6.3	HS-5308-0	#	B 95	P5	-----	Strikes at about 52
6Q7	6.3	HS-0308-1	15	B 48	P4	D 1200	TRIODE SECT. CAP=G
6Q7	6.3	HS-0508-3	15	A 30	P1	-----	Diode No. 1
6Q7	6.3	HS-0408-3	15	A 30	P1	-----	Diode No. 2
6R4	6.3	EV-1803-0	28	B 86	P4	D 4000	
6R7	6.3	HS-0308-1	21	B 72	P4	C 1900	TRIODE SECT. CAP=G

6R4	6.3	EV-1803-0	28	B 86	P4	C 1900	TRIODE SECT. CAP=G
6R7	6.3	HS-0308-1	21	B 72	P4	-----	Diode No. 1
6R7	6.3	HS-0508-3	21	A 30	P1	-----	Diode No. 2
6R7	6.3	HS-0408-3	21	A 30	P1	-----	Triode Sect.
6R8	6.3	EV-8907-2	21	B 72	P4	C 1900	Diode No. 1
6R8	6.3	EV-0107-8	0	A 78	P1	-----	Diode No. 2
6R8	6.3	EV-0607-8	0	A 78	P1	-----	Diode No. 3
6R8	6.3	EV-0203-9	0	A 78	P1	-----	
6S4	6.3	EV-6902-0	21	B 88	P4	D 4500	
6S7	6.3	HS-0348-5	12	B 65	P4	D 1750	Cap=G TRIODE SECT. CAP=G
6S8	6.3	HY-0602-0	11	B 39	P4	D 1100	Diode No. 1
6S8	6.3	HY-0305-0	11	A 38	P1	-----	Diode No. 2
6S8	6.3	HY-0402-0	11	A 38	P1	-----	Diode No. 3
6S8	6.3	HY-0102-0	11	A 38	P1	-----	
6SA7	6.3	HS-5346-8	Use this setting	for short	check only.		
6SA7	6.3	HS-5406-8	32	B 81	P4	D 3000	Do not check for shorts
6SB7	6.3	HS-5346-8	Use this setting	for short	check only.		
6SB7	6.3	HS-5406-8	30	B 86	P4	D 4000	Do not check for shorts
6SC7	6.3	HY-4506-2	12	B 53	P4	D 1325	Triode No. 1
6SC7	6.3	HY-3206-5	12	B 53	P4	D 1325	Triode No. 2
6SD7	6.3	HS-4865-3	10	B 79	P4	D 3000	
6SF5	6.3	HY-3502-1	12	B 57	P4	D 1500	
6SF7	6.3	HY-2643-1	10	B 70	P4	D 2000	Pent. Sect.
6SF7	6.3	HY-0543-6	0	A 30	P1	-----	Diode Sect.
6SG7	6.3	HS-4865-1	10	B 78	P4	D 3000	
6SH7	6.3	HS-4865-1	10	B 79	P4	E 3500	
6SJ7	6.3	HS-4865-3	18	B 65	P4	D 1650	
6SK7	6.3	HS-4865-3	10	B 69	P4	D 2000	
6SL7	6.3	HY-4506-2	13	B 59	P4	D 1600	Triode No. 1
6SL7	6.3	HY-1203-5	13	B 59	P4	D 1600	Triode No. 2
6SN7	6.3	HY-4506-2	23	B 79	P4	D 2600	Triode No. 1
6SN7	6.3	HY-1203-5	23	B 79	P4	D 2600	Triode No. 2
6SQ7	6.3	HY-2603-1	11	B 39	P4	D 1100	Triode Sect.
6SQ7	6.3	HY-0503-6	0	A 30	P1	-----	Diode No. 1
6SQ7	6.3	HY-0403-6	0	A 30	P1	-----	Diode No. 2
6SR7	6.3	HY-2603-1	21	B 72	P4	C 1900	Triode Sect.
6SR7	6.3	HY-0503-6	0	A 30	P1	-----	Diode No. 1
6SR7	6.3	HY-0403-6	0	A 30	P1	-----	Diode No. 2
6SS7	6.3	HS-4865-3	20	B 68	P4	D 1850	
6ST7	6.3	HY-2603-1	21	B 72	P4	C 1900	Triode Sect.
6ST7	6.3	HY-0503-6	0	A 30	P1	-----	Diode No. 1
6ST7	6.3	HY-0403-6	0	A 30	P1	-----	Diode No. 2
6SU7	6.3	HY-4506-2	13	B 59	P4	D 1600	Triode No. 1
6SU7	6.3	HY-1203-5	13	B 59	P4	D 1600	Triode No. 2
6SV7	6.3	HY-2643-0	11	B 77	P4	D 2600	Pent. Sect.
6SV7	6.3	HY-2543-0	11	A 75	P1	-----	Diode Sect.
6T4	6.3	ET-2105-0	16	B 88	P4	E 6500	Plate Volts=Low
6T8	6.3	EV-8907-6	15	B 48	P4	D 1200	Triode Sect.
6T8	6.3	EV-0607-1	0	A 78	P1	-----	Diode No. 1
6T8	6.3	EV-0203-7	0	A 78	P1	-----	Diode No. 2
6T8	6.3	EV-0107-8	0	A 78	P1	-----	Diode No. 3
6U3	6.3	EV-0903-0	0	B 55	P3	-----	
6U4	6.3	HY-0503-0	0	B 52	P3	-----	
6U5	6.3	GR-5403-0	0	B100	P4	-----	Eye Open
6U5	6.3	GR-5423-0	0	B100	P4	-----	Eye Closed
6U6	6.3	HS-5348-0	17	B 88	P4	E 6000	Plate Volts=Low
6U8	6.3	EV-2637-0	12	B 78	P4	D 3000	Pent. Sect.
6U8	6.3	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
6V3	6.3	EV-0000-0	0	B 60	---	-----	MAKE SHORTS TEST
6V3	6.3	EV-0002-0	0	B 60	P3	-----	DO NOT MAKE SHORTS TEST REMOVE REVERSE METAL

							MAKE SHORTS TEST	
							CAP=P	
							MAKE NO SHORTS TEST	
							CAP=P REVERSE METER	
6V3	6.3	EV-0000-0	0	B	60	P3	-----	
6V3	6.3	EV-0002-0	0	B	60	P3	-----	
6V4	6.3	EV-0703-1	0	B	0	P3	-----	Plate No. 1
6V4	6.3	EV-0103-7	0	B	0	P3	-----	Plate No. 2
6V5	6.3	HY-5340-0	46	B	79	P4	D 4100	
6V6	6.3	HS-5348-1	18	B	84	P4	D 3700	
6V8	6.3	EV-6103-8	15	B	48	P4	D 1200	Triode Sect.
6V8	6.3	EV-0903-2	0	A	30	P1	-----	Diode No. 1
6V8	6.3	EV-0708-6	0	A	78	P1	-----	Diode No. 2
6V8	6.3	EV-0203-8	0	A	78	P1	-----	Diode No. 3
6W4	6.3	HY-0503-0	0	B	60	P3	-----	
6W6	6.3	HS-5348-0	25	B	88	-----	E 6000	HOLD DOWN P1 AND PRESS P4
6X4	6.3	ET-0607-1	0	B	18	P3	-----	Plate No. 1
6X4	6.3	ET-0107-6	0	B	18	P3	-----	Plate No. 2
6X5	6.3	HS-0508-1	0	B	20	P3	-----	Plate No. 1
6X5	6.3	HS-0308-1	0	B	20	P3	-----	Plate No. 2
6X8	6.3	EV-7986-1	10	B	86	P4	D 4600	Pent. Sect.
6X8	6.3	EV-2306-1	15	B	89	P4	E 5800	Triode Sect.
6Y6	6.3	HS-5348-0	41	B	88	P4	E 5500	
6Z4	6.3	FR-0304-0	0	B	35	P3	-----	Plate No. 1
6Z4	6.3	FR-0204-0	0	B	35	P3	-----	Plate No. 2
6ZY5	6.3	HS-0508-0	0	B	15	P3	-----	Plate No. 1
6ZY5	6.3	HS-0308-0	0	B	15	P3	-----	Plate No. 2
7A4	6.3	JR-6207-0	23	B	79	P4	D 2600	
7A5	6.3	JR-6237-0	0	B	89	P4	E 5500	Plate Volts=Low
7A6	6.3	JR-0607-5	0	A	72	P1	-----	Diode No. 1
7A6	6.3	JR-0302-5	0	A	72	P1	-----	Diode No. 2
7A7	6.3	JR-6237-4	10	B	69	P4	D 2000	
7A8	6.3	JR-4537-6	45	B	48	P4	C 1000	Sect. No. 1
7A8	6.3	JR-4257-6	40	B	0	P4	C 500	Sect. No. 2
7AD7	6.3	JR-6237-4	13	B	89	P4	E 6500	
7AF7	6.3	JR-5607-0	27	B	74	P4	D 2100	Triode No. 1
7AF7	6.3	JR-4302-0	27	B	74	P4	D 2100	Triode No. 2
7AG7	6.3	JR-6237-4	11	B	74	P4	D 2600	
7AH7	6.3	JR-6237-4	10	B	79	P4	D 3300	
7AK7	6.3	JR-6237-4	0	B	70	P4	D 2000	
7AU7	6.3	EV-7608-0	25	B	75	P4	C 2200	Triode No. 1
7AU7	6.3	EV-2103-0	25	B	75	P4	C 2200	Triode No. 2
7B4	6.3	JR-6207-0	12	B	57	P4	D 1500	
7B7	6.3	JR-6237-4	23	B	67	P4	D 1750	
7C5	6.3	JR-6237-0	18	B	84	P4	D 3700	
7C6	6.3	JR-3207-0	8	B	35	P4	D 1000	Triode Sect.
7C6	6.3	JR-0607-2	0	A	30	P1	-----	Diode No. 1
7C6	6.3	JR-0507-2	0	A	30	P1	-----	Diode No. 2
7C7	6.3	JR-6237-4	8	B	73	P4	D 2275	
7DJ8	7.5	EV-7608-0	20	B	91	P4	E12500	Triode No. 1
7DJ8	7.5	EV-2103-0	20	B	91	P4	E12500	Triode No. 2
7E5	6.3	JS-1304-0	18	B	83	P4	D 3000	
7E6	6.3	JR-3207-0	21	B	72	P4	C 1900	Triode Sect.
7E6	6.3	JR-0607-2	0	A	30	P1	-----	Diode No. 1
7E6	6.3	JR-0507-2	0	A	30	P1	-----	Diode No. 2
7E7	6.3	JR-6257-0	20	B	56	P4	D 1300	Pent. Sect.
7E7	6.3	JR-0407-2	0	A	30	P1	-----	Diode No. 1
7E7	6.3	JR-0307-2	0	A	30	P1	-----	Diode No. 2
7EY6	7.5	HS-5348-0	29	B	86	P4	D 4400	
7F7	6.3	JR-5607-3	13	B	59	P4	D 1600	Triode No. 1
7F7	6.3	JR-4302-6	13	B	59	P4	D 1600	Triode No. 2
7F8	6.3	HS-8605-0	16	B	84	P4	D 3300	Triode No. 1
7F8	6.3	HS-1304-0	16	B	84	P4	D 3300	Triode No. 2

7EY6	7.5	HS-5348-0	29	B 86	P4	D 4400	
7F7	6.3	JR-5607-3	13	B 59	P4	D 1600	Triode No. 1
7F7	6.3	JR-4302-6	13	B 59	P4	D 1600	Triode No. 2
7F8	6.3	HS-8605-0	16	B 84	P4	D 3300	Triode No. 1
7F8	6.3	HS-1304-0	16	B 84	P4	D 3300	Triode No. 2
7G7	6.3	JR-6237-4	11	B 82	P4	E 4000	
7H7	6.3	JR-6237-4	10	B 78	P4	D 3000	
7J7	6.3	JR-6257-4	21	B 35	P4	C 800	Heptode Sect.
7J7	6.3	JR-4307-5	23	B 62	P4	C 1400	Triode Sect.
7K7	6.3	JR-4302-0	13	B 59	P4	D 1600	Triode Sect.
7K7	6.3	JR-0507-0	0	A 53	P1	Diode No. 1
7K7	6.3	JR-0607-0	0	A 53	P1	Diode No. 2
7L7	6.3	JR-6237-4	12	B 75	P4	D 2500	
7N7	6.3	JR-5607-3	23	B 79	P4	D 2600	Triode No. 1
7N7	6.3	JR-4302-6	23	B 79	P4	D 2600	Triode No. 2
7O7	6.3	JR-6237-4	0	B 21	C 650	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
7O7	6.3	JR-4307-6	14	B 89	P4	E 5500	Osc. Sect.
7R7	6.3	JR-6257-0	8	B 77	P4	D 2800	Pent. Sect.
7R7	6.3	JR-0407-2	0	A 30	P1	Diode No. 1
7R7	6.3	JR-0307-2	0	A 30	P1	Diode No. 2
7V7	6.3	JR-6237-4	8	B 80	P4	E 4000	
7W7	6.3	JR-6237-5	8	B 80	P4	E 4000	
7X6	6.3	JR-0607-0	0	B 45	P3	Plate No. 1
7X6	6.3	JR-0302-0	0	B 45	P3	Plate No. 2
7X7	6.3	JR-3204-0	11	B 38	P4	D 1000	Triode Sect.
7X7	6.3	JR-0504-0	0	A 77	P1	Diode No. 1
7X7	6.3	JR-0607-0	0	A 77	P1	Diode No. 2
7Y4	6.3	JR-0607-0	0	B 20	P3	Plate No. 1
7Y4	6.3	JR-0307-0	0	B 20	P3	Plate No. 2
7Z4	6.3	JR-0607-0	0	A 35	P3	Plate No. 1
7Z4	6.3	JR-0307-0	0	A 35	P3	Plate No. 2
8AU8	7.5	EV-7986-0	10	B 88	P4	E 6000	Pent. Sect.
8AU8	7.5	EV-2301-0	13	B 88	P4	E 4900	Triode Sect.
8AW8A	7.5	EV-7986-3	14	B 89	P4	E 7500	Pent. Sect.
8AW8A	7.5	EV-2301-9	13	B 83	P4	E 4000	Triode Sect.
8BA8A	7.5	EV-7986-0	10	B 88	P4	E 6000	Pent. Sect.
8BA8A	7.5	EV-2301-0	29	B 79	P4	D 2700	Triode Sect.
8BH8	7.5	EV-7986-0	8	B 88	P4	E 6000	Pent. Sect.
8BH8	7.5	EV-2301-0	26	B 83	P4	D 3300	Triode Sect.
8BN8	7.5	EV-8709-0	15	B 78	P4	D 2500	Triode Sect.
8BN8	7.5	EV-0603-0	0	A 78	P1	Diode No. 1
8BN8	7.5	EV-0102-0	0	A 78	P1	Diode No. 2
8BQ5	7.5	EV-2793-0	14	B 89	P4	E 7500	
8CG7	7.5	EV-7608-9	23	B 79	P4	D 2600	Triode No. 1
8CG7	7.5	EV-2103-9	23	B 79	P4	D 2600	Triode No. 2
8CM7	7.5	EV-7603-0	27	B 73	P4	D 2000	Triode No. 1
8CM7	7.5	EV-8109-0	23	B 88	P4	E 4400	Triode No. 2
8CN7	7.5	EV-7806-0	15	B 48	P4	D 2100	Triode Sect.
8CN7	7.5	EV-0203-0	0	A 78	P1	Diode No. 1
8CN7	7.5	EV-0103-0	0	A 78	P1	Diode No. 2
8CS7	7.5	EV-7608-0	22	B 75	P4	D 2200	Triode No. 1
8CS7	7.5	EV-3109-0	26	B 88	P4	E 4500	Triode No. 2
8CW5	7.5	EV-2793-0	16	B 89	P4	E 7500	
8CX8	7.5	EV-7986-0	11	B 89	P4	E 6500	Pent. Sect.
8CX8	7.5	EV-2301-0	13	B 87	P4	D 4400	Triode Sect.
8CY7	7.5	EV-7608-0	13	B 53	P4	D 1300	Triode No. 1
8CY7	7.5	EV-2109-0	60	B 86	P4	D 4000	Triode No. 2
8EB8	7.5	EV-7986-0	0	B 88	P4	E10000	Pent. Sect.
8EB8	7.5	EV-2301-0	10	B 72	P4	C 2000	Triode Sect.

8A08	7.5	EV-2301-0	13	B 88	P4	E 4900	Triode Sect.
8AW8A	7.5	EV-7986-3	14	B 89	P4	E 7500	Pent. Sect.
8AW8A	7.5	EV-2301-9	13	B 83	P4	E 4000	Triode Sect.
8BA8A	7.5	EV-7986-0	10	B 88	P4	E 6000	Pent. Sect.
8BA8A	7.5	EV-2301-0	29	B 79	P4	D 2700	Triode Sect.
8BH8	7.5	EV-7986-0	8	B 88	P4	E 6000	Pent. Sect.
8BH8	7.5	EV-2301-0	26	B 83	P4	D 3300	Triode Sect.
8BN8	7.5	EV-8709-0	15	B 78	P4	D 2500	Triode Sect.
8BN8	7.5	EV-0603-0	0	A 78	P1	-----	Diode No. 1
8BN8	7.5	EV-0102-0	0	A 78	P1	-----	Diode No. 2
8BQ5	7.5	EV-2793-0	14	B 89	P4	E 7500	
8CG7	7.5	EV-7608-9	23	B 79	P4	D 2600	Triode No. 1
8CG7	7.5	EV-2103-9	23	B 79	P4	D 2600	Triode No. 2
8CM7	7.5	EV-7603-0	27	B 73	P4	D 2000	Triode No. 1
8CM7	7.5	EV-8109-0	23	B 88	P4	E 4400	Triode No. 2
8CN7	7.5	EV-7806-0	15	B 48	P4	D 2100	Triode Sect.
8CN7	7.5	EV-0203-0	0	A 78	P1	-----	Diode No. 1
8CN7	7.5	EV-0103-0	0	A 78	P1	-----	Diode No. 2
8CS7	7.5	EV-7608-0	22	B 75	P4	D 2200	Triode No. 1
8CS7	7.5	EV-3109-0	26	B 88	P4	E 4500	Triode No. 2
8CW5	7.5	EV-2793-0	16	B 89	P4	E 7500	
8CX8	7.5	EV-7986-0	11	B 89	P4	E 6500	Pent. Sect.
8CX8	7.5	EV-2301-0	13	B 87	P4	D 4400	Triode Sect.
8CY7	7.5	EV-7608-0	13	B 53	P4	D 1300	Triode No. 1
8CY7	7.5	EV-2109-0	60	B 86	P4	D 4000	Triode No. 2
8EB8	7.5	EV-7986-0	0	B 88	P4	E10000	Pent. Sect.
8EB8	7.5	EV-2301-0	10	B 72	P4	C 2000	Triode Sect.

©THE HICKOK ELECTRICAL INSTRUMENT COMPANY, CLEVELAND, OHIO, 1963

PRINTED IN U. S. A.

STOP

10-1-63

MODEL 750

Tube Tester

10-1-63

STOP

8EM5	7.5	EV-3917-0	16	B 88	P4	E 5100	
8ET7	7.5	EV-7986-0	11	B 88	P4	E 8000	Pent. Sect.
8ET7	7.5	EV-0301-0	0	A 18	P1	-----	Diode No. 1
8ET7	7.5	EV-0201-0	0	A 18	P1	-----	Diode No. 2
8FQ7	7.5	EV-7608-0	23	B 79	P4	D 2600	Triode No. 1
8FQ7	7.5	EV-2103-0	23	B 79	P4	D 2600	Triode No. 2
8GN8	7.5	EV-7986-0	14	B 88	P4	E 7700	Pent. Sect.
8GN8	7.5	EV-2301-0	16	B 61	P4	C 1350	Triode Sect.
8JK8	7.5	EV-7608-9	23	B 77	P4	C 2400	Triode No. 1
8JK8	7.5	EV-2103-9	18	B 89	P4	E 5500	Triode No. 2
8JT8	7.5	EV-7986-0	15	B 88	P4	F 9000	Pent. Sect.
8JT8	7.5	EV-2301-0	20	B 39	P4	C 850	Triode Sect.
8JV8	7.5	EV-7986-0	12	B 87	P4	E 7000	Pent. Sect.
8JV8	7.5	EV-2301-0	16	B 79	P4	D 2650	Triode Sect.
8KA8	7.5	EV-6983-7	14	B 71	P4	C 2000	Pent. Sect.
8KA8	7.5	EV-2103-0	19	B 71	P4	C 2000	Triode Sect.
8KS8	7.5	EV-7986-0	17	B 86	P4	E 6000	Pent. Sect.
8KS8	7.5	EV-2301-0	18	B 75	P4	C 2300	Triode Sect.
8SN7	7.5	HY-4506-2	23	B 79	P4	D 2600	Triode No. 1
8SN7	7.5	HY-1203-5	23	B 79	P4	D 2600	Triode No. 2
9AU7	10.0	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
9AU7	10.0	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
9BR7	10.0	EV-2103-0	14	B 85	P4	D 4000	Triode Sect.
9BR7	10.0	EV-0708-0	0	A 78	P1	-----	Diode No. 1
9BR7	10.0	EV-0608-0	0	A 78	P1	-----	Diode No. 2
9CL8	10.0	EV-9678-0	10	B 83	P4	D 3500	Tetrode Sect.
9CL8	10.0	EV-1203-0	12	B 89	P4	E 7000	Triode Sect.
9DZ8	10.0	EV-3672-0	25	B 87	P4	D 4600	Pent. Sect.
9DZ8	10.0	EV-1908-0	17	B 34	P4	C 850	Triode Sect.
9U8	10.0	EV-2637-0	12	B 78	P4	D 3000	Pent. Sect.
9U8	10.0	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
9X8	10.0	EV-7986-1	10	B 86	P4	D 4600	Pentode Sect.
9X8	10.0	EV-2306-1	15	B 89	P4	E 5800	Triode Sect.
10BQ5	10.0	EV-2793-0	14	B 89	P4	E 7500	
10C8	10.0	EV-8679-0	13	B 85	P4	D 4000	Pent. Sect.
10C8	10.0	EV-2103-0	14	B 84	P4	D 1800	

9X8	10.0	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
9X8	10.0	EV-7986-1	10	B 86	P4	D 4600	Pentode Sect.
9X8	10.0	EV-2306-1	15	B 89	P4	E 5800	Triode Sect.
10BQ5	10.0	EV-2793-0	14	B 89	P4	E 7500	
10C8	10.0	EV-8679-0	13	B 85	P4	D 4000	Pent. Sect.
10C8	10.0	EV-2103-0	14	B 84	P4	D 4000	Triode Sect.
10DA7	10.0	EV-7608-0	23	B 79	P4	D 2600	Triode No. 1
10DA7	10.0	EV-3109-0	55	B 87	P4	E 4700	Triode No. 2
10DE7	10.0	EV-7608-0	30	B 73	P4	C 2000	Triode No. 1
10DE7	10.0	EV-2109-0	55	B 88	P4	D 5000	Triode No. 2
10DR7	10.0	EV-7608-0	13	B 57	P4	C 1250	Triode No. 1
10DR7	10.0	EV-2109-0	55	B 89	P4	D 5400	Triode No. 2
10EB8	10.0	EV-7986-0	0	B 88	P4	E10000	Pent. Sect.
10EB8	10.0	EV-2301-0	10	B 72	P4	C 2000	Triode Sect.
10EG7	10.0	HY-4506-0	29	B 71	P4	C 2000	Triode No. 1
10EG7	10.0	HY-1203-0	55	B 93	P4	E 7500	Triode No. 2
10EM7	10.0	HY-4506-0	13	B 66	P4	C 1600	Triode No. 1
10EM7	10.0	HY-1203-0	60	B 89	P4	E 6650	Triode No. 2
10EW7	10.0	EV-7608-0	34	B 69	P4	C 1700	Triode No. 1
10EW7	10.0	EV-2109-0	61	B 91	P4	E 7500	Triode No. 2
10FD7	10.0	EV-7608-0	12	B 66	P4	C 1600	Triode No. 1
10FD7	10.0	EV-2109-0	59	B 89	P4	E 7500	Triode No. 2
10FR7	10.0	EV-7608-0	13	B 66	P4	C 1600	Triode No. 1
10FR7	10.0	EV-3109-0	60	B 89	P4	E 6650	Triode No. 2
10GF7	10.0	EV-9801-0	19	B 32	P4	C 400	TRIODE NO. 1. USE HICKOK ADAPTER CODE NO. 1050-144
10GF7	10.0	EV-2603-0	61	B 88	P4	E 400	Triode No. 2
10GN8	10.0	EV-7986-0	14	B 88	P4	E 7700	Pent. Sect.
10GN8	10.0	EV-2301-0	16	B 61	P4	C 1350	Triode Sect.
10HF8	10.0	EV-7986-0	11	B 86	P4	E 7500	Pent. Sect.
10HF8	10.0	EV-2301-0	15	B 76	P4	D 3200	Triode Sect.
10JA8	10.0	EV-7986-0	12	B 87	P4	E 8500	Tetrode Sect.
10JA8	10.0	EV-2301-0	21	B 65	P4	C 1500	Triode Sect.
10JT8	10.0	EV-7986-0	15	B 88	P4	F 9000	Pent. Sect.
10JT8	10.0	EV-2301-0	20	B 39	P4	C 850	Triode Sect.
10JY8	10.0	EV-7986-0	15	B 86	P4	E 8000	Pent. Sect.
10JY8	10.0	EV-2301-0	14	B 87	P4	E10000	Triode Sect.
10LB8	10.0	EV-7986-0	16	B 87	P4	E 8200	Pent. Sect.
10LB8	10.0	EV-2301-0	16	B 86	P4	E 4500	Triode Sect.
11C5	10.0	ET-2761-0	0	B 87	P4	E 5000	Plate Volts=Low
11CY7	10.0	EV-7608-0	13	B 53	P4	D 1300	Triode No. 1
11CY7	10.0	EV-2109-0	60	B 86	P4	D 4000	Triode No. 2
11JE8	10.0	EV-7986-0	13	B 88	P4	E 8500	Pent. Sect.
11JE8	10.0	EV-2301-0	13	B 80	P4	D 4000	Triode Sect.
11KV8	10.0	EV-7986-0	14	B 89	P4	F13500	Pent. Sect.
11KV8	10.0	EV-2301-0	15	B 77	P4	D 3100	Triode Sect.
12A4	12.6	EV-2901-0	25	B 89	P4	E 7800	
12A7	12.6	HR-0236-5	40	B 47	P4	C 975	PENT. SECT. CAP=B
12A7	12.6	HR-0504-2	0	B 30	P3	Rect. Sect.
12A8	12.6	HS-0348-5	0	B 48	P4	C 1000	PENT. SECT. CAP=B PLATE VOLTS=LOW
12A8	12.6	HS-5648-3	22	A 0	P4	G 350	Osc. Sect.
12AB5	12.6	EV-3917-0	18	B 84	P4	D 3700	
12AC6	12.6	ET-2657-1	20	A 15	P1	Make no gas test
12AD6	12.6	ET-7652-1	30	B 25	P1	Make no gas test
12AD7	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
12AD7	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
12AE6	12.6	ET-0702-1	0	A 0	P1	TRIODE SECT. MAKE NO GAS TEST.
12AE6	12.6	ET-0602-0	0	A 30	P1	Diode No. 1
12AE6	12.6	ET-0502-0	0	A 30	P1	Diode No. 2
12AE7	12.6	EV-0608-7	0	B 67	P1	TRIODE NO. 1. MAKE NO GAS TEST.
12AE7	12.6	EV-0103-2	0	B 70	P1	TRIODE NO. 2. MAKE NO GAS TEST.
12AF3	12.6	EV-0000-0	0	B	P1	TRIODE NO. 2. MAKE NO GAS TEST.

12AE6	12.6	ET-0702-1	0	A 0	P1	-----	TRIODE SECT. MAKE NO GAS TEST
12AE6	12.6	ET-0602-0	0	A 30	P1	-----	Diode No. 1
12AE6	12.6	ET-0502-0	0	A 30	P1	-----	Diode No. 2
12AE7	12.6	EV-0608-7	0	B 67	P1	-----	TRIODE NO. 1. MAKE NO GAS TEST.
12AE7	12.6	EV-0103-2	0	B 70	P1	-----	TRIODE NO. 2. MAKE NO GAS TEST
12AF3	12.6	EV-0000-0	0	B 44	----	-----	MAKE SHORTS TEST CAP=P
12AF3	12.6	EV-0002-0	0	B 44	P3	-----	MAKE NO SHORTS TEST CAP=P. REVERSE METER
12AF6	12.6	ET-1567-2	25	A 68	P4	G 1150	
12AG6	12.6	ET-7652-1	30	B 50	P1	-----	Make no gas test
12AH7	12.6	HY-5604-3	25	B 72	P4	C 1900	Triode No. 1
12AH7	12.6	HY-1302-6	25	B 72	P4	C 1900	Triode No. 2
12AJ6	12.6	ET-0702-1	0	A 0	P1	-----	TRIODE SECT. OK ABOVE 400 ON 3000 SCALE. MAKE NO GAS TEST
12AJ6	12.6	ET-0602-0	0	A 30	P1	-----	Diode No. 1
12AJ6	12.6	ET-0502-0	0	A 30	P1	-----	Diode No. 2
12AL5	12.6	ET-0701-6	0	A 78	P1	-----	Diode No. 1
12AL5	12.6	ET-0205-6	0	A 78	P1	-----	Diode No. 2
12AL8	12.6	EV-0367-2	0	B 78	P1	-----	TETRODE SECT. MAKE NO GAS TEST
12AL8	12.6	EV-0109-8	0	A 0	P1	-----	TRIODE SECT. OK ABOVE 500 ON 3000 SCALE. MAKE NO GAS TEST.
12AQ5	12.6	ET-1562-0	18	B 84	P4	D 3700	
12AS5	12.6	ET-2761-0	22	B 89	----	E 5600	HOLD DOWN P1 AND PRESS P4
12AT6	12.6	ET-1702-0	15	B 48	P4	D 1200	Triode Sect.
12AT6	12.6	ET-1602-0	15	A 30	P1	-----	Diode No. 1
12AT6	12.6	ET-1502-0	15	A 30	P1	-----	Diode No. 2
12AT7	12.6	EV-7608-0	14	B 85	P4	D 4000	Triode No. 1
12AT7	12.6	EV-2103-0	14	B 85	P4	D 4000	Triode No. 2
12AU6	12.6	ET-1567-2	10	B 78	P4	D 3000	
12AU7	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
12AU7	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
12AU8	12.6	EV-7986-0	10	B 88	P4	E 6000	Pent. Sect.
12AU8	12.6	EV-2301-0	13	B 88	P4	E 4900	Triode Sect.
12AV5	12.6	HS-1583-0	28	B 89	P4	E 5500	Plate Volts=Low
12AV6	12.6	ET-1702-5	14	B 48	P4	D 1250	Triode Sect.
12AV6	12.6	ET-1602-5	14	A 30	P1	-----	Diode No. 1
12AV6	12.6	ET-1502-7	14	A 30	P1	-----	Diode No. 2
12AV7	12.6	EV-7608-2	10	B 89	P4	E 8500	Triode No. 1
12AV7	12.6	EV-2103-7	10	B 89	P4	E 8500	Triode No. 2
12AW6	12.6	ET-1562-7	10	B 84	P4	D 4000	
12AX4	12.6	HY-0503-0	0	B 40	P3	-----	
12AX7	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
12AX7	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
12AY3	12.6	EV-0209-0	0	B 48	P3	-----	USE HICKOK ADAPTER CODE NO. 1053-144
12AY7	12.6	EV-7608-0	15	B 67	P4	D 1750	Triode No. 1
12AY7	12.6	EV-2103-0	15	B 67	P4	D 1750	Triode No. 2
12AZ7	12.6	EV-7608-0	14	B 85	P4	D 4000	Triode No. 1
12AZ7	12.6	EV-2103-0	14	B 85	P4	D 4000	Triode No. 2
12B4	12.6	EV-2901-0	50	B 88	P4	E 6500	
12B7	12.6	JR-6237-4	10	B 69	P4	D 2000	
12BA6	12.6	ET-1567-2	0	B 79	P4	D 3200	
12BA7	12.6	EV-7913-2	0	B 31	----	C 750	AMPL SECT HOLD DOWN P1 AND PRESS P4
12BA7	12.6	EV-2103-7	16	B 89	P4	E 8000	Osc. Sect.
12BD6	12.6	ET-1567-2	10	B 69	P4	D 2000	
12BE6	12.6	ET-7562-1	0	B 35	----	C 800	AMPL SECT HOLD DOWN P1 AND PRESS P4
12BE6	12.6	ET-1602-7	20	B 88	P4	E 6500	Osc. Sect.
12BF6	12.6	ET-1702-0	21	B 72	P4	C 1900	Triode Sect.
12BF6	12.6	ET-1602-0	21	A 30	P1	-----	Diode No. 1
12BF6	12.6	ET-1502-0	21	A 30	P1	-----	Diode No. 2
12BH7	12.6	EV-7608-2	28	B 82	P4	D 3100	Triode No. 1

12BF6	12.6	ET-1602-0	21	A 30	P1	Diode No. 1
12BF6	12.6	ET-1502-0	21	A 30	P1	Diode No. 2
12BH7	12.6	EV-7608-2	28	B 82	P4	D 3100	Triode No. 1
12BH7	12.6	EV-2103-7	28	B 82	P4	D 3100	Triode No. 2
12BK5	12.6	EV-3186-0	0	B 89	P4	E 7500	
12BK6	12.6	ET-1702-5	14	B 48	P4	D 1250	Triode Sect.
12BK6	12.6	ET-0602-5	0	A 53	P1	Diode No. 1
12BK6	12.6	ET-0502-7	0	A 53	P1	Diode No. 2
12BL6	12.6	ET-2657-1	22	B 25	P1	MAKE NO GAS TEST
12BN6	12.6	ET-2751-6	0	A 30	P4	G 800	Limiter Grid
12BN6	12.6	ET-6751-2	0	A 40	P4	G 825	Quadrature Grid
12BQ6	12.6	HS-5048-0	28	B 89	P4	E 5500	CAP=P PLATE VOLTS=LOW
12BR7	12.6	EV-2103-0	14	B 85	P4	D 4000	Triode Sect.
12BR7	12.6	EV-0708-0	0	A 78	P1	Diode No. 1
12BR7	12.6	EV-0608-0	0	A 78	P1	Diode No. 2
12BS3	12.6	EV-0209-0	0	A 50	P3	USE HICKOK ADAPTER CODE NO. 1061-144
12BT6	12.6	ET-1702-0	15	B 48	P4	D 1200	Triode Sect.
12BT6	12.6	ET-1602-0	15	A 53	P1	Diode No. 1
12BT6	12.6	ET-1502-0	15	A 53	P1	Diode No. 2
12BU6	12.6	ET-1702-0	21	B 72	P4	C 1900	Triode Sect.
12BU6	12.6	ET-1602-0	21	A 53	P1	Diode No. 1
12BU6	12.6	ET-1502-0	21	A 53	P1	Diode No. 2
12BV7	12.6	EV-2781-3	0	B 88	P4	E 8000	
12BW4	12.6	EV-0709-1	0	A 40	P3	Plate No. 1
12BW4	12.6	EV-0109-7	0	A 40	P3	Plate No. 2
12BY7	12.6	EV-2781-3	0	B 88	P4	E 8000	
12BZ6	12.6	ET-1562-7	10	B 86	P4	D 4500	
12BZ7	12.6	EV-7608-0	13	B 75	P4	C 2300	Triode No. 1
12BZ7	12.6	EV-2103-0	13	B 75	P4	C 2300	Triode No. 2
12C5	12.6	ET-2761-0	13	B 89	E 7500	
12C8	12.6	HS-0368-1	22	B 48	P4	C 1000	
12C8	12.6	HS-0508-3	22	A 32	P1	Diode No. 1
12C8	12.6	HS-0408-3	22	A 32	P1	Diode No. 2
12CA5	12.6	DU-2761-0	0	B 88	P4	E 7000	Plate Volts=Low
12CM6	12.6	EV-3917-0	18	B 84	P4	D 3700	
12CN5	12.6	ET-0671-2	0	B 55	P1	Make no gas test
12CR6	12.6	ET-7561-2	11	B 73	P4	D 2200	Pent. Sect.
12CR6	12.6	ET-0201-0	0	A 30	P1	Diode Sect.
12CS6	12.6	ET-1562-7	16	A 22	P4	G 500	Grid No. 1
12CS6	12.6	ET-7562-1	0	A 60	P4	G 1250	Grid No. 3
12CT8	12.6	EV-8679-0	10	B 88	P4	E 6000	Pent. Sect.
12CT8	12.6	EV-2103-0	13	B 88	P4	E 4900	Triode Sect.
12CU5	12.6	ET-2761-0	22	B 88	E 6000	HOLD DOWN P1 AND PRESS P4
12CU6	12.6	HS-5048-0	28	B 89	P4	E 5500	CAP=P PLATE VOLTS=LOW
12CX6	12.6	ET-2657-1	0	B 53	P1	Make no gas test
12D4	12.6	HY-0503-0	0	B 40	P3	
12DB5	12.6	EV-3912-0	25	B 90	E 6000	HOLD DOWN P1 AND PRESS P4
12DE8	12.6	EV-7869-1	0	A 32	P1	PENT. SECT. MAKE NO GAS TEST
12DE8	12.6	EV-0302-0	0	A 82	P1	Diode Sect.
12DF5	12.6	EV-0608-0	0	A 40	P3	Plate No. 1
12DF5	12.6	EV-0103-0	0	A 40	P3	Plate No. 2
12DF7	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
12DF7	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
12DJ8	12.6	EV-7608-0	20	B 91	P4	E12500	Triode No. 1
12DJ8	12.6	EV-2103-0	20	B 91	P4	E12500	Triode No. 2
12DK6	12.6	ET-1562-7	10	B 87	P4	E 6500	
12DK7	12.6	EV-0372-1	0	B 62	P1	TETRODE SECT. MAKE NO GAS TEST
12DK7	12.6	EV-0602-0	0	A 30	P1	Diode No. 1
12DK7	12.6	EV-0902-0	0	A 30	P1	Diode No. 2

12DK7	12.6	EV-0372-1	0	B 02	P1	-----	Diode No. 1
12DK7	12.6	EV-0602-0	0	A 30	P1	-----	Diode No. 2
12DK7	12.6	EV-0902-0	0	A 30	P1	-----	TETRODE SECT. MAKE NO GAS TEST
12DL8	12.6	EV-0362-7	0	B 81	P1	-----	Diode No. 1
12DL8	12.6	EV-0908-0	0	A 46	P1	-----	Diode No. 1
12DL8	12.6	EV-0108-0	0	A 46	P1	-----	Diode No. 2
12DM4	12.6	HY-0503-0	0	B 49	P3	-----	
12DM5	12.6	ET-2761-0	13	B 91	---	E 7500	HOLD DOWN P1 AND PRESS P4
12DQ4	12.6	JX-0503-0	0	B 43	P3	-----	
12DQ6	12.6	HS-5048-0	36	B 87	----	E 5000	CAP-P. HOLD DOWN P1 AND PRESS P4
12DQ7	12.6	EV-2781-3	9	B 87	P4	E 8000	
12DS7	12.6	EV-7368-0	0	B 79	P1	-----	TETRODE SECT. MAKE NO GAS TEST
12DS7	12.6	EV-0908-0	0	A 44	P1	-----	Diode No. 1
12DS7	12.6	EV-0108-0	0	A 44	P1	-----	Diode No. 2
12DT5	12.6	EV-3917-0	22	B 88	P4	E 5100	
12DT7	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
12DT7	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
12DT8	12.6	EV-7608-9	14	B 85	P4	D 4000	Triode No. 1
12DT8	12.6	EV-2103-9	14	B 85	P4	D 4000	Triode No. 2
12DU7	12.6	EV-0362-1	0	B 68	P1	-----	TETRODE SECT. MAKE NO GAS TEST
12DU7	12.6	EV-0902-0	0	A 0	P1	-----	Diode No. 1
12DU7	12.6	EV-0702-0	0	A 0	P1	-----	Diode No. 2
12DV7	12.6	EV-0608-7	0	A 0	P1	-----	TRIODE SECT. OK ABOVE 700 ON 3000 SCALE MAKE NO GAS TEST
12DV7	12.6	EV-0301-0	0	A 0	P1	-----	Diode No. 1
12DV7	12.6	EV-0201-0	0	A 0	P1	-----	Diode No. 2
12DV8	12.6	EV-0362-7	0	A 77	P1	-----	TETRODE SECT. MAKE NO GAS TEST.
12DV8	12.6	EV-0908-0	0	A 28	P1	-----	Diode No. 1
12DV8	12.6	EV-0108-0	0	A 28	P1	-----	Diode No. 2
12DW5	12.6	EV-3917-0	28	B 89	P4	E 5500	Plate Volts=Low
12DW7	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
12DW7	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
12DW8	12.6	EV-7608-0	19	B 47	P1	-----	TRIODE NO. 1 MAKE NO GAS TEST
12DW8	12.6	EV-2103-0	0	B 76	P1	-----	TRIODE NO. 2 MAKE NO GAS TEST
12DW8	12.6	EV-0908-0	0	A 76	P1	-----	DIODE SECT. MAKE NO GAS TEST
12DY8	12.6	EV-0362-1	0	B 66	P1	-----	TETRODE SECT. MAKE NO GAS TEST.
12DY8	12.6	EV-0807-9	0	A 24	P1	-----	TRIODE SECT. MAKE NO GAS TEST.
12DZ6	12.6	ET-2657-1	0	B 60	P1	-----	Make no gas test
12DZ8	12.6	EV-3672-0	25	B 87	P4	D 4600	Pent. Sect.
12DZ8	12.6	EV-1908-0	17	B 34	P4	C 850	Triode Sect.
12EA6	12.6	ET-2657-1	0	B 56	P1	-----	Make no gas test
12EC8	12.6	EV-0768-9	0	B 21	P1	-----	PENT. SECT. MAKE NO GAS TEST.
12EC8	12.6	EV-0203-1	0	B 40	P1	-----	TRIODE SECT. MAKE NO GAS TEST.
12ED5	12.6	DU-2761-0	0	B 88	P4	E 7000	Plate Volts=Low
12EG6	12.6	ET-7652-1	0	B 56	P1	-----	Make no gas test
12EH5	12.6	ET-2761-0	13	B 88	P4	E 7200	
12EK6	12.6	ET-2657-1	0	B 60	P1	-----	Make no gas test
12EL6	12.6	ET-0207-1	0	B 0	P1	-----	TRIODE SECT. MAKE NO GAS TEST OK ABOVE 400 ON 3000 SCALE
12EL6	12.6	ET-0507-0	0	A 30	P1	-----	Diode No. 1
12EL6	12.6	ET-0607-0	0	A 30	P1	-----	Diode No. 2
12EM6	12.6	EV-0362-1	0	B 62	P1	-----	TETRODE SECT. MAKE NO GAS TEST
12EM6	12.6	EV-0902-0	0	A 30	P1	-----	Diode Sect.
12EN6	12.6	HS-5348-0	38	B 89	P4	E 6000	
12EQ7	12.6	EV-2763-1	20	B 44	P4	C 1300	Pent. Sect.
12EQ7	12.6	EV-0803-0	0	A 30	P1	-----	Diode Sect.
12EZ6	12.6	ET-2657-1	0	B 49	P1	-----	Make no gas test
12F8	12.6	EV-9237-8	25	A 0	P1	-----	PENTODE SECT. MAKE NO GAS TEST

12EQ7	12.6	ET-2657-1	0	B	49	P1	Make no gas test
12EZ6	12.6	ET-2657-1	0	B	49	P1	PENTODE SECT. MAKE NO GAS TEST
12F8	12.6	EV-9237-8	25	A	0	P1	Diode No. 1
12F8	12.6	EV-0607-0	0	A	30	P1	Diode No. 2
12F8	12.6	EV-0107-0	0	A	30	P1	TRIODE SECT. MAKE NO GAS TEST
12FK6	12.6	ET-1702-0	20	A	0	P1	Diode No. 1
12FK6	12.6	ET-0602-0	0	A	30	P1	Diode No. 2
12FK6	12.6	ET-0502-0	0	A	30	P1	TRIODE SECT. MAKE NO GAS TEST
12FM6	12.6	ET-0702-1	0	B	25	P1	Diode No. 1
12FM6	12.6	ET-0602-0	0	A	36	P1	Diode No. 2
12FM6	12.6	ET-0502-0	0	A	36	P1	TRIODE NO. 1 PLATE NO. 1
12FQ8	12.6	EV-7809-0	10	B	32	P4	C 850	TRIODE NO. 1 PLATE NO. 2
12FQ8	12.6	EV-7609-0	10	B	32	P4	C 850	TRIODE NO. 2 PLATE NO. 1
12FQ8	12.6	EV-2309-0	10	B	32	P4	C 850	TRIODE NO. 2 PLATE NO. 2
12FQ8	12.6	EV-2109-0	10	B	32	P4	C 850	PENT. SECT. MAKE NO GAS TEST
12FR8	12.6	EV-3670-0	25	A	79	P1	TRIODE SECT. MAKE NO GAS TEST
12FR8	12.6	EV-1902-0	10	A	62	P1	Diode Sect.
12FR8	12.6	EV-0802-0	0	A	55	P1	TRIODE SECT. MAKE NO GAS TEST
12FT6	12.6	ET-1702-0	0	B	43	P1	DIODE NO. 1 MAKE NO GAS TEST
12FT6	12.6	ET-0602-0	0	A	46	P1	DIODE NO. 2 MAKE NO GAS TEST
12FT6	12.6	ET-0502-0	0	A	46	P1	Triode No. 1
12FV7	12.6	EV-7608-0	25	B	90	P4	E 9000	Triode No. 2
12FV7	12.6	EV-2103-0	25	B	90	P4	E 9000	HEPTODE SECT. MAKE NO GAS TEST
12FX5	12.6	ET-2761-0	15	B	88	P4	E 7750	TRIODE SECT. MAKE NO GAS TEST
12FX8	12.6	EV-9137-2	30	B	40	P1	MAKE NO GAS TEST
12FX8	12.6	EV-6800-0	0	B	76	P1	MAKE NO GAS TEST
12G4	12.6	ET-6107-0	23	B	79	P4	D 2600	TRIODE NO. 1 MAKE NO GAS TEST.
12G8	12.6	EV-0607-8	0	B	65	P1	TRIODE NO. 2 MAKE NO GAS TEST.
12G8	12.6	EV-0102-3	0	B	25	P1	MAKE NO GAS TEST
12GA6	12.6	ET-7652-1	30	B	23	P1	Cap=P
12GC6	12.6	HS-5083-0	50	B	89	P4	E 4750	(CAP=P. HOLD DOWN P1 AND PRESS P4 USE HICKOK ADAPTER CODE NO. 1050-144
12GJ5	12.6	EV-6073-0	31	B	89	E 7000	(HOLD DOWN P1 AND AND PRESS P4 USE HICKOK ADAPTER CODE NO. 1050-144
12GN7	12.6	EV-2781-9	10	B	89	P4	F 1900	CAP=P. HOLD DOWN P1 AND PRESS P4
12GT5	12.6	EV-6973-0	31	B	89	E 7000	Diode No. 1
12GW6	12.6	HS-5048-0	31	B	89	E 7000	Diode No. 2
12H6	12.6	HS-0508-1	0	A	73	P1	Cap=G
12H6	12.6	HS-0304-1	0	A	73	P1	TETRODE SECT. MAKE NO GAS TEST.
12J5	12.6	HS-5308-1	23	B	79	P4	D 2600	Diode No. 1
12J7	12.6	HS-0348-5	21	B	57	P4	C 1225	Diode No. 2
12J8	12.6	EV-0362-1	0	B	65	P1	PLATE VOLTS-LOW. MAKE NO GAS TEST
12J8	12.6	EV-0907-0	0	A	78	P1	(CAP=P. HOLD DOWN P1 AND PRESS P4. USE HICKOK ADAPTER CODE NO. 1050-144
12J8	12.6	EV-0807-0	0	A	82	P1	Cap=G
12K5	12.6	ET-2751-0	10	B	80	P4	D 4000	HEX. SECT. CAP=G
12JB6	12.6	EV-2013-8	31	B	89	E 7000	Triode Sect.
12K7	12.6	HS-0348-5	18	B	63	P4	C 1450	PENT. SECT. HOLD DOWN P1 AND PRESS P4
12K8	12.6	HS-5348-6	11	B	48	P4	C 1000	Diode Sect.
12K8	12.6	HS-5608-4	17	B	81	P4	D 3000	HOLD DOWN P1 AND PRESS P4
12KL8	12.6	EV-2763-1	5	B	70	D 2300	Pent. No. 1
12KL8	12.6	EV-0803-0	0	A	33	P1	Pent. No. 2
12L6	12.6	HS-5348-0	25	B	88	E 6000	TRIODE SECT. CAP=G
12L8	12.6	HW-1852-3	0	B	68	P4	C 1700	Diode No. 1
12L8	12.6	HW-3452-1	0	B	68	P4	C 1700	Diode No. 2
12Q7	12.6	HS-0308-0	15	B	48	P4	D 1200	
12Q7	12.6	HS-0508-3	15	A	30	P1	
12Q7	12.6	HS-0408-3	15	A	30	P1	

12Q7	12.6	HS-0408-3	15	A	30	P1	Diode No. 2
12R5	12.6	ET-2761-0	13	B	89	E 7000	HOLD DOWN P1 AND PRESS P4 TRIODE SECT. GAP=B
12S8	12.6	HY-0602-0	11	B	39	P4	D 1100	Diode No. 1
12S8	12.6	HY-0305-0	11	A	38	P1	Diode No. 2
12S8	12.6	HY-0402-0	11	A	38	P1	Diode No. 3
12S8	12.6	HY-0102-0	11	A	38	P1	Diode No. 3
12SA7	12.6	HS-5346-8	Use	this	setting	for	short	check only
12SA7	12.6	HS-5406-8	32	B	81	P4	D 3000	Do not check for shorts
12SC7	12.6	HY-4506-2	12	B	53	P4	D 1325	Triode No. 1
12SC7	12.6	HY-3206-5	12	B	53	P4	D 1325	Triode No. 2
12SF5	12.6	HY-3502-0	12	B	57	P4	D 1500	
12SF7	12.6	HY-2643-1	10	B	70	P4	D 2000	Pent. Sect.
12SF7	12.6	HY-0503-6	0	A	30	P1	Diode Sect.
12SG7	12.6	HS-4865-1	10	B	78	P4	D 3000	
12SH7	12.6	HS-4865-1	10	B	79	P4	E 3500	
12SJ7	12.6	HS-4865-3	18	B	65	P4	D 1650	
12SK7	12.6	HS-4865-3	10	B	69	P4	D 2000	
12SL7	12.6	HY-4506-2	13	B	59	P4	D 1600	Triode No. 1
12SL7	12.6	HY-1203-5	13	B	59	P4	D 1600	Triode No. 2
12SN7	12.6	HY-4506-2	23	B	79	P4	D 2600	Triode No. 1
12SN7	12.6	HY-1203-5	23	B	79	P4	D 2600	Triode No. 2
12SQ7	12.6	HY-2603-1	11	B	39	P4	D 1100	Triode Sect.
12SQ7	12.6	HY-0503-6	0	A	30	P1	Diode No. 1
12SQ7	12.6	HY-0403-6	0	A	30	P1	Diode No. 2
12SR7	12.6	HY-2603-1	21	B	72	P4	C 1900	Triode Sect.
12SR7	12.6	HY-0503-6	0	A	30	P1	Diode No. 1
12SR7	12.6	HY-0403-6	0	A	30	P1	Diode No. 2
12U7	12.6	EV-0608-7	0	A	0	P1	TRIODE NO. 1 MAKE NO GAS TEST.
12U7	12.6	EV-0103-2	0	A	0	P1	TRIODE NO. 2 MAKE NO GAS TEST.
12V6	12.6	HS-5348-0	18	B	84	P4	D 3700	
12W6	12.6	HS-5348-0	25	B	88	E 6000	HOLD DOWN P1 AND PRESS P4
12X4	12.6	ET-0607-1	0	B	18	P3	Plate No. 1
12X4	12.6	ET-0107-6	0	B	18	P3	Plate No. 2
13CW4	12.6	DR-4208-0	9	B	87	P4	E 9000	PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO 1050-127
13DE7	12.6	EV-7608-0	30	B	73	P4	C 2000	Triode No. 1
13DE7	12.6	EV-2109-0	55	B	88	P4	D 5000	Triode No. 2
13DR7	12.6	EV-7608-0	13	B	57	P4	C 1250	Triode No. 1
13DR7	12.6	EV-2109-0	55	B	89	P4	D 5400	Triode No. 2
13EM7	12.6	HY-4506-0	13	B	66	P4	C 1600	Triode No. 1
13EM7	12.6	HY-1203-0	60	B	89	P4	E 6650	Triode No. 2
13FD7	12.6	EV-7608-0	12	B	66	P4	C 1600	Triode No. 1
13FD7	12.6	EV-2109-0	59	B	89	P4	E 7500	Triode No. 2
13FR7	12.6	EV-7608-0	13	B	66	P4	C 1600	Triode No. 1
13FR7	12.6	EV-3109-0	60	B	89	P4	E 6650	Triode No. 2
13GF7	12.6	EV-9801-0	19	B	32	P4	C 400	TRIODE NO 1 USE HICKOK ADAPTER CODE NO 1050-144
13GF7	12.6	EV-2603-0	61	B	88	P4	E 400	Triode No. 2
14A7	12.6	JR-6237-4	10	B	69	P4	D 2000	
14AF7	12.6	JR-5607-0	27	B	74	P4	D 2100	Triode No. 1
14AF7	12.6	JR-4302-0	27	B	74	P4	D 2100	Triode No. 2
14B6	12.6	JR-3207-0	11	B	39	P4	D 1100	Triode Sect.
14B6	12.6	JR-0607-2	0	A	30	P1	Diode No. 1
14B6	12.6	JR-0507-2	0	A	30	P1	Diode No. 2
14B8	12.6	JR-6257-4	0	B	48	P4	C 1000	PENT. SECT. PLATE VOLTS=LOW
14B8	12.6	JR-4357-6	22	A	0	P4	G 350	Osc. Sect.
14C5	12.6	JR-6237-0	18	B	84	P4	D 3700	
14C7	12.6	JR-6237-4	8	B	73	P4	D 2275	
14E6	12.6	JR-3207-0	21	B	72	P4	C 1900	Triode Sect.
14E6	12.6	JR-0607-2	0	A	30	P1	Diode No. 1
14E6	12.6	JR-0507-2	0	A	30	P1	Diode No. 2

14C7	12.6	JR-6237-4	8	B	73	P4	D 2275	
14E6	12.6	JR-3207-0	21	B	72	P4	C 1900	Triode Sect.
14E6	12.6	JR-0607-2	0	A	30	P1	-----	Diode No. 1
14E6	12.6	JR-0507-2	0	A	30	P1	-----	Diode No. 2
14F7	12.6	JR-5607-3	13	B	59	P4	D 1600	Triode No. 1
14F7	12.6	JR-4302-6	13	B	59	P4	D 1600	Triode No. 2
14F8	12.6	HS-8605-0	16	B	84	P4	D 3300	Triode No. 1
14F8	12.6	HS-1304-0	16	B	84	P4	D 3300	Triode No. 2
14GT8	12.6	EV-8907-0	10	B	38	P4	C 800	Triode Sect.
14GT8	12.6	EV-0601-0	0	A	78	P1	-----	Diode No. 1
14GT8	12.6	EV-0203-0	0	A	78	P1	-----	Diode No. 2
14H7	12.6	JR-6237-4	10	B	78	P4	D 3000	
14J7	12.6	JR-6257-4	21	B	35	P4	C 800	Heptode Sect.
14J7	12.6	JR-4307-5	23	B	62	P4	C 1400	Triode Sect.
14JG8	12.6	EV-8907-0	10	B	62	P4	C 1500	Triode Sect.
14JG8	12.6	EV-0601-0	0	A	78	P1	-----	Diode No. 1
14JG8	12.6	EV-0203-0	0	A	78	P1	-----	Diode No. 2
14N7	12.6	JR-5607-3	23	B	79	P4	D 2600	Triode No. 1
14N7	12.6	JR-4302-6	23	B	79	P4	D 2600	Triode No. 2
14Q7	12.6	JR-6237-4	0	B	21	----	C 650	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
14Q7	12.6	JR-4307-6	14	B	89	P4	E 5500	Osc. Sect.
14R7	12.6	JR-6257-0	8	B	77	P4	D 2800	Pent. Sect.
14R7	12.6	JR-0407-2	0	A	30	P1	-----	Diode No. 1
14R7	12.6	JR-0307-2	0	A	30	P1	-----	Diode No. 2
14S7	12.6	JR-6257-4	16	B	65	P4	C 1500	Heptode Sect.
14S7	12.6	JR-4307-5	14	B	66	P4	C 1650	Triode Sect.
14V7	12.6	JR-6237-4	8	B	80	P4	E 4000	
14W7	12.6	JR-6237-5	8	B	80	P4	E 4000	
14X7	12.6	JR-3204-0	11	B	38	P4	D 1000	Triode Sect.
14X7	12.6	JR-0504-0	0	A	77	P1	-----	Diode No. 1
14X7	12.6	JR-0607-0	0	A	77	P1	-----	Diode No. 2
14Y4	12.6	JR-0607-0	0	A	45	P3	-----	Plate No. 1
14Y4	12.6	JR-0307-0	0	A	45	P3	-----	Plate No. 2
15A6	12.6	EV-2713-6	8	B	89	P4	E 7500	
15CW5	12.6	EV-2793-0	43	B	89	P4	E 6000	SET "LINE ADJUST" AT 110 ON 200 SCALE.
15EW6	12.6	ET-1562-7	10	B	87	P4	E10750	SET LINE ADJUST AT 110 ON 200 SCALE
15HB6	12.6	EV-2781-9	12	A	87	P4	F15500	SET "LINE ADJUST" AT 110 ON 200 SCALE.
15KY8	12.6	EV-2673-0	43	B	89	P4	E 5600	PENT. SECT. SET "LINE ADJUST" TO 875 ON 1500 SCALE
15KY8	12.6	EV-9801-0	19	B	48	P4	C 1000	Triode Sect.
17AV5	20.0	HS-1583-0	28	B	89	P4	E 5500	PLATE VOLTS-LOW SET CATH. ACT. SW. TO LIFE TEST POS.
17AX4	20.0	JX-0503-0	0	B	40	P3	-----	SET CATH ACT. SW. TO LIFE TEST POS.
17AY3	20.0	EV-0209-0	0	B	43	P3	-----	SET LINE ADJUST AT 94 ON 200 SCALE
17BH3	20.0	EV-0209-0	0	B	43	P3	-----	USE HICKOK ADAPTER CODE NO. 1050-144
17BQ6	20.0	HS-5048-0	47	B	88	P4	D 4200	SET LINE ADJUST AT 94 ON 200 SCALE
17BS3	20.0	EV-0209-0	0	A	45	P3	-----	USE HICKOK ADAPTER CODE NO. 1050-144
17C5	20.0	ET-2761-0	13	B	89	----	E 7500	Cap=P
17CA5	20.0	ET-2761-0	20	B	88	P4	E 5000	SET "LINE ADJUST" AT 50 ON 200 SCALE USE HICKOK ADAPTER CODE NO. 1050-144
17CU5	20.0	ET-2761-0	38	B	86	P4	D 4100	HOLD DOWN P1 AND PRESS P4 SET CATH ACT SW. TO LIFE TEST POS.
17D4	20.0	HY-0503-0	0	B	40	P3	-----	SET CATH. ACT. SWITCH TO LIFE TEST POS.
17DE4	20.0	HY-0503-0	0	B	49	P3	-----	SET "LINE ADJUST" AT 99 ON 200 SCALE
17DM4	20.0	HY-0503-0	0	B	49	P3	-----	SET CATH ACT SWITCH TO LIFE TEST POS.
17DQ4	20.0	JX-0503-0	0	B	43	P3	-----	
17DQ6	20.0	HS-5048-0	36	B	87	----	E 5000	CAP P HOLD DOWN P1 AND PRESS P4 (CAP=P, HOLD DOWN P1 AND

17DE4	20.0	HY-0503-0	0	B 49	P3	-----	
17DM4	20.0	HY-0503-0	0	B 49	P3	-----	
17DQ4	20.0	JX-0503-0	0	B 43	P3	-----	
17DQ6	20.0	HS-5048-0	36	B 87	----	E 5000	CAP-P. HOLD DOWN P1 AND PRESS P4
17GJ5	20.0	EV-6073-0	31	B 89	----	E 7000	[CAP-P. HOLD DOWN P1 AND PRESS P4. SET CATH. ACT. SW. TO LIFE TEST POS. USE HICKOK ADAPTER (CODE NO. 1508-144)
17GT5	20.0	EV-6973-0	31	B 89	----	E 7000	(HOLD DOWN P1 AND PRESS P4. SET CATH. ACT. SW. TO LIFE TEST POS. USE HICKOK ADAPTER CODE NO. 1050-144)
17GW6	20.0	HS-5048-0	31	B 89	----	E 7000	[CAP-P. HOLD DOWN P1 AND PRESS P4. SET CATH. ACT. SW. TO LIFE TEST POS. SET CATH. ACT SW. TO LIFE TEST POS.
17H3	20.0	EV-0301-0	0	B 40	P3	-----	PENT. SECT. SET CATH. ACT. SW. TO LIFE TEST POS.
17HC8	20.0	EV-3672-0	17	B 87	P4	D 4600	Triode Sect.
17HC8	20.0	EV-1908-0	10	B 71	P4	C 2000	[CAP-P. HOLD DOWN P1 AND PRESS P4. SET CATH. ACT. SW. TO LIFE TEST POS. USE HICKOK ADAPTER CODE NO. 1050-144
17JB6	20.0	EV-2013-8	31	B 89	----	E 7000	TRIODE NO. 1. SET CATH. ACT. SW. TO LIFE TEST POS.
17JK8	20.0	EV-7608-9	23	B 77	P4	C 2400	Triode No. 2
17JK8	20.0	EV-2103-9	18	B 89	P4	E 5500	SET CATH. ACT. SWITCH TO LIFE TEST POS.
17L6	20.0	HS-5348-0	40	B 89	P4	E 6000	HOLD DOWN P1 AND PRESS P4. SET CATH. ACT SW. TO LIFE TEST POS.
17R5	20.0	ET-2761-0	13	B 88	----	E 6000	
18A5	20.0	HS-1583-0	40	B 87	P4	D 4800	
18DZ8	20.0	EV-3672-0	25	B 87	P4	D 4600	Pent. Sect.
18DZ8	20.0	EV-1908-0	17	B 34	P4	C 850	Triode Sect.
18FW6	20.0	ET-1567-2	14	B 71	P4	D 2200	
18FX6	20.0	ET-1562-7	12	B 42	P4	C 1000	Ampl. Sect.
18FX6	20.0	ET-1602-7	18	B 88	P4	E 6000	Osc. Sect.
18FY6	20.0	ET-1702-0	12	B 53	P4	G 700	Triode Sect.
18FY6	20.0	ET-0602-0	0	A 32	P1	-----	Diode No. 1
18FY6	20.0	ET-0502-0	0	A 32	P1	-----	Diode No. 2
18GD6A	20.0	ET-1567-2	15	B 71	P4	C 2000	
18HB8	20.0	EV-9768-0	24	B 81	P4	D 3000	PENT. SECT. SET CATH. ACT. SWITCH TO LIFE TEST POS.
18HB8	20.0	EV-1302-0	15	B 81	P4	D 3000	TRIODE SECT. SET CATH. ACT SWITCH TO LIFE TEST POS.
19AQ5	20.0	ET-1562-0	18	B 84	P4	D 3700	
19AU4	20.0	HY-0503-0	0	B 58	P3	-----	
19BG6	20.0	HS-5083-0	18	B 89	P4	E 6000	Cap-P
19C8	20.0	EV-8907-0	14	B 48	P4	D 1250	Triode Sect.
19C8	20.0	EV-8607-0	14	A 78	P1	-----	Diode No. 1
19C8	20.0	EV-8203-0	14	A 78	P1	-----	Diode No. 2
19C8	20.0	EV-8107-0	14	A 78	P1	-----	Diode No. 3
19CL8A	20.0	EV-9678-0	13	B 83	P4	D 3500	Tetrode Sect.
19CL8A	20.0	EV-1203-0	12	B 89	P4	E 7000	Triode Sect.
19EA8	20.0	EV-2637-0	13	B 79	P4	D 3600	Pent. Sect.
19EA8	20.0	EV-9108-0	11	B 88	P4	E 8500	Triode Sect.
19EZ8	20.0	EV-9800-0	14	B 79	P4	D 3100	Triode No. 1
19EZ8	20.0	EV-7600-0	14	B 79	P4	D 3100	Triode No. 2
19EZ8	20.0	EV-2301-0	16	B 82	P4	D 3200	Triode No. 3
19HR6	20.0	ET-1567-2	10	B 85	P4	E 6250	
19HS6	20.0	ET-1567-2	15	B 81	P4	D 4100	
19HV8	20.0	EV-9678-0	10	B 81	P4	E 5000	Pent. Sect.
19HV8	20.0	EV-1203-0	14	B 55	P4	C 1300	Triode Sect.
19J6	20.0	ET-5207-6	17	B 88	P4	E 5300	Triode No. 1
19J6	20.0	ET-6107-5	17	B 88	P4	E 5300	Triode No. 2
19JN8	20.0	EV-9678-0	17	B 90	P4	E 7000	Pent. Sect.
19JN8	20.0	EV-1203-0	17	B 85	P4	E 6000	Triode Sect.
19KG8	20.0	EV-9678-0	10	B 82	P4	D 4100	Pent. Sect.
19KG8	20.0	EV-2103-0	15	B 88	P4	E 7250	Triode Sect.
19T8	20.0	EV-8907-6	15	B 48	P4	D 12 0	Triode Sect.

19T8	20.0	EV-8907-6	15	B 48	P4	D 1200	Triode Sect.
19T8	20.0	EV-0607-1	0	A 78	P1	-----	Diode No. 1
19T8	20.0	EV-0203-7	0	A 78	P1	-----	Diode No. 2
19T8	20.0	EV-0107-8	0	A 78	P1	-----	Diode No. 3
19V8	20.0	EV-6103-8	15	B 48	P4	D 1200	Triode Sect.
19V8	20.0	EV-0903-2	0	A 30	P1	-----	Diode No. 1
19V8	20.0	EV-0708-6	0	A 78	P1	-----	Diode No. 2
19V8	20.0	EV-0203-8	0	A 78	P1	-----	Diode No. 3
19X3	20.0	EV-0903-0	0	B 50	P3	-----	
19X8	20.0	EV-7986-1	10	B 86	P4	D 4600	Pent. Sect.
19X8	20.0	EV-2306-1	15	B 89	P4	E 5800	Triode Sect.
19Y3	20.0	EV-0903-0	0	B 50	P3	-----	
20EQ7	20.0	EV-2763-1	20	B 44	P4	C 1300	Pent. Sect.
20EQ7	20.0	EV-0803-0	0	A 30	P1	-----	Diode Sect.
20EZ7	20.0	CR-8709-0	14	B 48	P4	D 1250	Triode No. 1
20EZ7	20.0	CR-5604-0	14	B 48	P4	D 1250	Triode No. 2
21A6	20.0	EV-2083-9	42	B 88	P4	E 6000	Cap=P
21EX6	20.0	HS-5083-0	53	B 90	P4	E 5500	Cap=P
Tubes indicating shorts: Re-test using HS-5013-0							
22BH3	20.0	EV-0209-0	0	B 48	P3	-----	(SET "LINE ADJUST" AT 110 ON 200 SCALE, USE HICKOK ADAPTER CODE NO. 1050-144)
22DE4	25.0	HY-0503-0	0	B 49	P3	-----	
22JG6	25.0	EV-2973-6	37	B 91	..	E 8000	(SET "LINE ADJUST" AT 90 ON 200 SCALE, HOLD DOWN P1 AND PRESS P4, USE HICKOK ADAPTER CODE NO. 1050-144)
25A6	25.0	HS-5348-0	18	B 70	P4	D 2300	
25AV5	25.0	HS-1583-0	28	B 89	P4	E 5500	Plate Volts=Low
25AX4	25.0	HY-0503-0	0	B 40	P3	-----	
25BK5	25.0	EV-3186-0	0	B 89	P4	E 7500	
25BQ6	25.0	HS-5048-0	28	B 89	P4	E 5500	CAP=P. PLATE VOLTS=LOW HOLD DOWN P1 AND PRESS P4
25C5	25.0	ET-2761-0	13	B 89	---	E 7500	
25C6	25.0	HS-5348-0	41	B 88	P4	E 5500	
25CA5	25.0	DU-2761-0	0	B 88	P4	E 7000	Plate Volts=Low
25CD6	25.0	HS-5083-0	29	B 88	P4	E 6000	CAP=P. PLATE VOLTS=LOW
25CU6	25.0	HS-5048-0	28	B 89	P4	E 5500	CAP=P. PLATE VOLTS=LOW
25DK4	25.0	ET-0507-0	0	B 57	P3	-----	
25DN6	25.0	HS-5083-0	28	B 89	-----	E 9000	CAP=P HOLD DOWN P1 AND PRESS P4
25DQ6	25.0	HS-5048-0	36	B 87	-----	E 5000	CAP=P. HOLD DOWN P1 AND PRESS P4
25EC6	25.0	HS-5083-0	69	B 86	P4	D 4000	Cap=P
25EH5	25.0	ET-2761-0	13	B 88	P4	E 7200	
25F5	25.0	ET-2761-0	30	B 86	P4	D 4000	
25L6	25.0	HS-5348-1	25	B 88	---	E 6000	HOLD DOWN P1 AND PRESS P4
25W4	25.0	HY-0503-0	0	B 60	P3	-----	
25W6	25.0	HS-5348-0	25	B 88	---	E 6000	HOLD DOWN P1 AND PRESS P4
25Z6	25.0	HS-0508-1	0	B 30	P3	-----	Plate No. 1
25Z6	25.0	HS-0304-1	0	B 30	P3	-----	Plate No. 2
26A6	25.0	ET-1567-2	8	B 78	P4	D 3000	
26A7	25.0	HW-1852-3	8	B 76	P4	E 5700	PENT. NO. 1. PLATE VOLTS=LOW
26A7	25.0	HW-3452-1	8	B 76	P4	E 5700	PENT. NO. 2. PLATE VOLTS=LOW
26BK6	25.0	ET-1702-5	14	B 48	P4	D 1250	Triode Sect.
26BK6	25.0	ET-0602-5	0	A 53	P1	-----	Diode No. 1
26BK6	25.0	ET-0502-7	0	A 53	P1	-----	Diode No. 2
26C6	25.0	ET-1702-0	21	B 72	P4	C 1900	Triode Sect.
26C6	25.0	ET-1602-0	21	A 30	P1	-----	Diode No. 1
26C6	25.0	ET-1502-0	21	A 30	P1	-----	Diode No. 2
26D6	25.0	ET-7562-1	0	B 35	---	C 800	AMPL. SECT HOLD DOWN P1 AND PRESS P4
26D6	25.0	ET-1602-7	20	B 88	P4	E 6500	Osc. Sect.
26E6	25.0	HS-5348-0	0	B 89	---	E 6500	HOLD DOWN P1 AND PRESS P4
26Z5W	25.0	EV-0608-0	0	B 20	P3	-----	

26C6	25.0	ET-1702-0	21	B 72	P4	-----	Triode Sect.
26C6	25.0	ET-1602-0	21	A 30	P1	-----	Diode No. 1
26C6	25.0	ET-1502-0	21	A 30	P1	-----	Diode No. 2
26D6	25.0	ET-7562-1	0	B 35	----	C 800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
26D6	25.0	ET-1602-7	20	B 88	P4	E 6500	Osc. Sect.
26E6	25.0	HS-5348-0	0	B 89	----	E 6500	HOLD DOWN P1 AND PRESS P4
26Z5W	25.0	EV-0608-0	0	B 30	P3	-----	Plate No. 1
26Z5W	25.0	EV-0103-0	0	B 30	P3	-----	Plate No. 2
28D7	25.0	JR-7536-2	9	B 81	P4	D 3400	PENT. NO. 1 PLATE VOLTS=LOW
28D7	25.0	JR-2436-7	9	B 81	P4	D 3400	PENT. NO. 2 PLATE VOLTS=LOW
32	2.0	ER-0230-0	20	B 20	----	C 640	CAP=G. HOLD DOWN P1 AND PRESS P4
32ET5	35.0	ET-2761-0	38	B 85	P4	D 4200	
34GD5	35.0	ET-2761-0	39	B 87	P4	D 4400	
35B5	35.0	ET-1562-0	0	B 87	P4	E 5000	Plate Volts=Low
35C5	35.0	ET-2761-0	0	B 87	P4	E 5000	Plate Volts=Low
35CD6	35.0	HS-5083-0	29	B 88	P4	E 6000	CAP=P. PLATE VOLTS LOW
35DZ8	35.0	EV-3672-0	25	B 87	P4	D 4600	Pent. Sect.
35DZ8	35.0	EV-1908-0	17	B 34	P4	C 850	Triode Sect.
35EH5	35.0	ET-2761-0	15	B 87	P4	E 7250	
35GL6	35.0	ET-2751-0	35	B 88	P4	E 5300	
35HB8	35.0	EV-9768-0	24	B 81	P4	D 3000	Pent. Sect.
35HB8	35.0	EV-1302-0	15	B 81	P4	D 3000	Triode Sect.
35L6	35.0	HS-5348-0	0	B 87	P4	E 5000	Plate Volts=Low
35W4	BLST	ET-0167-0	----	----	----	-----	Short on 1-2-3-5
35W4	35.0	ET-0507-0	0	B 50	P3	-----	Rect. Sect.
35Y4	BLST	JR-0247-0	----	----	----	-----	Short on 1-2-3-5
35Y4	35.0	JR-0207-0	0	B 50	P3	-----	Rect. Sect.
35Z3	35.0	JR-0207-0	0	B 50	P3	-----	
35Z5	BLST	HS-0538-0	----	----	----	-----	Short on 1-2-3-5
35Z5	35.0	HS-0508-0	0	B 50	P3	-----	Rect. Sect.
36AM3	35.0	ET-0507-0	0	B 49	P3	-----	
40FR5	40.0	ET-2761-0	15	B 85	P4	E 5250	
45	2.5	ER-3200-0	57	B 65	P4	C 1850	
50A5	50.0	JR-6237-0	25	B 88	----	E 6000	HOLD DOWN P1 AND PRESS P4
50B5	50.0	ET-1562-0	13	B 89	----	E 7500	HOLD DOWN P1 AND PRESS P4
50BK5	50.0	EV-3186-0	0	B 89	P4	E 7500	
50BM8	50.0	EV-3672-0	26	B 84	P4	D 4000	Pent. Sect.
50BM8	50.0	EV-1908-0	0	B 73	P4	C 2500	Triode Sect.
50C5	50.0	ET-2761-0	13	B 89	----	E 7500	HOLD DOWN P1 AND PRESS P4
50C6	50.0	HS-5348-0	41	B 88	P4	E 5500	
50DC4	50.0	ET-0507-0	0	B 54	P3	-----	
50EH5	50.0	ET-2761-0	13	B 88	P4	E 7200	
50FA5	50.0	ET-2761-0	39	B 87	P4	D 4400	
50FE5	50.0	HS-5348-0	30	B 93	P4	E 6300	
50FK5	50.0	ET-2761-0	21	B 84	P4	D 4750	
50FY8	50.0	EV-3672-0	32	B 89	P4	E 4500	Pent. Sect.
50FY8	50.0	EV-1908-0	21	B 65	P4	C 1500	Triode Sect.
50HC6	50.0	ET-2751-0	13	B 88	P4	E 7200	
50HK6	50.0	ET-2751-0	13	B 89	----	E 7500	HOLD DOWN P1 AND PRESS P4
50L6	50.0	HS-5348-0	25	B 88	----	E 6000	HOLD DOWN P1 AND PRESS P4
50X6	50.0	JR-0607-5	0	B 45	P3	-----	Plate No. 1
50X6	50.0	JR-0302-5	0	B 45	P3	-----	Plate No. 2
50Y7	BLST	HS-0060-0	----	----	----	-----	Short on 1-2-3-5
50Y7	50.0	HS-0508-0	0	B 45	P3	-----	Plate No. 1
50Y7	50.0	HS-0304-0	0	B 45	P3	-----	Plate No. 2
52	6.3	FR-3240-0	0	B 72	P4	C 2400	
53	2.5	HR-5604-2	17	B 65	P4	C 1500	Triode No. 1
53	2.5	HR-3204-6	17	B 65	P4	C 1500	Triode No. 2
55	2.5	GR-0205-0	42	B 47	P4	C 975	TRIODE SECT CAP=J.R.

52	6.3	FR-3240-0	0	B 72	P4	C 2400	Triode No. 1
53	2.5	HR-5604-2	17	B 65	P4	C 1500	Triode No. 2
53	2.5	HR-3204-6	17	B 65	P4	C 1500	Triode No. 2
55	2.5	GR-0205-0	42	B 47	P4	C 975	TRIODE SECT. CAP=G
55	2.5	GR-0405-0	42	A 30	P1	-----	Diode No. 1
55	2.5	GR-0305-0	42	A 30	P1	-----	Diode No. 2
56	2.5	FR-3204-0	32	B 63	P4	C 1450	
57	2.5	GR-0235-4	21	B 57	P4	C 1225	Cap=G
58	2.5	GR-0235-4	17	B 67	P4	C 1600	Cap=G
59	2.5	HR-4236-5	0	B 68	P4	C 2000	
60FX5	50.0	ET-2761-0	15	B 88	P4	E 7750	
KT66	6.3	HS-5348-1	20	B 89	P4	E 6300	

A 2-YEAR ROLL CHART SUBSCRIPTION— SUBSCRIBE TODAY!

70L7	75.0	HS-5346-0	10	B 89	----	E 7500	PENT. SECT. HOLD DOWN P1 AND PRESS P4
70L7	75.0	HS-0801-3	0	B 55	P3	-----	Rect. Sect.
75	6.3	GR-0205-0	11	B 39	P4	D 1100	TRIODE SECT. CAP=G
75	6.3	GR-0405-2	11	A 32	P1	-----	Diode No. 1
75	6.3	GR-0305-2	11	A 32	P1	-----	Diode No. 2
76	6.3	FR-3204-0	32	B 63	P4	C 1450	
77	6.3	GR-0235-4	18	B 58	P4	C 1250	Cap=G
78	6.3	GR-0235-4	13	B 63	P4	C 1450	Cap=G
80	5.0	ER-0300-0	0	A 36	P3	-----	Plate No. 1
80	5.0	ER-0200-0	0	A 27	P3	-----	Plate No. 2
83	5.0	ER-0300-0	0	B 60	P3	-----	Plate No. 1
83	5.0	ER-0200-0	0	B 57	P3	-----	Plate No. 2
83V	5.0	ER-0300-0	0	B 60	P3	-----	Plate No. 1
83V	5.0	ER-0200-0	0	B 60	P3	-----	Plate No. 2
84	6.3	FR-0304-0	0	B 25	P3	-----	Plate No. 1
84	6.3	FR-0204-0	0	B 25	P3	-----	Plate No. 2
KT88	6.3	HS-5348-1	13	B 90	P4	F 7000	
89/89Y	6.3	GR-0235-4	29	B 63	P4	C 1550	Cap=G
90C1	See Top of Chart.						
117L7/M7	117.0	HS-4358-0	28	B 85	P4	D 4000	Pent. Sect.
117L7/M7	117.0	HS-0601-0	0	B 55	P3	-----	Rect. Sect.
117N7	117.0	HS-4356-0	30	B 87	P4	E 5000	Pent. Sect.
117N7	117.0	HS-0008-0	0	B 55	----	-----	RECT. SECT. MAKE SHORTS TEST RECT. SECT. REVERSE METER. MAKE NO SHORTS TEST
117N7	117.0	HS-0800-0	0	B 55	P3	-----	
117P7	117.0	HS-4356-0	28	B 85	P4	D 4000	Pent. Sect.
117P7	117.0	HS-0008-0	0	B 55	----	-----	RECT. SECT. MAKE SHORTS TEST RECT. SECT. REVERSE METER MAKE NO SHORTS TEST
117P7	117.0	HS-0800-0	0	B 55	P3	-----	
117Z3	117.0	ET-0506-0	0	B 50	P3	-----	
117Z6	117.0	HS-0508-0	0	B 50	P3	-----	Plate No. 1
117Z6	117.0	HS-0304-0	0	B 50	P3	-----	Plate No. 2
150B2	See top of Chart						
X-155	6.3	EV-7608-9	14	B 88	P4	E 7000	Triode No. 1
X-155	6.3	EV-2103-9	14	B 88	P4	E 7000	Triode No. 2
CAA322	6.3	HS-0500-0	0	A 58	P3	-----	USE HICKOK ADAPTER CODE NO. 1030-50
GL502A	6.3	HS-5308-6	#	B 95	P5	-----	Strikes at about 28
CK502AX	1.1	DV-4120-0	17	A 35	P4	G 550	
CK503AX	1.1	DV-4120-0	20	A 35	P4	G 550	
CK506AX	1.1	DV-4120-0	32	A 32	P4	G 500	
CK512AX	0.6	DV-4120-0	15	-----	P4	G 160	OK above 100
CK518AX	1.1	DV-4120-0	18	A 37	P4	G 550	
CK522AX	1.1	DV-4120-0	28	A 37	P4	G 550	

CK506AX	1.1	DV-4120-0	32	A 32	P4	G	500	
CK512AX	0.6	DV-4120-0	15	P4	G	160	OK above 100
CK518AX	1.1	DV-4120-0	18	A 37	P4	G	550	
CK522AX	1.1	DV-4120-0	20	A 24	P4	G	450	
CK523AX	1.1	DV-4120-0	28	A 14	P4	G	360	
CK524AX	1.1	DV-4120-0	45	A 0	P4	G	300	
CK525AX	1.1	DV-4120-0	29	A 0	P4	G	325	
CK526AX	1.1	DV-4120-0	34	A 17	P4	G	400	
CK527AX	1.1	DV-4120-0	15	P4	G	225	OK above 150
CK528AX	1.1	DV-4120-0	17	A 25	P4	G	450	
CK529AX	1.1	DV-4120-0	39	A 10	P4	G	350	
CK533AX	1.1	DV-4120-0	23	A 24	P4	G	400	
CK535AX	1.1	DV-4120-0	39	A 10	P4	G	350	
CK541DX	1.1	DV-4120-0	16	A 20	P4	G	425	
CK542DX	1.1	DV-4120-0	35	A 0	P4	G	325	
CK543DX	0.6	DV-4210-0	0	A 0	P1		OK ABOVE 200 ON 1500 SCALE
CK544DX	1.1	DV-4120-0	15	A 0	P4	G	325	
CK546DX	1.4	DV-4120-0	20	A 24	P4	G	450	MAKE NO GAS TEST
GL546	6.3	ET-1752-0	#	B 40	P3		Strikes at about 78
CK547DX	1.1	DV-4120-0	15	A 13	P4	G	425	
CK548DX	1.1	DV-4120-0	29	A 0	P4	G	300	
629	3.0	FR-3204-0	#	B 95	P5		Strikes at about 22
801A	7.5	ER-3200-0	0	B 60	P4	C	1500	
802	6.3	HR-4036-5	0	B 69	P4	C	2000	Cap=P
807	6.3	FR-3024-0	28	B 87	P4	D	3800	Cap=P
809	6.3	ER-3000-0	0	B 68	P4	C	1700	Cap=P
811A	6.3	ER-3000-0	0	B 60	P4	C	1350	Cap=P
812	6.3	ER-3000-0	0	B 73	P4	C	2000	Cap=P
815	6.3	JV-7043-2	20	B 86	P4	D	4000	PENT NO 1 LEFT CAP=P
815	6.3	BV-2043-7	20	B 86	P4	D	4000	PENT, NO. 2 RIGHT CAP=P
816	3.0	ER-0000-0	0	B 58	P3		Cap=P
829B	6.3	HS-4561-0	0	B 80	P4	E	4000	Plate No. 1
829B	6.3	HS-4861-0	0	B 80	P4	E	4000	Plate No. 2
832A	6.3	HS-4561-0	13	B 73	P4	D	2000	USE HICKOK ADAPTER CODE NO. 1050-33
832A	6.3	HS-4861-0	13	B 73	P4	D	2000	Plate No. 1
837	12.6	HR-4036-5	0	B 79	P4	D	3000	Plate No. 2 USE HICKOK ADAPTER CODE NO. 1050-33
841	7.5	ER-3200-0	15	B 48	P4	C	1050	Cap=P
842	7.5	ER-3200-0	52	B 48	P4	C	1150	
843	2.5	FR-3204-0	12	B 64	P4	C	1625	
864	1.1	ER-3200-0	45	B 21	P4	C	650	
865	7.5	ER-3020-0	35	B 18	P4	C	625	Cap=P
866A	4.3	ER-0000-0	0	B 50	P3		Cap=P
874		See top of Chart						
879	2.5	ER-0000-0	0	B 88	P5		Cap=P
884	6.3	HS-5308-0	#	B 95	P5		Strikes at about 68
885	2.5	FR-3204-0	#	B 95	P5		Strikes at about 68
950	2.0	FR-3240-0	45	B 45	P4	C	950	
951	2.0	ER-0230-0	15	A 48	P4	G	650	Cap=G
954	6.3	GR-8037-4	23	B 53	P4	C	1100	Cap=P
955	6.3	GR-4307-0	24	B 72	P4	C	1900	
956	6.3	GR-8037-4	13	B 62	P4	D	1500	Cap=P
957	1.4	GR-4300-0	33	B 21	P4	C	650	
958	1.4	GR-4300-0	39	B 56	P4	C	1200	
959	1.4	GR-8030-0	20	B 15	C	600	CAP=P HOLD DOWN P1 AND PRESS P4
CK1042	...	AP-0105-0	0	B 0	P2		
1201	6.3	JS-1304-0	18	B 83	P4	D	3000	
1203	6.3	JR-0407-0	0	A 70	P1		Diode
1204	6.3	HS-5314-0	10	B 65	P4	D	1600	

958	1.4	GR-4300-0	39	B	56	P4	C	1200	
959	1.4	GR-8030-0	20	B	15	C	600	CAP=P HOLD DOWN P1 AND PRESS P4
CK1042	AP-0105-0	0	B	0	P2		
1201	6.3	JS-1304-0	18	B	83	P4	D	3000	
1203	6.3	JR-0407-0	0	A	70	P1		Diode
1204	6.3	HS-5314-0	10	B	65	P4	D	1600	
1222	6.3	GR-4237-8	17	B	88	P4	E	5000	
1229	2.0	ER-0230-0	20	B	20	C	640	CAP=G, HOLD DOWN P1 AND PRESS P4
1230	2.0	ER-3200-0	43	B	42	P4	C	900	
1231	6.3	JR-6237-4	10	B	83	P4	E	4000	
1232	6.3	JR-6237-4	11	B	82	P4	E	4000	
1237	2.5	HS-0300-0	0	B	70	P3		PLATE NO 1 SHORT ON 1-2-3-4 ON TESTERS HAVING SERIAL NUMBER PREFIX 149-.... PLATE NO. 2 SHORT ON 1-2-3-4 ON TESTERS HAVING SERIAL NUMBER PREFIX 149-....
1237	2.5	HS-0600-0	0	B	70	P3		
1273	6.3	JR-6237-4	8	B	73	P4	D	2275	
1274	6.3	HS-0508-3	0	B	20	P3		Plate No. 1
1274	6.3	HS-0308-5	0	B	20	P3		Plate No. 2
1280	12.6	JR-6237-4	8	B	73	P4	D	2275	
1284	12.6	JR-6237-4	23	B	73	P4	C	2000	
1285	25.0	HS-5348-0	0	B	89	P4	E	8000	Plate Volts=Low
1293	1.4	JR-6200-0	28	B	60	P4	C	1300	
1294	1.4	JR-0407-0	0	A	48	P1		
1299	2.5	JR-6230-0	16	B	76	D	2400	HOLD DOWN P1 AND PRESS P4
1603	6.3	GR-0235-4	21	B	57	P4	C	1225	Cap=G
1609	1.1	FR-3240-0	0	B	27	C	700	HOLD DOWN P1 AND PRESS P4 CAP GRID. CAP=G
1612	6.3	HS-0348-5	10	B	48	P4	D	1100	Pin Grid
1612	6.3	HS-5348-1	14	B	48	P4	D	1100	
1613	6.3	HS-5348-0	23	B	70	P4	C	2000	
1614	6.3	HS-5348-1	17	B	88	P4	E	5000	
1619	2.5	HS-5340-8	12	B	83	P4	D	3400	Cap=G
1620	6.3	HS-0348-5	21	B	57	P4	C	1225	
1621	6.3	HS-5348-0	23	B	70	P4	C	2000	
1622	6.3	HS-5348-0	17	B	88	P4	E	5000	
1623	6.3	ER-3000-0	0	B	75	P4	C	2200	Cap=P
1624	2.5	FR-3020-0	0	B	84	P4	D	3500	Cap=P
1631	12.6	HS-5348-1	17	B	88	P4	E	5000	
1632	12.6	HS-5348-0	25	B	88	E	6000	HOLD DOWN P1 AND PRESS P4
1633	25.0	HY-4506-0	23	B	79	P4	D	2600	Triode No. 1
1633	25.0	HY-1203-0	23	B	79	P4	D	2600	Triode No. 2
1634	12.6	HY-4506-1	12	B	53	P4	D	1325	Triode No. 1
1634	12.6	HY-3206-1	12	B	53	P4	D	1325	Triode No. 2
1635	6.3	HS-4308-0	0	B	35	P4	C	800	Triode No. 1
1635	6.3	HS-5608-0	0	B	35	P4	C	800	Triode No. 2
1642	6.3	HR-4506-0	35	B	62	P4	C	1375	Triode No. 1
1642	6.3	HR-0302-0	35	B	62	P4	C	1375	TRIODE NO. 2 CAP=G
1644	12.6	HW-1852-3	0	B	68	P4	C	1700	Pent. No. 1
1644	12.6	HW-3452-1	0	B	68	P4	C	1700	Pent. No. 2
1658	2.0	ER-3200-0	43	B	42	P4	C	900	
1851	6.3	HS-0348-5	13	B	86	P4	E	6000	Cap=G
1852	6.3	HS-4865-3	13	B	86	P4	E	6000	
1853	6.3	HS-4865-3	0	B	84	P4	D	4000	
2050	6.3	HS-5308-6	#	B	95	P5		Strikes at about 28
2051	6.3	HS-5308-6	#	B	95	P5		Strikes at about 28
5516	6.3	HS-5031-0	0	B	85	P4	D	4000	CAP=P, SHORT ON 1
5556	4.3	ER-3200-0	26	B	47	P4	C	980	
5610	6.3	ET-6102-0	27	B	85	P4	D	4000	
5618	6.3	BX-6234-0	0	B	81	P4	D	3000	
5633	6.3	EW-3051-2	12	B	75	P4	D	2400	Top Lead=P
5634	6.3	EW-3051-2	12	B	80	P4	E	3500	Top Lead=P

5556	4.3	ET-3102-0	27	B 85	P4	D 4000	
5610	6.3	ET-6234-0	0	B 81	P4	D 3000	
5618	6.3	BX-6234-0	0	B 81	P4	D 3000	Top Lead=P
5633	6.3	EW-3051-2	12	B 75	P4	D 2400	Top Lead=P
5634	6.3	EW-3051-2	12	B 80	P4	E 3500	Triode No. 1
5635	6.3	DW-1708-4	12	B 83	P4	D 3800	Triode No. 2
5635	6.3	DW-2508-4	12	B 83	P4	D 3800	
5636	6.3	DW-1572-4	11	B 73	P4	D 2000	
5637	6.3	DU-2105-0	10	B 73	P4	D 2700	Plate Volts=Low
5638	6.3	EW-3152-0	22	B 71	P4	D 2000	
5639	6.3	DW-1572-0	15	B 87	P4	E 5500	
5640	6.3	DW-1578-0	44	B 87	P4	E 5000	
5641	6.3	DW-0205-0	0	B 0	P3	-----	
5642	1.1	BS-0000-0	0	G 0	P3	-----	TOP LEAD=P. CONNECT FIL LEADS TO PINS 1 AND 2. READ RANGE A SCALE ON METER
5643	6.3	DW-7105-2	#	B 50	P3	-----	Strikes at about 78
5644		See top of Chart					
5645	6.3	FT-4102-0	25	B 81	P4	D 2700	
5646	6.3	FT-4102-0	9	B 62	P4	D 1500	Plate Volts=Low
5647	6.3	CT-0104-0	0	A 80	P1	-----	Diode
5651		See top of Chart					
5654	6.3	ET-1562-0	10	B 83	P4	D 4400	
5659	12.6	HS-5348-0	18	B 81	P4	D 3000	
5660	12.6	HS-0368-0	22	B 48	P4	C 1000	PENT SECT CAP=G
5660	12.6	HS-0568-0	22	A 32	P1	-----	Diode No. 1
5660	12.6	HS-0468-0	22	A 32	P1	-----	Diode No. 2
5661	12.6	HS-4865-3	10	B 69	P4	D 2000	
5662	6.3	ET-1705-0	#	B 95	P5	-----	Strikes at about 24
5663	6.3	ET-1752-0	#	B 50	P3	-----	Strikes at about 76
5670	6.3	KR-7608-0	16	B 88	P4	E 5000	Triode No. 1
5670	6.3	KR-3402-0	16	B 88	P4	E 5000	Triode No. 2
5672	1.1	DV-4120-0	27	A 33	P4	G 500	
5676	1.1	ES-3100-0	26	B 67	P4	C 1600	
5677	1.1	ES-3100-0	38	B 21	P4	C 650	
5678	1.1	DV-4120-0	8	A 55	P4	G 850	
5679	6.3	JR-0607-5	0	A 72	P1	-----	Diode No. 1
5679	6.3	JR-0302-5	0	A 72	P1	-----	Diode No. 2
5686	6.3	EV-2763-0	10	B 81	P4	D 3100	
5687	12.6	EV-7906-1	28	B 89	P4	E 7500	Triode No. 1
5687	12.6	EV-2103-9	28	B 89	P4	E 7500	Triode No. 2
5690	6.3	HW-0508-3	0	B 50	P3	-----	Unit No. 1
5690	6.3	CR-0304-5	0	B 50	P3	-----	Unit No. 2
5691	6.3	HY-4506-2	13	B 59	P4	D 1600	Triode No. 1
5691	6.3	HY-1203-5	13	B 59	P4	D 1600	Triode No. 2
5692	6.3	HY-4506-2	23	B 75	P4	D 2200	Triode No. 1
5692	6.3	HY-1203-5	23	B 75	P4	D 2200	Triode No. 2
5693	6.3	HS-4865-3	18	B 65	P4	D 1650	
5694	6.3	HS-4301-0	0	B 73	P4	C 2000	Triode No. 1
5694	6.3	HS-5608-0	0	B 73	P4	C 2000	Triode No. 2
5696	6.3	ET-1602-5	#	B 95	P5	-----	Strikes at about 27
5702	6.3	DU-7126-5	10	B 83	P4	D 4400	
5703	6.3	DU-5106-0	22	B 86	P4	E 5000	
5704	6.3	CT-0104-0	0	A 80	P1	-----	Diode
5718	6.3	DW-1805-7	10	B 88	P4	E 5500	Plate Volts=Low
5719	6.3	DW-1805-7	10	B 70	P4	D 2300	
5725	6.3	ET-1562-7	0	B 70	P4	C 1800	
5726	6.3	ET-0701-6	0	A 78	P1	-----	Diode No. 1
5726	6.3	ET-0205-6	0	A 78	P1	-----	Diode No. 2
5727	6.3	ET-1602-5	#	B 95	P5	-----	Stikes at about 26
5731	6.3	GR-4307-0	20	B 75	P4	C 2200	
5732	6.3	HS-0348-5	13	B 63	P4	C 1450	Cap=G

5727	6.3	ET-1602-5	20	B 75	P4	C 2200	
5731	6.3	GR-4307-0	20	B 75	P4	C 1450	Cap = G
5732	6.3	HS-0348-5	13	B 63	P4	C 850	
5742	4.3	ER-3200-0	10	B 39	P4	E 4000	
5744	6.3	CT-4105-0	7	B 81	P4	D 3200	
5749	6.3	ET-1567-2	0	B 79	P4	C 800	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
5750	6.3	ET-7562-1	0	B 35	----	E 6500	Osc. Sect.
5750	6.3	ET-1602-7	20	B 88	P4	D 1250	Triode No. 1
5751	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 2
5751	12.6	EV-2103-0	14	B 48	P4	D 1500	Triode No. 1
5755	12.6	EV-6807-3	0	B 56	P4	D 1500	Triode No. 2
5755	12.6	EV-3102-6	0	B 56	P4	E 7000	
5763	6.3	EV-9167-3	0	B 88	P4		
5783	See top of Chart						
5784	6.3	DU-7126-5	16	B 68	P4	D 1850	
5785	1.1	GX-0100-0	0	A 0	P1	-----	
5787	See top of Chart						
5812	6.3	ET-1560-2	28	B 86	P4	D 4300	
5814	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
5814	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
5823	OFF	AP-4301-0	0	B 90	----	-----	REVERSE METER HOLD DOWN P6 AND PRESS P5 RELEASE P5 BEFORE P6.
5824	25.0	HS-5348-0	20	B 88	P4	E 5000	Plate Volts = Low
5825	1.4	ER-0000-0	0	A 0	P5	-----	CAP = P. OK ABOVE 250 ON 1500 SCALE
5829	6.3	DV-0607-0	0	A 78	P1	-----	Diode No. 1
5829	6.3	DV-0102-0	0	A 78	P1	-----	Diode No. 2
5838	12.6	HS-0508-1	0	B 20	P3	-----	Plate No. 1
5838	12.6	HS-0308-1	0	B 20	P3	-----	Plate No. 2
5839	25.0	HS-0508-3	0	A 35	P3	-----	Plate No. 1
5839	25.0	HS-0308-5	0	A 35	P3	-----	Plate No. 2
5840	6.3	DW-1574-0	16	B 79	P4	D 3000	
5844	6.3	ET-5207-0	24	B 84	P4	D 3400	Triode No. 1
5844	6.3	ET-6107-0	24	B 84	P4	D 3400	Triode No. 2
5847	6.3	DZ-1684-0	13	B 88	P4	F10000	
5851	2.5	HR-8360-0	30	B 67	P4	C 1600	
5852	6.3	HS-0508-0	0	A 35	P3	-----	Plate No. 1
5852	6.3	HS-0308-0	0	A 35	P3	-----	Plate No. 2
5854	1.1	DV-4120-0	20	A 35	P4	G 550	
5875	1.1	DV-4120-0	13	B 63	P4	D 2000	
5879	6.3	EV-1873-9	20	B 48	P4	C 1000	
5881	6.3	HS-5348-1	17	B 88	P4	E 5000	
5886	1.1	DU-7120-0	57	-----	P4	G 160	OK above 100
5894	6.3	HS-4561-0	10	B 73	P4	C 2000	Plate No. 1
5894	6.3	HS-4861-0	10	B 73	P4	C 2000	Plate No. 2
5896	6.3	DW-0507-4	0	B 40	P3	-----	USE HICKOK ADAPTER CODE NO. 1050-33
5896	6.3	DW-0102-4	0	B 40	P3	-----	Plate No. 1
5897	6.3	DW-1805-0	19	B 88	P4	E 5000	Plate No. 2
5899	6.3	DW-1574-0	13	B 79	P4	D 3000	
5900	6.3	DW-1574-0	13	B 79	P4	D 3000	
5902	6.3	DW-1572-0	40	B 86	P4	D 4200	
5903	25.0	DW-0507-4	0	B 40	P3	-----	Plate No. 1
5903	25.0	DW-0102-4	0	B 40	P3	-----	Plate No. 2
5904	25.0	DW-1805-0	20	B 84	P4	D 3000	Plate Volts = Low
5905	25.0	DW-1572-0	30	B 67	P4	C 1600	
5906	25.0	DW-1572-0	13	B 81	P4	D 3000	
5907	25.0	DW-1572-0	15	B 72	P4	D 2200	Plate Volts = Low
5908	25.0	DW-1572-4	8	B 65	P4	D 1750	Plate Volts = Low
5910	1.4	BX-6230-0	19	B 42	P4	C 900	
5915	6.3	ET-7562-1	0	B 56	----	C 1200	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
5915	6.3	ET-1562-7	0	B 56	P4	C 1200	Osc. Sect.

5906	25.0	DW-1572-0	13	B 81	P4	D 3000	
5907	25.0	DW-1572-0	15	B 72	P4	D 2200	Plate Volts=Low
5908	25.0	DW-1572-4	8	B 65	P4	D 1750	Plate Volts=Low
5910	1.4	BX-6230-0	19	B 42	P4	C 900	
5915	6.3	ET-7562-1	0	B 56	C 1200	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
5915	6.3	ET-1562-7	0	B 56	P4	C 1200	Osc. Sect.
5916	25.0	DW-1572-4	20	B 63	P4	D 1600	Grid No. 1
5916	25.0	DW-4572-1	20	B 31	C 750	GRID NO. 3. HOLD DOWN P1 AND PRESS P4
5930	2.5	ER-3200-0	74	B 81	P4	D 3000	
5931	5.0	JS-0600-0	0	B 35	P3	-----	Plate No. 1
5931	5.0	JS-0400-0	0	B 30	P3	-----	Plate No. 2
5932	6.3	HS-5348-1	17	B 88	P4	E 5000	
5933	6.3	FR-3024-0	28	B 87	P4	D 3800	Cap=P
5963	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
5963	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
5964	6.3	ET-5207-6	21	B 85	P4	D 4000	Triode No. 1
5964	6.3	ET-6107-5	21	B 85	P4	D 4000	Triode No. 2
5965	12.6	EV-7608-1	15	B 89	P4	E 6500	Triode No. 1
5965	12.6	EV-2103-6	15	B 89	P4	E 6500	Triode No. 2
5967	1.1	ES-6801-3	18	B 48	P4	C 1000	TRIODE NO. 1 PLATE VOLTS=LOW
5967	1.1	ES-3108-6	18	B 48	P4	C 1000	TRIODE NO. 2 PLATE VOLTS=LOW
5971	1.1	FT-2100-0	20	B 64	P4	D 1500	
5975	6.3	EV-3102-0	29	B 86	P4	D 4000	
5977	6.3	DW-1805-3	30	B 86	P4	D 4000	
5987	6.3	DW-1205-0	39	B 70	P4	C 1850	Plate Volts=Low
5992	6.3	HS-5348-0	13	B 83	P4	D 3500	
5993	6.3	DX-0905-1	0	B 30	P3	-----	Plate No. 1
5993	6.3	DX-0105-9	0	B 30	P3	-----	Plate No. 2
5995	6.3	ET-0105-0	0	B 30	P3	-----	Leads-1-3-4-5
6005	6.3	ET-1562-0	18	B 84	P4	D 3700	
6007	1.1	DV-4120-0	25	A 20	P4	G 420	
6008	0.6	DV-4210-0	28	P4	G 100	OK above 60
6012	6.3	HS-3501-8	#	B 95	P5	-----	Strikes at about 30
6021	6.3	DW-7805-0	15	B 88	P4	E 5400	Triode No. 1
6021	6.3	DW-2104-0	15	B 88	P4	E 5400	Triode No. 2
6026	6.3	EV-7803-0	25	B 88	P4	D 4300	
6028	20.0	ET-1562-0	10	B 83	P4	D 4400	
6029	1.1	CU-3100-0	34	B 73	P4	C 2000	
6050	1.1	ES-3100-0	32	B 60	P4	D 1300	
6051	1.1	DV-4120-0	37	B 0	P4	G 550	Plate Volts=Low
6052	6.3	DW-0507-4	0	B 40	P3	-----	Plate No. 1
6052	6.3	DW-0102-4	0	B 40	P3	-----	Plate No. 2
6055	25.0	DW-1805-0	20	B 84	P4	D 3000	Plate Volts=Low
6056	25.0	DW-1572-0	15	B 72	P4	D 2200	Plate Volts=Low
6058	6.3	ET-0701-6	0	A 78	P1	-----	Diode No. 1
6058	6.3	ET-0205-6	0	A 78	P1	Diode No. 2
6072	12.6	EV-7608-0	15	B 67	P4	D 1750	Triode No. 1
6072	12.6	EV-2103-0	15	B 67	P4	D 1750	Triode No. 2
6073		See top of Chart					
6074		See top of Chart					
6080	7.5	HY-4506-2	55	B 86	P4	D 4000	TRIODE NO. 1 PLATE VOLTS=LOW
6080	7.5	HY-1203-5	55	B 86	P4	D 4000	TRIODE NO. 2 PLATE VOLTS=LOW
6082	25.0	HY-4506-2	55	B 86	P4	D 4000	TRIODE NO. 1 PLATE VOLTS=LOW
6082	25.0	HY-1203-5	55	B 86	P4	D 4000	TRIODE NO. 2 PLATE VOLTS=LOW
6084	6.3	EV-9613-8	15	B 71	P4	C 1850	
6085	12.6	EV-7608-0	17	B 80	P4	D 2700	Triode No. 1
6085	12.6	EV-2103-0	17	B 80	P4	D 2700	Triode No. 2
6086	20.0	EV-2613-9	10	B 89	P4	E 9000	
6087	5.0	JS-0600-0	0	A 40	P3	-----	Plate No. 1
6087	5.0	JS-0400-0	0	A 40	P3	-----	Plate No. 2

6085	12.6	EV-7608-0	17	B 80	P4	D 2700	Triode No. 1
6085	12.6	EV-2103-0	17	B 80	P4	D 2700	Triode No. 2
6086	20.0	EV-2613-9	10	B 89	P4	E 9000	
6087	5.0	JS-0600-0	0	A 40	P3	-----	Plate No. 1
6087	5.0	JS-0400-0	0	A 40	P3	-----	Plate No. 2
6088	1.1	DV-4120-0	19	A 42	P4	G 625	
6094	6.3	DV-1428-0	18	B 84	P4	D 3700	
6096	6.3	ET-1562-0	10	B 83	P4	D 4400	
6097	6.3	ET-0701-6	0	A 78	P1	-----	Diode No. 1
6097	6.3	ET-0205-6	0	A 78	P1	-----	Diode No. 2
6098	6.3	GY-7351-0	17	B 86	P4	E 5400	
6099	6.3	ET-5207-0	17	B 88	P4	E 5300	Triode No. 1
6099	6.3	ET-6107-0	17	B 88	P4	E 5300	Triode No. 2
6100	6.3	ET-6107-0	25	B 75	P4	C 2200	
6101	6.3	ET-5207-6	14	B 88	P4	E 6000	Triode No. 1
6101	6.3	ET-6107-5	14	B 88	P4	E 6000	Triode No. 2
6106	5.0	JS-0600-0	0	A 35	P3	-----	Plate No. 1
6106	5.0	JS-0400-0	0	A 35	P3	-----	Plate No. 2
6110	6.3	DW-0507-4	0	A 70	P1	-----	Diode No. 1
6110	6.3	DW-0102-4	0	A 70	P1	-----	Diode No. 2
6111	6.3	DW-7805-0	8	B 86	P4	E 5000	TRIODE NO. 1
6111	6.3	DW-2104-0	8	B 86	P4	E 5000	PLATE VOLTS=LOW
6112	6.3	DW-7805-0	15	B 75	P4	D 2500	TRIODE NO. 2
6112	6.3	DW-2104-0	15	B 75	P4	D 2500	PLATE VOLTS=LOW
6113	6.3	HY-4506-2	13	B 59	P4	D 1600	Triode No. 1
6113	6.3	HY-1203-5	13	B 59	P4	D 1600	Triode No. 2
6134	6.3	HS-4865-3	13	B 86	P4	E 6000	
6135	6.3	ET-6107-0	25	B 75	P4	C 2200	
6136	6.3	ET-1567-2	10	B 78	P4	D 3000	
6137	6.3	HS-4865-3	10	B 69	P4	D 2000	
6145	6.3	JR-6237-4	0	B 89	P4	E 6500	
6146	6.3	HS-5031-8	12	B 89	P4	E 7000	CAP=P.
6147	2.5	HR-8360-0	30	B 67	P4	C 1600	PLATE VOLTS=LOW
6152	6.3	EV-3102-0	29	B 86	P4	D 4000	
6159	25.0	HS-5031-8	12	B 89	P4	E 7000	CAP=P.
6169	6.3	DW-1204-0	13	B 84	P4	D 4000	PLATE VOLTS=LOW
6184	6.3	DW-0204-8	0	A 78	P1	-----	Diode No. 1
6184	6.3	DW-0705-8	0	A 78	P1	-----	Diode No. 2
6186	6.3	ET-1562-0	10	B 84	P4	D 4000	
6188	6.3	HY-4506-2	13	B 59	P4	D 1600	Triode No. 1
6188	6.3	HY-1203-5	13	B 59	P4	D 1600	Triode No. 2
6189	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
6189	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
6197	6.3	EV-2631-7	12	B 89	P4	E 7500	
6201	12.6	EV-7608-0	14	B 85	P4	D 4000	Triode No. 1
6201	12.6	EV-2103-0	14	B 85	P4	D 4000	Triode No. 2
6202	6.3	ET-0607-1	0	B 0	P3	-----	Plate No. 1
6202	6.3	ET-0107-6	0	B 0	P3	-----	Plate No. 2
6203	6.3	EV-0907-1	0	B 18	P3	-----	Plate No. 1
6203	6.3	EV-0107-9	0	B 18	P3	-----	Plate No. 2
6205	6.3	DW-1572-4	16	B 79	P4	D 3000	
6206	6.3	DW-1572-4	13	B 79	P4	D 3000	
6211	12.6	EV-7608-2	23	B 86	P4	D 3600	Triode No. 1
6211	12.6	EV-2103-7	23	B 86	P4	D 3600	Triode No. 2
6213	See Top of Chart						
6216	6.3	EV-2173-0	0	B 89	P4	E 9000	Plate Volts=Low
6221	6.3	DW-1805-0	20	B 85	P4	E 5800	
6222	6.3	DW-1805-0	21	B 34	P4	C 900	
6223	6.3	DW-1578-0	16	B 77	P4	D 3000	
6225	6.3	DW-1572-0	16	B 75	P4	D 3100	
6245	6.3	DW-1572-0	16	B 75	P4	D 3100	

6216	6.3	EV-2173-0	0	B 89	P4	E 9000	Plate Volts=Low
6221	6.3	DW-1805-0	20	B 85	P4	E 5800	
6222	6.3	DW-1805-0	21	B 34	P4	C 900	
6223	6.3	DW-1578-0	16	B 77	P4	D 3000	
6225	6.3	DW-1572-0	16	B 75	P4	D 3100	
6245	6.3	DU-7126-5	10	B 83	P4	D 4400	
6247	6.3	DW-2805-0	11	B 69	P4	D 2000	
6265	6.3	ET-1562-7	10	B 77	P4	D 2800	
6286	1.4	ES-3100-0	22	B 68	P4	C 1700	Plate Volts=Low
6293	6.3	HS-5031-0	0	B 88	P4	E 6500	CAP=P. PLATE VOLTS=LOW
6308	See top of Chart						
6332	See top of Chart						
6350	12.6	EV-8607-3	27	B 88	P4	E 4600	Triode No. 1
6350	12.6	EV-3102-8	27	B 88	P4	E 4600	Triode No. 2
6354	See top of Chart						
6355	6.3	FT-1427-0	0	B100	P4	-----	EYE 1 OPEN
6355	6.3	FT-4127-0	0	B100	P4	-----	EYE 2 CLOSED
6386	6.3	KR-7608-5	23	B 86	P4	D 4000	EYE 2 OPEN
6386	6.3	KR-3402-5	23	B 86	P4	D 4000	EYE 1 CLOSED
6397	2.5	HR-8360-0	29	B 72	P4	C 1950	Triode No. 1
6414	12.6	EV-7608-0	15	B 85	P4	E 5500	Triode No. 2
6414	12.6	EV-2103-0	15	B 85	P4	E 5500	Triode No. 1
6417	12.6	EV-9167-3	0	B 88	P4	E 7000	Triode No. 2
6418	1.4	DV-0204-1	0	B 0	P1	-----	OK ABOVE 350 ON 3000
6463	12.6	EV-8607-1	24	B 86	P4	E 5200	SCALE. MAKE NO GAS TEST
6463	12.6	EV-3102-6	24	B 86	P4	E 5200	Triode No. 1
6485	6.3	ET-1567-2	13	B 86	P4	E 6000	Triode No. 2
6519	1.4	DV-4120-0	20	A 24	P4	G 550	MAKE NO GAS TEST
6526	1.1	DV-4120-0	40	B 41	P4	C 900	
6533	6.3	GX-2105-0	21	B 43	P4	C 1000	
6540	6.3	DU-7126-5	10	B 83	P4	D 4400	
6542	See top of Chart						
6611	1.4	DV-0204-1	0	B 0	P1	-----	OK ABOVE 600 ON 3000
6612	1.4	DV-0204-1	0	A 45	P1	-----	SCALE. MAKE NO GAS TEST
6626	See top of Chart						
6627	See top of Chart						
6660	6.3	ET-1567-2	0	B 79	P4	D 3200	
6661	6.3	ET-1562-7	10	B 77	P4	D 2800	
6662	6.3	ET-1562-7	10	B 75	P4	C 2500	
6663	6.3	ET-0701-6	0	A 78	P1	-----	Diode No. 1
6663	6.3	ET-0205-6	0	A 78	P1	-----	Diode No. 2
6669	6.3	ET-1562-0	18	B 84	P4	D 3700	
6676	6.3	ET-1562-7	10	B 86	P4	D 4500	
6677	6.3	EV-2631-7	12	B 89	P4	E 7500	
6678	6.3	EV-2637-0	12	B 78	P4	D 3000	Pent. Sect.
6678	6.3	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
6679	12.6	EV-7608-0	14	B 85	P4	D 4000	Triode No. 1
6679	12.6	EV-2103-0	14	B 85	P4	D 4000	Triode No. 2
6680	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
6680	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
6681	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
6681	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
6688	6.3	EV-2791-8	8	B 89	P4	E 9500	
6690	6.3	DW-7508-0	13	B 88	P4	E 4800	Triode No. 1
6690	6.3	DW-2104-0	13	B 88	P4	E 4800	Triode No. 2
6754	6.3	EV-0907-0	0	B 45	P3	-----	Plate No. 1
6754	6.3	EV-0103-0	0	B 45	P3	-----	Plate No. 2
6788	6.3	DW-1572-0	17	B 38	P4	C 800	
6814	6.3	DW-1805-0	24	B 87	P4	D 4200	
6829	12.6	EV-7608-0	15	B 89	P4	E 6700	Triode No. 1
6829	12.6	EV-2103-0	15	B 89	P4	E 6700	Triode No. 2

6814	6.3	DW-1805-0	24	B 87	P4	C 4200	
6829	12.6	EV-7608-0	15	B 89	P4	E 6700	Triode No. 1
6829	12.6	EV-2103-0	15	B 89	P4	E 6700	Triode No. 2
6832	6.3	DW-7805-0	27	B 49	P4	C 1050	Triode No. 1
6832	6.3	DW-2104-0	27	B 49	P4	C 1050	Triode No. 2
6872	6.3	DU-7126-5	15	B 77	P4	C 2350	
6877	6.3	DV-1408-0	62	B 90	P4	D 4000	
6883	6.3	HS-5031-8	12	B 89	P4	E 7000	CAP-P. PLATE VOLTS=LOW.
6887	6.3	ET-0701-0	0	A 78	P1	Diode No. 1
6887	6.3	ET-0205-0	0	A 78	P1	Diode No. 2
6888	6.3	HS-4865-3	37	B 75	P4	C 2100	
6889	6.3	GY-7051-0	17	B 86	P4	E 5400	Cap-P
6919	6.3	ET-0701-6	0	A 78	P1	Diode No. 1
6919	6.3	ET-0205-6	0	A 78	P1	Diode No. 2
6943	6.3	DW-1572-4	11	B 77	P4	D 3100	
6944	6.3	DW-1572-4	9	B 77	P4	D 3100	
6945	6.3	DW-1572-0	44	B 81	P4	D 2900	
6946	6.3	DW-1805-0	27	B 82	P4	D 3800	
6947	6.3	DW-7805-0	17	B 81	P4	D 4000	Triode No. 1
6947	6.3	DW-2104-0	17	B 81	P4	D 4000	Triode No. 2
6948	6.3	DW-7805-0	16	B 72	P4	D 2000	Triode No. 1
6948	6.3	DW-2104-0	16	B 72	P4	D 2000	Triode No. 2
6954	6.3	ET-1562-7	10	B 73	P4	C 2000	
6973	6.3	EV-3917-0	14	B 87	P4	E 4800	
7000	6.3	HS-0348-5	21	B 57	P4	C 1225	Cap-G
7025	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
7025	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
7027	6.3	HS-5318-0	17	B 88	P4	E 5000	
7036	6.3	ET-7562-1	0	B 56	C 1200	AMPL. SECT. HOLD DOWN P1 AND PRESS P4
7036	6.3	ET-1562-7	0	B 56	P4	C 1200	Osc. Sect.
7044	12.6	EV-7906-0	28	B 90	P4	E 7500	Triode No. 1
7044	12.6	EV-2103-0	28	B 90	P4	E 7500	Triode No. 2
7054	12.6	EV-2781-3	0	B 88	P4	E 8000	
7055	12.6	ET-0701-6	0	A 78	P1	Diode No. 1
7055	12.6	ET-0205-6	0	A 78	P1	Diode No. 2
7056	12.6	ET-1562-7	10	B 86	P4	D 4500	
7057	12.6	EV-7608-9	17	B 89	P4	E 6800	Triode No. 1
7057	12.6	EV-2103-9	17	B 89	P4	E 6800	Triode No. 2
7058	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
7058	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
7059	12.6	EV-2637-0	12	B 78	P4	D 3000	Pent. Sect.
7059	12.6	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
7060	12.6	EV-8679-0	11	B 84	P4	D 4600	Pent. Sect.
7060	12.6	EV-2103-0	16	B 83	P4	D 3900	Triode Sect.
7061	12.6	EV-3917-0	18	B 84	P4	D 3700	
7119	12.6	EV-7906-0	17	B 92	P4	F15500	Triode No. 1
7119	12.6	EV-2103-0	17	B 92	P4	F15500	Triode No. 2
7137	6.3	ET-1702-0	15	B 89	P4	F11000	
7167	12.6	ET-1562-0	12	B 84	D 3300	HOLD DOWN P1 AND PRESS P4
7189	6.3	EV-2793-0	12	B 89	P4	E 9000	
7199	6.3	EV-7236-0	7	B 84	P4	E 6000	Pent. Sect.
7199	6.3	EV-9108-0	29	B 74	P4	C 2100	Triode Sect.
7212	6.3	HS-5031-8	12	B 89	P4	E 7000	CAP-P. PLATE VOLTS=LOW
7233	6.3	EV-2908-0	40	B 91	P4	F17500	Plate Volts=Low
7247	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
7247	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
7258	12.6	EV-8679-1	10	B 83	P4	E 6000	Pent. Sect.
7258	12.6	EV-2173-6	21	B 84	P4	D 4400	Triode Sect.
7316	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
7316	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
7355	6.3	HS-6385-0	10	B 91	P4	E 7600	

7316	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
7316	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
7355	6.3	HS-6385-0	10	B 91	P4	E 7600	
7358	6.3	HS-5031-8	12	B 89	P4	E 7000	CAP-P. PLATE VOLTS=LOW (CONNECT PIN 1 TO PIN 8 AND PIN 6 TO PIN 7 ON LOctal SOCKET
7360	6.3	EV-3621-9	13	B 70	P4	C 1250	
7370	20.0	FY-7906-0	28	B 89	P4	E 7500	Triode No. 1
7370	20.0	JU-2103-0	28	B 89	P4	E 7500	Triode No. 2
7408	6.3	HS-5348-1	18	B 84	P4	D 3700	
7543	6.3	ET-1567-2	10	B 78	P4	D 3000	
7551	12.6	EV-2631-7	23	B 86	P4	E 6000	
7558	6.3	EV-2631-7	23	B 86	P4	E 6000	
7581	6.3	HS-5348-0	17	B 88	P4	E 5900	
7586	6.3	DR-4208-0	15	B 90	P4	E 9750	[PLATE VOLTS=LOW USE HICKOK ADAPTER CODE NO. 1050-127
7587	6.3	DR-4028-0	10	B 84	----	E 7000	CAP-P. HOLD DOWN P1 AND PRESS P4 USE HICKOK ADAPTER CODE NO. 1050 127
7591	6.3	HS-6345-0	10	B 89	P4	E 7900	
7687	6.3	EV-2637-0	10	B 83	P4	D 3500	Pent. Sect.
7687	6.3	EV-9108-0	28	B 78	P4	D 2700	Triode Sect.
7695	50.0	EV-6917-0	34	B 94	P4	E 7000	
7700	6.3	GR-0235-4	21	B 57	P4	C 1225	Cap-G
7701	12.6	EV-2691-0	10	B 83	P4	D 3400	
7716	12.6	EV-7986-0	10	B 87	P4	E 7250	Pent. Sect.
7716	12.6	EV-2301-0	10	B 61	P4	D 2900	Triode Sect.
7717	6.3	ET-1562-0	12	B 84	..	D 4000	HOLD DOWN P1 AND PRESS P4
7719	12.6	EV-2103-0	32	B 82	P4	D 3000	
7724	12.6	EV-8907-0	10	B 38	P4	C 800	Triode Sect.
7724	12.6	EV-0601-0	0	A 78	P1	-----	Diode No. 1
7724	12.6	EV-0203-0	0	A 78	P1	-----	Diode No. 2
7728	12.6	EV-7608-0	14	B 85	P4	D 4000	Triode No. 1
7728	12.6	EV-2103-0	14	B 85	P4	D 4000	Triode No. 2
7729	12.6	EV-7608-0	14	B 48	P4	D 1250	Triode No. 1
7729	12.6	EV-2103-0	14	B 48	P4	D 1250	Triode No. 2
7730	12.6	EV-7608-0	25	B 75	P4	C 2200	Triode No. 1
7730	12.6	EV-2103-0	25	B 75	P4	C 2200	Triode No. 2
7731	6.3	EV-2637-0	12	B 78	P4	D 3000	Pent. Sect.
7731	6.3	EV-9108-0	10	B 89	P4	E 8500	Triode Sect.
7732	6.3	ET-1562-7	10	B 86	P4	D 4500	
7733	12.6	EV-2781-3	0	B 88	P4	E 8000	
7734	6.3	EV-8917-0	14	B 71	P4	D 2300	Pent. Sect.
7734	6.3	EV-3602-0	63	B 89	P4	E 6200	Triode Sect.
7738	6.3	ET-2105-0	13	B 88	P4	E 7500	
7754	6.3	EV-6917-0	34	B 94	P4	E 7000	
7759	25.0	DW-7805-0	15	B 88	P4	E 5400	Triode No. 1
7759	25.0	DW-2104-0	15	B 88	P4	E 5400	Triode No. 2
7760	25.0	DW-7805-0	20	B 84	P4	D 3000	TRIODE NO. 1 PLATE VOLTS=LOW.
7760	25.0	DW-2104-0	20	B 84	P4	D 3000	TRIODE NO. 2 PLATE VOLTS=LOW.
7761	25.0	DW-1572-0	15	B 87	P4	E 5500	
7762	25.0	DW-1572-0	40	B 86	P4	D 4200	
7802	6.3	HY-4506-2	45	B 91	P4	F16000	Triode No. 1
7802	6.3	HY-1203-5	45	B 91	P4	F16000	Triode No. 2
7803	6.3	EV-7608-0	20	B 91	P4	E12500	Triode No. 1
7803	6.3	EV-2103-0	20	B 91	P4	E12500	Triode No. 2
7861	12.6	KR-7608-0	16	B 88	P4	E 5000	Triode No. 1
7861	12.6	KR-3402-0	16	B 88	P4	E 5000	Triode No. 2
7867	6.3	HS-5083-0	23	B 92	..	E 9000	CAP-P. HOLD DOWN P1 AND PRESS P4.
7868	6.3	EV-2973-0	10	B 90	P4	E 8500	USE HICKOK ADAPTER CODE NO. 1050-144
7889	25.0	DW-7805-0	15	B 75	P4	D 2500	Triode No. 1
7889	25.0	DW-2104-0	15	B 75	P4	D 2500	Triode No. 2
7895	6.3	DR-4208-0	16	B 89	P4	E 8950	USE HICKOK ADAPTER

7867	6.3	HS-5083-0	23	B 92	----	E 9000	CAP=P HOLD DOWN P1 AND PRESS P4.
7868	6.3	EV-2973-0	10	B 90	P4	E 8500	USE HICKOK ADAPTER CODE NO. 1050-144
{ 7889	25.0	DW-7805-0	15	B 75	P4	D 2500	Triode No. 1
{ 7889	25.0	DW-2104-0	15	B 75	P4	D 2500	Triode No. 2
7895	6.3	DR-4208-0	16	B 89	P4	E 8250	USE HICKOK ADAPTER CODE NO. 1050-127
{ 7898	12.6	EV-7608-0	11	B 86	P4	E 7500	Triode No. 1
{ 7898	12.6	EV-2103-0	11	B 86	P4	E 7500	Triode No. 2
7905	6.3	KR-2680-7	17	B 88	P4	E 5000	
8013A	3.0	FR-0000-0	0	B 82	P5	-----	Cap=P
8016	1.1	HS-0000-0	0	A 80	P5	-----	Cap=P
8032	12.6	HS-5031-8	12	B 89	P4	E 7000	CAP=P PLATE VOLTS-LOW
8056	6.3	DR-0208-4	0	B 70	P1	-----	USE HICKOK ADAPTER CODE NO. 1050-127, OK ABOVE 1300 ON 1000 SCALE.
8058	6.3	DR-0002-0	13	B 89	P4	E10000	MAKE NO GAS TEST.
8077	12.6	EV-2781-3	0	B 88	P4	E 8000	CAP=P, G-SHELL.
{ 8102	12.6	EV-9678-0	11	B 81	P4	D 4000	USE HICKOK ADAPTER CODE NO. 1050-127
{ 8102	12.6	EV-3102-0	13	B 88	P4	E 8500	Pent. Sect.
8106	12.6	EV-7189-0	14	B 85	P4	E 8000	Triode Sect.
8185	6.3	JR-2306-0	19	A 88	P4	F18000	
8186	25.0	JR-2306-0	19	A 88	P4	F18000	
8334	6.3	ET-6705-0	12	A 80	P4	E12000	
9001	6.3	ET-1567-0	20	B 53	P4	C 1100	
9002	6.3	ET-6107-0	25	B 72	P4	C 1900	
9003	6.3	ET-1562-0	12	B 64	P4	C 1500	
9004	6.3	GR-0304-0	0	A 78	P1	-----	Diode
9005	4.3	GR-0403-0	0	A 65	P1	-----	Diode
9006	6.3	ET-0107-0	0	A 65	P1	-----	Diode

STOP

10-1-63

TUBE TESTER

K4XL's **BAMA**

This manual is provided **FREE OF CHARGE** from the “BoatAnchor Manual Archive” as a service to the Boatanchor community.

It was uploaded by someone who wanted to help you repair and maintain your equipment.

If you paid anyone other than BAMA for this manual, you paid someone who is making a profit from the free labor of others without asking their permission.

You may pass on copies of this manual to anyone who needs it. But do it without charge.

Thousands of files are available without charge from BAMA. Visit us at <http://bama.sbc.edu>